

# USER'S MANUAL

*notebook*



## Notice

The company reserves the right to revise this publication or to change its contents without notice. Information contained herein is for reference only and does not constitute a commitment on the part of the manufacturer or any subsequent vendor. They assume no responsibility or liability for any errors or inaccuracies that may appear in this publication nor are they in anyway responsible for any loss or damage resulting from the use (or misuse) of this publication.

This publication and any accompanying software may not, in whole or in part, be reproduced, translated, transmitted or reduced to any machine readable form without prior consent from the vendor, manufacturer or creators of this publication, except for copies kept by the user for backup purposes.

Brand and product names mentioned in this publication may or may not be copyrights and/or registered trademarks of their respective companies. They are mentioned for identification purposes only and are not intended as an endorsement of that product or its manufacturer.

©June 2009

## Trademarks

This product incorporates copyright protection technology that is protected by method claims of certain U.S. patents and other intellectual property rights owned by Macrovision Corporation and other rights owners. Use of this copyright protection technology must be authorized by Macrovision Corporation, and is intended for home or other limited viewing uses only unless otherwise authorized by Macrovision Corporation. Reverse engineering or disassembly is prohibited.

**Intel**, **Celeron**, and **Intel Core** are trademarks/registered trademarks of Intel Corporation.

### **FCC Statement (Federal Communications Commission)**

You are cautioned that changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Re orient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the service representative or an experienced radio/TV technician for help.

#### **Operation is subject to the following two conditions:**

1. This device may not cause interference.

And

2. This device must accept any interference, including interference that may cause undesired operation of the device.

## FCC RF Radiation Exposure Statement:

1. This Transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.
2. This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of 20 centimeters between the radiator and your body.



### Warning

Use only shielded cables to connect I/O devices to this equipment. You are cautioned that changes or modifications not expressly approved by the manufacturer for compliance with the above standards could void your authority to operate the equipment.

If your purchase option includes both **Wireless LAN** and **3.75G** modules, then the appropriate antennas will be installed. Note that In order to comply with FCC RF exposure compliance requirements, the antenna must not be co-located or operate in conjunction with any other antenna or transmitter.

### **IMPORTANT SAFETY INSTRUCTIONS**

Follow basic safety precautions, including those listed below, to reduce the risk of fire, electric shock, and injury to persons when using any electrical equipment:

1. Do not use this product near water, for example near a bath tub, wash bowl, kitchen sink or laundry tub, in a wet basement or near a swimming pool.
2. Avoid using this equipment with a telephone line (other than a cordless type) during an electrical storm. There may be a remote risk of electrical shock from lightning.
3. Do not use the telephone to report a gas leak in the vicinity of the leak.
4. Use only the power cord and batteries indicated in this manual. Do not dispose of batteries in a fire. They may explode. Check with local codes for possible special disposal instructions.
5. This product is intended to be supplied by a Listed Power Unit with an AC Input of 100 - 240V, 50 - 60Hz, DC Output of 19V, 3.42A OR 18.5V, 3.5A (65 Watts) minimum AC/DC Adapter.

**This Computer's Optical Device is a Laser Class 1 Product**

## Instructions for Care and Operation

The computer is tough, but it can be damaged. To prevent this, follow these suggestions:

1. **Don't drop it, or expose it to shock.** the tough magnesium alloy case and shock mounted design will help the computer resist shocks, bumps and small drops but If the computer falls, the case and the components could still be damaged so try and this situation.
  - *Do not place it on an unstable surface.*
  - *Do not place anything heavy on the computer*
2. **Keep it dry, and don't overheat it.** Keep the computer and power supply away from any kind of heating element. The computer is spill resistant, but as with any electrical appliance, contact with water is to be avoided.
  - *Do not expose it to excessive heat.*
  - *Do not leave it in a place where foreign matter or moisture may affect the system.*
  - *Don't store the computer in a humid environment.*
3. **Avoid interference.** Keep the computer away from high capacity transformers, electric motors, and other strong magnetic fields. These can hinder proper performance and damage your data.
4. **Follow the proper working procedures for the computer.** Shut the computer down properly and don't forget to save your work. Remember to periodically save your data as data may be lost if the battery is depleted
  - *Do not turn off the power until you properly shut down all programs.*
  - *Do not turn off any peripheral devices when the computer is on.*
  - *Do not disassemble the computer by yourself.*
  - *Perform routine maintenance on your computer.*
5. **Take care when using peripheral devices.**
  - *Use only approved brands of peripherals.*
  - *Unplug the power cord before attaching peripheral devices.*

### Power Safety

The computer has specific power requirements:



#### Power Safety Warning


Before you undertake any upgrade procedures, make sure that you have turned off the power, and disconnected all peripherals and cables (including telephone lines). It is advisable to also remove your battery in order to prevent accidentally turning the machine on.

- Only use a power adapter approved for use with this computer.
- Your AC/DC adapter may be designed for international travel but it still requires a steady, uninterrupted power supply. If you are unsure of your local power specifications, consult your service representative or local power company.
- The power adapter may have either a 2-prong or a 3-prong grounded plug. The third prong is an important safety feature; do not defeat its purpose. If you do not have access to a compatible outlet, have a qualified electrician install one.
- When you want to unplug the power cord, be sure to disconnect it by the plug head, not by its wire.
- Make sure the socket and any extension cord(s) you use can support the total current load of all the connected devices.
- Before cleaning the computer, make sure it is disconnected from any external power supplies (i.e. AC/DC adapter or car adapter).


*Do not plug in the power cord if you are wet.*



*Do not use the power cord if it is broken.*



*Do not place heavy objects on the power cord.*



## Battery Precautions

- Only use batteries designed for this computer. The wrong battery type may explode, leak or damage the computer.
- Do not remove any batteries from the computer while it is powered on.
- Do not continue to use a battery that has been dropped, or that appears damaged (e.g. bent or twisted) in any way. Even if the computer continues to work with a damaged battery in place, it may cause circuit damage, which may possibly result in fire.
- Recharge the batteries using the notebook's system. Incorrect recharging may make the battery explode.
- Do not try to repair a battery pack. Refer any battery pack repair or replacement to your service representative or qualified service personnel.
- Keep children away from, and promptly dispose of a damaged battery. Always dispose of batteries carefully. Batteries may explode or leak if exposed to fire, or improperly handled or discarded.
- Keep the battery away from metal appliances.
- Affix tape to the battery contacts before disposing of the battery.
- Do not touch the battery contacts with your hands or metal objects.



### Battery Disposal & Caution

The product that you have purchased contains a rechargeable battery. The battery is recyclable. At the end of its useful life, under various state and local laws, it may be illegal to dispose of this battery into the municipal waste stream. Check with your local solid waste officials for details in your area for recycling options or proper disposal.

Danger of explosion if battery is incorrectly replaced. Replace only with the same or equivalent type recommended by the manufacturer. Discard used battery according to the manufacturer's instructions.

## Preface

### Cleaning

Do not apply cleaner directly to the computer; use a soft clean cloth.

Do not use volatile (petroleum distillates) or abrasive cleaners on any part of the computer.

### Servicing

Do not attempt to service the computer yourself. Doing so may violate your warranty and expose you and the computer to electric shock. Refer all servicing to authorized service personnel. Unplug the computer from the power supply. Then refer servicing to qualified service personnel under any of the following conditions:

- When the power cord or AC/DC adapter is damaged or frayed.
- If the computer has been exposed to rain or other liquids.
- If the computer does not work normally when you follow the operating instructions.
- If the computer has been dropped or damaged (do not touch the poisonous liquid if the LCD panel breaks).
- If there is an unusual odor, heat or smoke coming from your computer.



#### Removal Warning

When removing any cover(s) and screw(s) for the purposes of device upgrade, remember to replace the cover(s) and screw(s) before turning the computer on.

## Travel Considerations

### Packing

As you get ready for your trip, run through this list to make sure the system is ready to go:

1. Check that the battery pack and any spares are fully charged.
2. Power off the computer and peripherals.
3. Close the display panel and make sure it's latched.
4. Disconnect the AC/DC adapter and cables. Stow them in the carrying bag.
5. The AC/DC adapter uses voltages from 100 to 240 volts so you won't need a second voltage adapter. However, check with your travel agent to see if you need any socket adapters.
6. Put the notebook in its carrying bag and secure it with the bag's straps.
7. If you're taking any peripherals (e.g. a printer, mouse or digital camera), pack them and those devices' adapters and/or cables.
8. Anticipate customs - Some jurisdictions may have import restrictions or require proof of ownership for both hardware and software. Make sure your documents are prepared.



#### Power Off Before Traveling

Make sure that your notebook is completely powered off before putting it into a travel bag (or any such container). Putting a notebook which is powered on in a travel bag may cause the vent(s)/fan intake(s)/outlet(s) to be blocked. To prevent your computer from overheating make sure nothing blocks the vent(s)/fan intake(s)/outlet(s) while the computer is in use.

### On the Road

In addition to the general safety and maintenance suggestions in this preface, and Chapter 8: Troubleshooting, keep these points in mind:

**Hand-carry the notebook** - For security, don't let it out of your sight. In some areas, computer theft is very common. Don't check it with normal luggage. Baggage handlers may not be sufficiently careful. Avoid knocking the computer against hard objects.

**Beware of Electromagnetic fields** - Devices such as metal detectors & X-ray machines can damage the computer, hard disk, floppy disks, and other media. They may also destroy any stored data - Pass your computer and disks around the devices. Ask security officials to hand-inspect them (you may be asked to turn it on). **Note:** Some airports also scan luggage with these devices.

**Fly safely** - Most airlines have regulations about the use of computers and other electronic devices in flight. These restrictions are for your safety, follow them. If you stow the notebook in an overhead compartment, make sure it's secure. Contents may shift and/or fall out when the compartment is opened.

**Get power where you can** - If an electrical outlet is available, use the AC/DC adapter and keep your battery(ies) charged.

**Keep it dry** - If you move quickly from a cold to a warm location, water vapor can condense inside the computer. Wait a few minutes before turning it on so that any moisture can evaporate.

## Developing Good Work Habits

Developing good work habits is important if you need to work in front of the computer for long periods of time. Improper work habits can result in discomfort or serious injury from repetitive strain to your hands, wrists or other joints. The following are some tips to reduce the strain:

- Adjust the height of the chair and/or desk so that the keyboard is at or slightly below the level of your elbow. Keep your forearms, wrists, and hands in a relaxed position.
- Your knees should be slightly higher than your hips. Place your feet flat on the floor or on a footrest if necessary.
- Use a chair with a back and adjust it to support your lower back comfortably.
- Sit straight so that your knees, hips and elbows form approximately 90-degree angles when you are working.
- Take periodic breaks if you are using the computer for long periods of time.



### Remember to:

- Alter your posture frequently.
- Stretch and exercise your body several times a day.
- Take periodic breaks when you work at the computer for long periods of time. Frequent and short breaks are better than fewer and longer breaks.



### Lighting

Proper lighting and comfortable display viewing angle can reduce eye strain and muscle fatigue in your neck and shoulders.

- Position the display to avoid glare or reflections from overhead lighting or outside sources of light.
- Keep the display screen clean and set the brightness and contrast to levels that allow you to see the screen clearly.
- Position the display directly in front of you at a comfortable viewing distance.
- Adjust the display-viewing angle to find the best position.

### LCD Screen Care

To prevent **image persistence** on LCD monitors (caused by the continuous display of graphics on the screen for an extended period of time) take the following precautions:

- Set the *Windows* **Power Plans** to turn the screen off after a few minutes of screen idle time.
- Use a rotating, moving or blank screen saver (this prevents an image from being displayed too long).
- Rotate desktop background images every few days.
- Turn the monitor off when the system is not in use.

## Contents

Notice .....	I	Keyboard .....	1-10
FCC Statement .....	II	Function Keys & Visual Indicators .....	1-11
FCC RF Radiation Exposure Statement: .....	III	System Map: Front & Rear Views .....	1-12
Instructions for Care and Operation .....	V	System Map: Left View .....	1-13
Power Safety .....	VI	System Map: Right View .....	1-14
Battery Precautions .....	VII	System Map: Bottom View .....	1-15
Cleaning .....	VIII	Windows Vista Start Menu & Control Panel .....	1-16
Servicing .....	VIII	Video Features .....	1-17
Travel Considerations .....	IX	Display Devices & Options .....	1-17
		Power Options .....	1-19

## Quick Start Guide

Overview .....	1-1
Introduction .....	1-2
LED Backlight LCD .....	1-2
Advanced Users .....	1-3
Beginners and Not-So-Advanced Users .....	1-3
Warning Boxes .....	1-3
Not Included .....	1-4
System Software .....	1-5
System Startup .....	1-6
Operating System Setup .....	1-7
System Map: LCD Panel Open .....	1-8
LED Indicators .....	1-9

## Features & Components

Overview .....	2-1
Hard Disk Drive/Solid State Drive .....	2-2
Optical (CD/DVD) Device .....	2-3
Loading Discs .....	2-3
Handling CDs or DVDs .....	2-4
DVD Regional Codes .....	2-5
7-in-1 Card Reader .....	2-6
ExpressCard Slot .....	2-7
Inserting and Removing ExpressCards .....	2-7
Touchpad and Buttons/Mouse .....	2-8
Audio Features .....	2-9

## Preface

Adding a Printer .....	2-10
USB Printer .....	2-10
Parallel Printer .....	2-10

## Power Management

Overview .....	3-1
The Power Sources .....	3-2
AC/DC Adapter .....	3-2
Battery .....	3-2
Turning on the Computer .....	3-3
Power Plans .....	3-4
Power-Saving States .....	3-6
Sleep .....	3-6
Hibernate .....	3-7
Shut Down .....	3-7
Configuring the Power Buttons .....	3-8
Resuming Operation .....	3-9
Battery Information .....	3-10
Battery Power .....	3-10
Conserving Battery Power .....	3-11
Battery Life .....	3-12
New Battery .....	3-12
Recharging the Battery with the AC/DC Adapter .....	3-12
Proper handling of the Battery Pack .....	3-13
Battery FAQ .....	3-14

## Drivers & Utilities

What to Install .....	4-1
Module Driver Installation .....	4-1
Driver Installation .....	4-2
Updating/Reinstalling Individual Drivers .....	4-4
User Account Control (Win Vista) .....	4-4
Windows Security Message .....	4-4
New Hardware Found .....	4-4
Driver Installation Procedure .....	4-5
Chipset .....	4-5
Video .....	4-5
LAN .....	4-5
Card Reader .....	4-5
Touchpad .....	4-5
Trusted Platform Module (TPM) .....	4-6
Fingerprint Reader .....	4-6
Hot Key Utility .....	4-6
PC Camera (Optional) .....	4-6
Audio .....	4-7
Optional Drivers .....	4-8
Bluetooth Module .....	4-8
Wireless LAN Module .....	4-8
3.75G/HSPA Module .....	4-8

## BIOS Utilities

Overview .....	5-1
The Power-On Self Test (POST) .....	5-2
Failing the POST .....	5-3
Fatal Errors .....	5-3
Non-Fatal Errors .....	5-3
The Setup Program .....	5-4
Entering Setup .....	5-4
Setup Screens .....	5-5
Main Menu .....	5-6
System Time & Date (Main Menu) .....	5-6
SATA Port1/2 (Main Menu) .....	5-7
System/Extended Memory: (Main Menu) .....	5-7
Advanced Menu .....	5-8
SIO ITE8305E Configuration (Advanced Menu) .....	5-8
Installed O/S (Advanced Menu) .....	5-9
Legacy USB Support: (Advanced Menu) .....	5-9
Boot-time Diagnostic Screen (Advanced Menu) .....	5-9
Legacy OS Boot (Advanced Menu) .....	5-9
Reset Configuration Data (Advanced Menu) .....	5-10
Power On Boot Beep (Advanced Menu) .....	5-10
Battery Low Alarm Beep (Advanced Menu) .....	5-10
Fan Control (Advanced Menu) .....	5-10
Power Conserve Mode (Advanced Menu) .....	5-10
Security Menu .....	5-11

Set Supervisor Password (Security Menu) .....	5-11
Set User Password (Security Menu) .....	5-12
Fixed disk boot sector (Security Menu) .....	5-12
Password on boot (Security Menu) .....	5-12
TPM Support (Security Menu) .....	5-13
TPM State .....	5-14
Change TPM State (TPM State) .....	5-14
Boot Menu .....	5-16
Exit Menu .....	5-17

## Upgrading The Computer

Overview .....	6-1
When Not to Upgrade .....	6-2
Removing the Battery .....	6-3
Upgrading the Hard Disk Drive .....	6-4
Upgrading the Optical (CD/DVD) Device .....	6-7
Upgrading the System Memory (RAM) .....	6-9
What to do if you Spill Liquid on the Computer .....	6-11

## Modules & Options

Overview .....	7-1
Bluetooth Module .....	7-2
Bluetooth Configuration in Windows Vista .....	7-3
Security Modules (TPM & Fingerprint) .....	7-6
Trusted Platform Module .....	7-7

## Preface

Enabling & Activating TPM .....	7-7
Initializing TPM .....	7-9
Infineon Security Platform Settings Tool .....	7-12
Fingerprint Reader Module .....	7-13
User Enrollment .....	7-14
Fingerprint Control Center Features .....	7-18
PC Camera Module .....	7-19
Wireless LAN Module .....	7-26
802.11 b/g WLAN Driver Installation .....	7-27
Intel® Wi-Fi Link 5100/5300 Series (802.11 a/g/n) Driver Installation .....	7-27
Intel® My WiFi Installation & Configuration .....	7-31
Intel® Wi-Fi Link 5100/5300 Series My WiFi Driver Installation .....	7-32
3.75G/HSPA Module .....	7-44
USIM Card Installation .....	7-46
3G Watcher Application .....	7-48
3G Watcher Application Installation .....	7-48
Setting Up a Carrier Profile .....	7-49
Short Messaging Service .....	7-54
HSPA Modem .....	7-55
HSPA Modem Interface Installation .....	7-55
HSPA Modem Interface .....	7-56
Adding a Profile .....	7-58
Contacts .....	7-60

Messages .....	7-61
Settings .....	7-62
Mobile Partner .....	7-64
Mobile Partner Application Installation .....	7-64
Mobile Partner Application .....	7-65
Profile Management .....	7-65
GPS Module .....	7-69

## Troubleshooting

Overview .....	8-1
Basic Hints and Tips .....	8-2
Backup and General Maintenance .....	8-3
Viruses .....	8-4
Upgrading and Adding New Hardware/Software .....	8-5
Problems and Possible Solutions .....	8-7
Screen Resolution Error .....	8-13

## Interface (Ports & Jacks)

Notebook Ports and Jacks .....	A-2
--------------------------------	-----

## Intel Video Driver Controls

Intel Video Driver Installation .....	B-1
Video .....	B-1
Dynamic Video Memory Technology .....	B-1
Intel Graphics Properties .....	B-2

Scheme Options ..... B-4  
 Attaching Other Displays ..... B-5  
 Display Modes ..... B-7

**Windows XP Information**

DVD Regional Codes ..... D-2  
 Windows XP Start Menu & Control Panel ..... D-3  
 Touchpad and Buttons/Mouse ..... D-4  
 Function Keys & Visual Indicators ..... D-5  
 Audio Features ..... D-6  
 Video Features ..... D-7  
 Intel GMA Driver Controls ..... D-9  
 Power Management Features ..... D-16  
 The Power Sources ..... D-17  
 Turning on the Computer ..... D-18  
 Power Schemes ..... D-19  
 System Power Options ..... D-21  
 Configuring the Power Button ..... D-23  
 Battery Information ..... D-24  
 Driver Installation ..... D-28  
     Driver Installation Procedure ..... D-30  
 Bluetooth Module ..... D-35  
 Security Modules (TPM & Fingerprint) ..... D-40  
 Trusted Platform Module ..... D-41  
     Enabling & Activating TPM ..... D-41

    Initializing TPM ..... D-43  
     Infineon Security Platform Settings Tool ..... D-46  
 Fingerprint Reader Module ..... D-47  
 PC Camera Module ..... D-53  
 WLAN Module ..... D-59  
 3.75G/HSPA Module ..... D-62



# Chapter 1: Quick Start Guide

## Overview

This Quick Start Guide is a brief introduction to the basic features of your computer, to navigating around the computer and to getting your system started. The remainder of the manual covers the following:

- **Chapter 2** A guide to using some of the main features of the computer e.g. the **storage devices (hard disk, optical device, 7-in-1 card reader, ExpressCard/34/54), Touchpad & Mouse, Audio Features, Tablet PC Options & Printer.**
- **Chapter 3** The computer's **power** saving options.
- **Chapter 4** The installation of the **drivers** and utilities essential to the operation or improvement of some of the computer's subsystems.
- **Chapter 5** An outline of the computer's built-in software or **BIOS** (Basic Input Output System).
- **Chapter 6** Instructions for **upgrading** your computer.
- **Chapter 7** A quick guide to the computer's **Bluetooth, Wireless LAN, PC Camera, Fingerprint** and **3.75G** modules (some of which may be **optional** depending on your purchase configuration).
- **Chapter 8** A **troubleshooting** guide.
- **Appendix A** Definitions of the **interface, ports/jacks** which allow your computer to communicate with external devices.
- **Appendix B** Information on the **Intel Video driver controls.**
- **Appendix C** The computer's **specifications.**
- **Appendix D** Information on the **Windows XP OS.**

## Introduction

This wide screen tough notebook computer provides an ideal platform for mobile computer use with a magnesium alloy case to help provide resistance to shocks, bump and drops, an anti-shock mounting design to protect the hard disk and LCD screen from damage and a spill resistant keyboard (water resistant to 100cc) and case design preventing spills (see *“What to do if you Spill Liquid on the Computer”* on page 6 - 11 for details) from leaking into the sensitive interior.

### LED Backlight LCD

The LED Backlight LCD on this computer model allows for greater color quality, and consumes less power than conventional fluorescent LCDs and can therefore save significant battery life. In addition the LED backlit LCD allows for clearer reading in bright conditions.

## Advanced Users

If you are an advanced user you may skip over most of this Quick Start Guide. However you may find it useful to refer to *“What to Install” on page 4 - 1*, *“BIOS Utilities” on page 5 - 1* and *“Upgrading The Computer” on page 6 - 1* in the remainder of this User’s Manual. You may also find the notes marked with a  of interest to you.

## Beginners and Not-So-Advanced Users

If you are new to computers (or do not have an advanced knowledge of them) then the information contained in this Quick Start Guide should be enough to get you up and running. Eventually you should try to look through all the documentation (more detailed descriptions of the functions, setup and system controls are covered in the remainder of the User’s Manual), but do not worry if you do not understand everything the first time. Keep this manual nearby and refer to it to learn as you go. You may find it useful to refer to the notes marked with a  as indicated in the margin. For a more detailed description of any of the interface ports and jacks see *“Interface (Ports & Jacks)” on page A - 1*.



### Notes

Check the light colored boxes with the mark above to find detailed information about the computer’s features.

## Warning Boxes

No matter what your level please pay careful attention to the warning and safety information indicated by the  symbol. Also please note the safety and handling instructions as indicated in the *Preface*.

## Not Included

Operating Systems (e.g. *Windows Vista/Windows XP*) and applications (e.g. word processing, spreadsheet and database programs) have their own manuals, so please consult the appropriate manuals.



### Drivers

If you are installing new system software, or are re-configuring your computer for a different system, you will need to install the drivers listed in [Table 4 - 1, on page 4 - 3](#). Drivers are programs which act as an interface between the computer and a hardware component e.g. a wireless network module. It is very important that you install the drivers in the order listed. You will be unable to use most advanced controls until the necessary drivers and utilities are properly installed. If your system hasn't been properly configured (your service representative may have already done that for you); refer to [Chapter 4](#) for installation instructions.

### Ports and Jacks

See [“Notebook Ports and Jacks” on page A - 2](#) for a description of the interface (ports & jacks) which allow your computer to communicate with external devices, connect to the internet etc.

## System Software

Your computer may already come with system software pre-installed. Where this is not the case, or where you are re-configuring your computer for a different system, you will find the following operating systems are supported.

Operating System & Version Supported	Note
*Windows XP Home or Professional Editions (with Service Pack 3)	In order to run <b>Windows XP</b> without limitations or decreased performance, your computer requires a minimum <b>512MB</b> of system memory (RAM)
Windows Vista Home Basic/Home Premium/Business/ Enterprise/Ultimate Editions (with Service Pack 1)	Note that <b>Windows Vista Home Basic Edition</b> supports only limited Tablet PC functions.  In order to run <b>Windows Vista</b> without limitations or decreased performance, your computer requires a minimum

Table 1 - 1 - Operating Systems Supported

**\*Note:** For information on the **Windows XP OS** (specifically power, video and driver information) see **“Windows XP Information” on page D - 1.**

## System Startup

1. Remove all packing materials and place the computer on a stable surface.
2. Securely attach any peripherals you want to use with the notebook (e.g. keyboard and mouse) to their ports.
3. Attach the AC/DC adapter to the DC-In jack on the left of the computer, then plug the AC power cord into an outlet, and connect the AC power cord to the AC/DC adapter.
4. Pull the carrying handle out to easily access the latch. use one hand to push the LCD latch up and forward to unlock it, and carefully raise the lid/LCD to a comfortable viewing angle while using the other hand (as illustrated in [Figure 1 - 1](#) below) to support the base of the computer (**Note: Never** lift the computer by the lid/LCD).
5. Press the power button and then release it to turn the computer “on”.



### Shutdown

Note that you should always shut your computer down by choosing the **Shut Down** command from the **Lock Button Menu** in **Windows Vista**. This will help prevent hard disk or system problems.

*Figure 1 - 1 - Opening the Lid/LCD/Computer with AC/DC Adapter Plugged-In*

# Operating System Setup

If you are installing new system software, or are re-configuring your computer for a different system, make sure you configure the appropriate OS setting in the BIOS before installing a new operating system.

1. Start-up the computer and press <F2> to enter the **BIOS**.
2. Go to the **Advanced** menu, select “**Installed O/S**” and make sure the appropriate operating system is selected.
3. Go to the **Exit** menu and select “**Exit Saving Changes**” (or press **F10** and select “**Yes**” then press Enter) and press Enter to exit the BIOS and reboot the computer.




Figure 1 - 2 - BIOS (Operating System Selection)

## System Map: LCD Panel Open

Figure 1 - 3  
LCD Panel Open

1. LCD Latch
2. Built-In PC Camera (Optional)
3. LCD
4. Power Button
5. Keyboard
6. Fingerprint Reader Module
7. Touchpad & Buttons
8. Built-In Microphone
9. LED Indicators
10. Carrying Handle



### Wireless Device Operation Aboard Aircraft

The use of any portable electronic transmission devices aboard aircraft is usually prohibited. Make sure the module(s) are OFF if you are using the computer aboard aircraft.

Use the function key combinations to toggle power to the **3.75G/WLAN/Bluetooth** modules, and check the LED indicator icon to see if the modules are powered on or not (see [Table 1 - 3](#), on page 1 - 11/[Table 1 - 2](#), on page 1 - 9).



## LED Indicators

The LED indicators on the computer display helpful information about the current status of the computer.

Icon	Color	Description
	Orange	DC Power is Plugged In
	Green	The Computer is On
	Blinking Green	The Computer is in Sleep Mode
	Orange	The Battery is Charging
	Green	The Battery is Fully Charged
	Blinking Orange	The Battery Has Reached Critically Low Power Status
	Green	Hard Disk Activity
	Green	The <b>(optional)</b> Wireless LAN Module is Powered On
	Orange	The <b>(optional)</b> Bluetooth Module is Powered On
	Green	Number Lock Activated
	Green	Caps Lock Activated

Table 1 - 2 - LED Power & Communication Indicators

# Keyboard

The keyboard has a numerical keypad for easy numeric data input, and features function keys to allow you to change operational features instantly (see *Figure 1 - 4*). See *Table 1 - 3, on page 1 - 11* for details of the function/hot key indicators.




Figure 1 - 4 - Keyboard

## Special Characters

Some software applications allow the number-keys to be used with **Alt** to produce special characters. These special characters can only be produced by using the numeric keypad. Regular number keys (in the upper row of the keyboard) will not work. Make sure that **NumLk** is on.

## Other Keyboards

If your keyboard is damaged or you just want to make a change, you can use any standard USB keyboard. The system will detect and enable it automatically. However special functions/hot-keys unique to the system's regular keyboard may not work.

## Function Keys & Visual Indicators

The **function keys** (F1 - F12 etc.) will act as **hot keys** when pressed while the **Fn** key is held down. In addition to the basic function key combinations; visual indicators (see the table below) are available when the Hot Key driver is installed (see *“” on page 4 - 7*).

Keys	Function/Visual Indicators		Keys	Function/Visual Indicators	
Fn + ~	Play/Pause (in Audio/Video Programs)		Fn + F7	Display Toggle	
Fn + 	3.75G Module Power Toggle*	 	Fn + F8/F9	Brightness Decrease/Increase	 
Fn + F1	Touchpad Toggle	 	Fn + F10	PC Camera Power Toggle*	 
Fn + F2	Turn LCD Backlight Off (Press a key to or use Touchpad to turn on)		Fn + F11	WLAN Module Power Toggle*	 
Fn + F3	Mute Toggle	 	Fn + F12	Bluetooth Module Power Toggle*	 
Fn + F4	Sleep Toggle		Fn + NumLk	Number Lock Toggle	
Fn + F5/F6	Volume Decrease/ Increase	 	Fn + ScrLk	Scroll Lock Toggle	

Table 1 - 3 - Function Keys & Visual Indicators

**\*Note:** Any modules not included in your purchase configuration will appear grayed out when the key combination is pressed.

## System Map: Front & Rear Views

Figure 1 - 5  
Front & Rear Views

1. LCD Latch
2. Carrying Handle
3. Speakers
4. Battery



### Carrying Handle

Pull the carrying handle out to transport the computer, and push it in until it clicks into position for standard desktop use.

### Battery Information

Always completely discharge, then fully charge, a new battery before using it. Completely discharge and charge the battery at least once every 30 days or after about 20 partial discharges. See [“Battery Information” on page 3 - 10](#) for full instructions.

## System Map: Left View




Figure 1 - 6  
Left View

1. DC-In Jack
2. External Monitor Port
3. S/PDIF-Out Jack
4. Microphone-In Jack
5. Headphone-Out Jack
6. Vent/Fan Intake/Outlet
7. RJ-45 LAN Jack
8. 2 \* USB 2.0 Port
9. ExpressCard Slot (see page 2 - 7)
10. 7-in-1 Card Reader



### 7-in-1 Card Reader

The card reader allows you to use the most popular digital storage card formats:

MMC (MultiMedia Card) / SD (Secure Digital) / MS (Memory Stick) /  
MS Pro (Memory Stick Pro) / MS Duo (requires PC adapter) /  
Mini SD (requires PC adapter) / RS MMC (requires PC adapter)



### Overheating

To prevent your computer from overheating make sure nothing blocks the Vent/Fan Intake while the computer is in use.

## System Map: Right View

Figure 1 - 7  
Right View

1. Optical Device Drive Bay (for CD/DVD Device - see page 2 - 3)
2. 1 \* USB 2.0 Port
3. GPS Antenna Socket (for optional GPS Module)
4. Serial (COM1) Port
5. Security Lock Slot



### Changing DVD Regional Codes

Go to the **Control Panel** and double-click **Device Manager (Hardware and Sound)**, then click the **+** next to **DVD/CD-ROM drives**. Double-click on the DVD-ROM device to bring up the **Properties** dialog box, and select the **DVD Region** (tab) to bring up the control panel to allow you to adjust the regional code (see [“DVD Regional Codes” on page 2 - 5](#)).

DVD region detection is device dependent, not OS-dependent. You can select your module's region code **5** times. The fifth selection is permanent. This cannot be altered even if you change your operating system or you use the module in another computer.



### Disk Eject Warning

Don't try to eject a CD/DVD while the system is accessing it. This may cause the system to “crash”. Stop the disk first then eject it, or press the stop button twice.

### CD/DVD Emergency Eject

If you need to manually eject a CD/DVD (e.g. due to an unexpected power interruption) you may push the end of a straightened paper clip into the emergency eject hole. Do not use a sharpened pencil or any object that may break and become lodged in the hole. Don't try to remove a floppy disk/CD/DVD while the system is accessing it. This may cause the system to “crash”.

## System Map: Bottom View



### CPU

The CPU is not a user serviceable part. Opening this compartment, or accessing the CPU in any way, may violate your warranty.

### Overheating

To prevent your computer from overheating make sure nothing blocks the Vent/Fan Intake while the computer is in use.



Figure 1 - 8  
Bottom View

1. Battery
2. Hard Disk Bay Cover (3.75G Module Location)
3. RAM & CPU Bay Cover
4. Vent/Fan Intake/Outlet
5. Drainage Outlet (see *[“What to do if you Spill Liquid on the Computer”](#)* on page 6 - 11)



### Battery Information

Always completely discharge, then fully charge, a new battery before using it. Completely discharge and charge the battery at least once every 30 days or after about 20 partial discharges. See *[“Battery Information”](#)* on page 3 - 10 for full instructions.

## Windows Vista Start Menu & Control Panel

Most of the control panels, utilities and programs within *Windows Vista* (and most other *Windows* versions) are accessed from the **Start** menu. When you install programs and utilities they will be installed on your hard disk drive, and a shortcut will usually be placed in the **Start** menu and/or the desktop. Right-click the **Start** menu icon , and then select **Properties** if you want to customize the appearance of the **Start** menu.




Figure 1 - 9 - Start Menu & Control Panel

In many instances throughout this manual you will see an instruction to open the **Control Panel**. The **Control Panel** is accessed from the **Start** menu, and it allows you to configure the settings for most of the key features in *Windows* (e.g. power, video, network, audio etc.). *Windows Vista* provides basic controls for many of the features, however many new controls are added (or existing ones are enhanced) when you install the drivers listed in *Table 4 - 1, on page 4 - 3*. To see all controls it may be necessary to toggle to Classic View on.

## Video Features

You can switch display devices, and configure display options, from the **Display Settings** control panel (in **Personalization**) in *Windows Vista* as long as the appropriate **Intel video driver** is installed. For more detailed video information see *“Intel Video Driver Controls” on page B - 1*.

To access Display Settings in *Windows Vista*:

1. Click **Start**, and click **Control Panel** (or point to **Settings** and click **Control Panel**).
2. Click **Adjust screen resolution** under the **Appearance and Personalization** menu (or double-click **Personalization > Display Settings**).
3. Move the slider to the preferred setting in **Resolution**: ① (*Figure 1 - 10 on page 1 - 18*).
4. Click the arrow, and scroll to the preferred setting In **Colors**: ② (*Figure 1 - 10 on page 1 - 18*).
5. Click **Advanced Settings** (button) ③ (*Figure 1 - 10 on page 1 - 18*) and click **Intel(R) GMA Driver for mobile** (tab).
6. Click **Graphics Properties (button)** ④ (*Figure 1 - 10 on page 1 - 18*) to access the **Intel GMA** control panel (this control panel can also be accessed by double-clicking **Intel(R) GMA Driver for mobile** in **Classic View**).
7. The **Intel GMA** control panel can also be accessed by clicking the icon  in the taskbar and selecting **Graphics Properties** from the menu.

## Display Devices & Options

Besides the built-in LCD, you can also use an **external VGA monitor** (CRT) or **external Flat Panel Display** connected to the external monitor port as your display device.

## Quick Start Guide




Figure 1 - 10 - Display Properties Desktop

Intel Display Mode	Description
Single Mode	One of the connected displays is used as the display device
Intel(R) Dual Display Clone Mode	Both connected displays output the same view and may be configured independently
Extended Desktop Mode	Both connected displays are treated as separate devices, and act as a virtual desktop


Table 1 - 4 - Display Options

## Power Options

The **Power Options** (**Hardware and Sound** menu) control panel icon in *Windows* (see page *1 - 16*) allows you to configure power management features for your computer. You can conserve power by means of **power plans** and configure the options for the **power button**, **sleep button**, **computer lid (when closed)**, **display** and **sleep mode** from the left menu. Note that the **Power saver** plan may have an affect on computer performance.

Click to select one of the existing plans, or click *Create a power plan* in the left menu and select the options to create a new plan. Click *Change Plan Settings* and click *Change advanced power settings* to access further configuration options.

Pay attention to the instructions on battery care in *“Battery Information” on page 3 - 10*.



**Note:** Sleep is the default power saving state in *Windows Vista*

Figure 1 - 11 - Power Options



# Chapter 2: Features & Components

## Overview

Read this chapter to learn more about the following main features and components of the computer:

- Hard Disk Drive/Solid State Drive
- Optical (CD/DVD) Device
- 7-in-1 Card Reader
- ExpressCard Slot
- Touchpad and Buttons/Mouse
- Audio Features
- Adding a Printer



### Power Safety

Before attempting to access any of the internal components of your computer please ensure that the machine is not connected to the AC power, and that the machine is turned off. Also ensure that all peripheral cables, including phone lines, are disconnected from the computer.

## Hard Disk Drive/Solid State Drive

The hard disk drive/solid state drive is used to store your data in the computer. The hard disk can be taken out to accommodate other 2.5" serial (SATA) hard disk drives OR solid state drives (see [“Storage” on page C-2](#)) with a height of 9.5 mm.

The HDD/SSD is accessible from the bottom of your computer as seen below. For further details see [“Upgrading the Hard Disk Drive” on page 6 - 4](#).



*Figure 2 - 1*

**Hard Disk Location**

## Optical (CD/DVD) Device

There is a bay for a 5.25" optical (CD/DVD) device (12.7mm height). The actual device will depend on the module you purchased (see *“Storage” on page C - 2*). The optical device is usually labeled **“Drive D:”** and may be used as a boot device if properly set in the **BIOS** (see *“Boot Menu” on page 5 - 16*).

### Loading Discs

To insert a CD/DVD, press the open button **1** and carefully place a CD/DVD onto the disc tray with label-side facing up (use just enough force for the disc to click onto the tray’s spindle). Gently push the CD/DVD tray in until its lock “clicks” and you are ready to start. The busy indicator **2** will light up while data is being accessed, or while an audio/video CD, or DVD, is playing. If power is unexpectedly interrupted, insert an object such as a straightened paper clip into the emergency eject hole **3** to open the tray.



### Sound Volume Adjustment

How high the sound volume can be set depends on the setting of the volume control within **Windows**. Click the **Volume** icon on the taskbar to check the setting (see *“Audio Features” on page 2 - 9*).

*Figure 2 - 2*  
Optical Device



### CD Emergency Eject

If you need to manually eject a CD (e.g. due to an unexpected power interruption) you may push the end of a straightened paper clip into the emergency eject hole. However please do NOT use a sharpened pencil or similar object that may break and become lodged in the hole.

### Disk Eject Warning

Don't try to remove a CD/DVD while the system is accessing it. This may cause the system to "crash".

## Handling CDs or DVDs

Proper handling of your CDs/DVDs will prevent them from being damaged. Please follow the advice below to make sure that the data stored on your CDs/DVDs can be accessed.

Note the following:

- Hold the CD or DVD by the edges; do not touch the surface of the disc.
- Use a clean, soft, dry cloth to remove dust or fingerprints.
- Do not write on the surface with a pen.
- Do not attach paper or other materials to the surface of the disc.
- Do not store or place the CD or DVD in high-temperature areas.
- Do not use benzene, thinner, or other cleaners to clean the CD or DVD.
- Do not bend the CD or DVD.
- Do not drop or subject the CD or DVD to shock.

## DVD Regional Codes

To change the DVD regional codes see *“Changing DVD Regional Codes” on page 1 - 14.*

DVD Regional Coding	
Region	Geographical Location
1	USA, Canada
2	Western Europe, Japan, South Africa, Middle East & Egypt
3	South-East Asia, Taiwan, South Korea, The Philippines, Indonesia, Hong Kong
4	South & Central America, Mexico, Australia, New Zealand
5	N Korea, Russia, Eastern Europe, India & Most of Africa
6	China




Table 2 - 1  
DVD Regional Coding

Figure 2 - 3  
DVD Regions



### Card Reader Cover

Make sure you keep the rubber cover provided in the card reader when not in use. This will help prevent foreign objects and/or dust getting in to the card reader.

## 7-in-1 Card Reader

The card reader allows you to use some of the latest digital storage cards. Push the card into the slot and it will appear as a removable device, and can be accessed in the same way as your hard disk (s). Make sure you install the Card Reader driver (see *“Card Reader” on page 4 - 5*).

- MMC (MultiMedia Card)
- SD (Secure Digital)
- MS (Memory Stick)
- MS Pro (Memory Stick Pro)
- MS Duo (requires PC adapter\*)
- Mini SD (requires PC adapter\*)
- RS MMC (requires PC adapter\*)

**\*Note:** The PC adapters are usually supplied with these cards.

*Figure 2 - 4*  
**Right View**

1. Card Reader



## ExpressCard Slot

The computer is equipped with an **ExpressCard/34/54** slot that reads Express Card/34 and ExpressCard/54 formats. ExpressCards are the successors to PCMCIA (PC Cards). Make sure you install the Card Reader driver (see *“Card Reader” on page 4 - 5*).

ExpressCard/54 is used for applications which require a larger interface slot, e.g. CompactFlash card reader. The number denotes the card width; 54mm for the Express Card/54 and 34mm for the ExpressCard/34.



### Inserting and Removing ExpressCards

- Align the ExpressCard with the slot and push it in until it locks into place (as pictured in the generic figure below).
- To remove an ExpressCard, simply press the card to eject it.



### ExpressCard Slot Cover

Make sure you keep the rubber cover provided in the ExpressCard slot when not in use. This will help prevent foreign objects and/or dust getting in to the ExpressCard Slot.

*Figure 2 - 5*  
**Left View**

1. ExpressCard Slot

*Figure 2 - 6*  
**Inserting & Removing Express Cards**



### Mouse Driver


If you are using an external mouse your operating system may be able to auto-configure your mouse during its installation or only enable its basic functions. Be sure to check the device's user documentation for details.

Figure 2 - 7  
Mouse Properties

## Touchpad and Buttons/Mouse

The Touchpad is an alternative to the mouse; however, you can also add a mouse to your computer through one of the USB ports. The Touchpad buttons function in much the same way as a two-button mouse.

Once you have installed the Touchpad driver (see *“Touchpad” on page 4 - 5*) you can configure the functions by double-clicking the Touchpad driver icon  on the **taskbar**. You may then configure the Touchpad tapping, buttons, scrolling, pointer motion and sensitivity options to your preferences. You will find further information at [www.synaptics.com](http://www.synaptics.com).




## Audio Features

You can configure the audio options on your computer from the **Sound**  control panel in *Windows*, or from the **Realtek HD Audio Manager**  icon in the taskbar/control panel (right-click the taskbar icon  to bring up an audio menu). The volume may also be adjusted by means of the **Fn + F5/F6** key combination or **On-Screen Menu** buttons.



Right-click the icon  to access the menu above.



### Sound Volume Adjustment

The sound volume level is set using the volume control within *Windows* (and the volume function keys on the computer). Click the volume icon in the taskbar to check the setting.




Figure 2 - 8  
Realtek Audio Manager



### Parallel Printer

After setting up the printer attach the parallel cable to the printer.

Connect the printer's parallel cable to the Parallel to USB converter, and then plug the converter into the USB port.

Turn ON the printer, then turn ON the computer.

*Windows* will identify the printer and either load one of its own drivers or ask you to supply one. Follow the on-screen instructions.

## Adding a Printer

The most commonly used peripheral is a printer. The following conventions will help you to add a printer; however it is always best to refer to the printer manual for specific instructions and configuration options.

### USB Printer

Most current printers have a USB interface connection. You may use any one of the ports to connect the printer.

#### Install Instructions:

1. Set up the printer according to its instructions (unpacking, paper tray, toner/ink cartridge etc.).
2. Turn ON the computer.
3. Turn ON the printer.
4. Connect the printer's USB cable to one of the USB ports on the computer.
5. **Windows** will identify the printer and either load one of its own drivers or ask you to supply one. Follow the on-screen instructions.

### Parallel Printer

This is still a very common type of printer. The install instructions are in the sidebar, however you will need to purchase a parallel to USB converter.

# Chapter 3: Power Management

## Overview

To conserve power, especially when using the battery, your computer power management conserves power by controlling individual components of the computer (the monitor and hard disk drive) or the whole system. This chapter covers:

- The Power Sources
- Turning on the Computer
- Power Plans
- Power-Saving States
- Configuring the Power Buttons
- Battery Information

The computer uses enhanced power saving techniques to give the operating system (OS) direct control over the power and thermal states of devices and processors. For example, this enables the OS to set devices into low-power states based on user settings and information from applications.



### OS Note

Power management functions will vary slightly depending on your operating system. For more information it is best to refer to the user's manual of your operating system.

(**Note:** All pictures used on the following pages are from the *Windows Vista OS*.)

### Hibernate Mode In Windows Vista SP1

If you are using *Windows Vista SP1* with **4GB RAM** installed, see page **8 - 12** for information on **Hibernate**.

# The Power Sources

The computer can be powered by either an AC/DC adapter or a battery pack.

## AC/DC Adapter

Use only the AC/DC adapter that comes with your computer. The wrong type of AC/DC adapter will damage the computer and its components.

1. Attach the AC/DC adapter to the DC-in jack on the left of the computer.
2. Plug the AC power cord into an outlet, and then connect the AC power cord to the AC/DC adapter.
3. Raise the lid/LCD to a comfortable viewing angle.
4. Press the power button to turn “On”.

## Battery

The battery allows you to use your computer while you are on the road or when an electrical outlet is unavailable. Battery life varies depending on the applications and the configuration you're using. **To increase battery life, let the battery discharge completely before recharging** (see *“How do I completely discharge the battery?” on page 3 - 14*).

We recommend that you do not remove the battery. For more information on the battery, please refer to *“Battery Information” on page 3 - 10*.

# Turning on the Computer

Now you are ready to begin using your computer. To turn it on simply press the power button on the front panel.

When the computer is on, you can use the power button as a Sleep/Hibernate hot-key button when it is pressed for less than **4 seconds** (pressing and holding the power button for longer than this will force the computer to shut down). Use **Power Options (Hardware and Sound menu)** control panel in *Windows Vista* to configure this feature.



### Forced Off

If the system “hangs”, and the **Ctrl + Alt + Del** key combination doesn’t work, press the power button for **4 seconds**, or longer, to force the system to turn itself off.


### Power Button Sleep

**Sleep** is the default power mode when the power button is pressed for less than 4 seconds. You may configure the options for the power button from the **Power Options (Hardware and Sound menu)** control panel in *Windows Vista* (see your OS’s documentation, or “*Configuring the Power Buttons*” on page 3 - 8 for details).



### Shut Down

Note that you should always shut your computer down by choosing the **Shut Down** command from the **Lock Button Menu** in *Windows Vista*. This will help prevent hard disk or system problems.





### Resuming Operation

See [Table 3 - 1](#), on [page 3 - 9](#) for information on how to resume from a power-saving state.

### Password


It is recommended that you enable a password on system resume in order to protect your data.

## Power Plans

The computer can be configured to conserve power by means of **power plans**. You can use (or modify) an existing **power plan**, or create a new one.

The settings may be adjusted to set the **display** to turn off after a specified time, and to send the computer into **Sleep** after a period of inactivity.

Click *Change plan settings* and then click *Change advanced power settings* to access further configuration options in **Advanced Settings**.



*Figure 3 - 1*  
**Power Plan  
Advanced Settings**

Each **Windows power plan** will also adjust the processor performance of your machine in order to save power. This is worth bearing in mind if you are experiencing any reduced performance (especially under DC/battery power).

Choose **High performance** for maximum performance when the computer is powered from an AC power source. Choose the **Power saver** (bear in mind that this scheme may slow down the overall performance of the computer in order to save power) for maximum power saving when the computer is battery (DC power) powered.




Figure 3 - 2  
Power Plans



### Power Button

The **Power Button**  in the Start Menu (in Classic View use the Shut Down button ) can be used to send the computer into a power-saving state.

### Sleep Mode & Mobile PC Battery

A mobile PC in **Sleep** uses very little battery power.

After an extended period of time the computer will save any open documents and applications to hard disk.

## Power-Saving States

You can use power-saving states to stop the computer's operation and restart where you left off. **Sleep** is the default power-saving state in *Windows Vista*.

Earlier versions of *Windows* used Stand By and Hibernate as system power-saving states. *Windows Vista* combines the features of Stand By and Hibernate into the default **Sleep** power-saving state.

### Sleep

In **Sleep** all of your work, settings and preferences are saved to memory before the system sleeps. When you are not using your computer for a certain length of time, which you specify in the operating system, it will enter **Sleep** to save power.

The PC wakes from **Sleep within seconds** and will return you to where you last left off (what was on your desktop) without reopening the application(s) and file(s) you last used.

If your mobile PC in **Sleep** is running on battery power the system will use only a minimum amount of power. After an extended period the system will save all the information to the hard disk and shut the computer down before the battery becomes depleted.

### Hibernate

**Hibernate** uses the least amount of power of all the power-saving states and saves all of your information on a part of the hard disk before it turns the system off. If a power failure occurs the system can restore your work from the hard disk; if a power failure occurs when work is saved only to memory, then the work will be lost. **Hibernate** will also return you to where you last left off within seconds. You should put your mobile PC into **Hibernate** if you will not use the computer for a period of time, and will not have the chance to charge the battery.

### Shut Down

You should **shut down** the computer if you plan to install new hardware (don't forget to remove the battery and follow all the safety instructions in **Chapter 6**), plan to be away from the computer for several days, or you do not need it to wake up and run a scheduled task. Returning to full operation from **shut down** takes longer than from **Sleep** or **Hibernate**.



**Hibernate Mode In Windows Vista SP1**

If you are using *Windows Vista SP1* with **4GB RAM** installed, see page **8 - 12** for information on **Hibernate**.



*Figure 3 - 3*  
**Lock Button Menu**



### Password Protection


It is recommended that you enable a password on wake up in order to protect your data.

However you can disable this setting from the **Power Options** menu by clicking **Require a password on wakeup** in the left menu, and selecting the options (click **Change settings that are currently unavailable**).

*Figure 3 - 4*  
**Power Options**  
**Define Power Buttons**

## Configuring the Power Buttons

The power/sleep button (**Fn + F4** key combo) and closed lid may be set to send the computer in to a power-saving state.



### Resuming Operation

You can resume operation from power-saving states by pressing the power button, or in some cases pressing the sleep button (**Fn + F4** key combo).

Power Status	Icon  Color	To Resume
Power Off	Off	Press the Power Button
Sleep	Blinking Green	Press the Power Button Press the Sleep Button (Fn + F4 Key Combo)
Hibernate	Off (battery) Orange (AC/DC adapter)	Press the Power Button
Display Turned Off	Green	Press a Key or Move the Mouse/Touchpad



**Closing the Lid**

If you have chosen to send the computer to **Sleep** when the lid is closed, raising the lid will wake the system up.

Table 3 - 1 Resuming Operation



**Power Button**

When the computer is on, you can use the power button as a Sleep/Hibernate/Shut Down hot key button when it is pressed for less than **4 seconds** (pressing and holding the power button for longer than this will force the computer to shut down).



### Low Battery Warning

When the battery is critically low, immediately connect the AC/DC adapter to the computer or save your work, otherwise, the unsaved data will be lost when the power is depleted.

*Figure 3 - 5*  
**Battery Icon (Taskbar) & Battery Advanced Settings**



## Battery Information

Please follow these simple guidelines to get the best use out of your battery.

### Battery Power

Your computer's battery power is dependent upon many factors, including the programs you are running, and peripheral devices attached. You can set actions to be taken (e.g. Shut down, Hibernate etc.), and set critical and low battery levels from **power plan Advanced Settings** (see *Figure 3 - 1 on page 3 - 4*).

Click the battery icon   in the taskbar to see the current battery level and charge status.



### Conserving Battery Power

- Use a **power plan** that conserves power (e.g **Power saver**), however note that this may have an affect on computer performance.
- Lower the brightness level of the LCD display. The system will decrease LCD brightness slightly to save power when it is not powered by the AC/DC adapter.
- Reduce the amount of time before the display is turned off.
- Close wireless, Bluetooth, modem or communication applications when they are not being used.
- Disconnect/remove any unnecessary external devices e.g. USB devices, ExpressCards etc.

  
**Windows Mobility Center**

The **Windows Mobility Center** control panel provides an easy point of access for information on battery status, power plans used etc.



Figure 3 - 6  
Windows Mobility Center

### Battery Life

Battery life may be shortened through improper maintenance. **To optimize the life and improve its performance, fully discharge and recharge the battery at least once every 30 days.**

We recommend that you do not remove the battery yourself. If you do need to remove the battery for any reason see *“Removing the Battery” on page 6 - 3.*

### New Battery

Always completely discharge, then fully charge, a new battery (see *“Battery FAQ” on page 3 - 14* for instructions on how to do this).

### Recharging the Battery with the AC/DC Adapter

The battery pack automatically recharges when the AC/DC adapter is attached and plugged into an electrical outlet. If the computer is powered on, and in use, it will take several hours to fully recharge the battery. When the computer is turned off but plugged into an electrical outlet, battery charge time is less. (Refer to *“System Map: LCD Panel Open - Models E & F” on page 1 - 10* for information on the battery charge status, and to *“Battery Information” on page 3 - 10* for more information on how to maintain and properly recharge the battery pack.)

### Proper handling of the Battery Pack

- DO NOT disassemble the battery pack under any circumstances
- DO NOT expose the battery to fire or high temperatures, it may explode
- DO NOT connect the metal terminals (+, -) to each other



#### Damaged Battery Warning

Should you notice any physical defects (e.g. the battery is bent out of shape after being dropped), or any unusual smells emanating from the notebook battery, shut your computer down immediately and contact your service center. If the battery has been dropped we do not recommend using it any further, as even if the computer continues to work with a damaged battery in place, it may cause circuit damage, which may possibly result in fire. It is recommended that you replace your computer battery every two years.



#### Caution

Danger of explosion if battery is incorrectly re-placed.

Replace only with the same or equivalent type recommended by the manufacturer. Discard used battery according to the manufacturer's instructions.


### Battery FAQ

#### How do I completely discharge the battery?

Use the computer with battery power until it shuts down due to a low battery. Don't turn off the computer even if a message indicates the battery is critically low, just let the computer use up all of the battery power and shut down on its own.

1. Save and close all files and applications.
2. **Create a power plan** for discharging the battery and set all the options to **Never**.
3. Click **Change plan settings** (after saving it) and click **Change advanced power settings**.

Figure 3 - 7  
Power Plan Create



- 4. Scroll down to **Battery** and click **+** to expand the battery options.
- 5. Choose the options below (click **Yes** if a warning appears):




Figure 3 - 8  
Power Options  
Advanced Settings -  
Battery

- Low battery levels = 0%
- Critical battery Levels = 0%
- Low battery action = Do Nothing
- Critical battery action (On battery) = Shut Down
- Critical battery action (Plugged in) = Do Nothing

### **How do I fully charge the battery?**

When charging the battery, don't stop until the LED charging indicator light changes from orange to green.

### **How do I maintain the battery?**

Completely discharge and charge the battery at least once every 30 days or after about 20 partial discharges.

# Chapter 4: Drivers & Utilities

This chapter deals with installing the drivers and utilities essential to the operation or improvement of some of the computer's subsystems. The system takes advantage of some newer hardware components for which the latest versions of most available operating systems haven't built in drivers and utilities. Thus, some of the system components won't be auto-configured with an appropriate driver or utility during operating system installation. Instead, you need to manually install some system-required drivers and utilities.

## What to Install

The *Device Drivers & Utilities + User's Manual* disc contains the drivers and utilities necessary for the proper operation of the computer.

*Table 4 - 1, on page 4 - 3* lists what you need to install and **it is very important that the drivers are installed in the order indicated** (see "*Driver Installation*" on page *D - 28* for *Windows XP* information).

## Module Driver Installation

The procedures for installing drivers for the **Wireless LAN** and **3.75G/HSPA** modules are provided in "*Modules & Options*" on page *7 - 1*.

**Note:** The operating system is the default setting for **Bluetooth** control in *Windows Vista*, and does not require a driver. See "*Bluetooth Module*" on page *7 - 2* for configuration instructions.

# Driver Installation

Insert the *Device Drivers & Utilities + User's Manual* disc and click **Install Drivers** (button), or **Option Drivers** (button) to access the optional driver menu.

4



Figure 4 - 1 - Drivers Installer Screen 1

1. Check the driver installation order from [Table 4 - 1, on page 4 - 3](#) (the drivers must be installed in **this order**) which is the same as that listed in the **Drivers Installer** menu below.
2. Click to select the driver you wish to install, after installing each driver it will become grayed out (if you need to reinstall any driver, click the **Unlock** button).
3. Follow the instructions for each individual driver installation procedure as listed on the following pages.



Figure 4 - 2 - Drivers Installer Screen 2

Driver Name	Page #
<i>Chipset</i>	<i>Page 4 - 5</i>
<i>Video</i>	<i>Page 4 - 5</i>
<i>LAN</i>	<i>Page 4 - 5</i>
<i>Card Reader</i>	<i>Page 4 - 5</i>
<i>Touchpad</i>	<i>Page 4 - 5</i>
<i>Trusted Platform Module (TPM)</i>	<i>Page 4 - 6</i>
<i>Fingerprint Reader</i>	<i>Page 4 - 6</i>
<i>Hot Key Utility</i>	<i>Page 4 - 6</i>
<i>PC Camera (Optional)</i>	<i>Page 4 - 6</i>
<i>Audio</i>	<i>Page 4 - 7</i>
<i>Wireless LAN Module</i>	<i>Page 7 - 26</i>
<i>3.75G/HSPA Module</i>	<i>Page 7 - 48</i>

Table 4 - 1 - Driver Installation

## Manual Driver Installation

Click **Browse CD** (button) in the *Drivers Installer* application and browse to the executable file in the appropriate driver folder.

## Windows Update

After installing all the drivers make sure you enable **Windows Update** in order to get all the latest security updates etc. (all updates will include the latest **hotfixes** from Microsoft). See **“Windows Update” on page 4 - 7** for instructions.



### Windows Vista Service Pack 1

Make sure you install **Windows Vista Service Pack 1** (or a Windows Vista version which includes Service Pack 1) **before installing any drivers**. Go to the Microsoft website for download details, or contact your service center.

### Updating/Reinstalling Individual Drivers

If you wish to update/reinstall individual drivers it may be necessary to uninstall the original driver. To do this go to the **Control Panel** in the *Windows OS* and double-click the **Programs and Features** icon (**Programs > Uninstall a program**). Click to select the driver (if it is not listed see below) and click **Uninstall**, and then follow the on screen prompts (it may be necessary to restart the computer). Reinstall the driver as outlined in this chapter.

If the driver is not listed in the **Programs and Features** menu:

1. Click **Start**, and click **Control Panel** (or point to **Settings** and click **Control Panel**).
2. Double-click **Device Manager (Hardware and Sound > Device Manager)**.
3. Double-click the **device** you wish to update/reinstall the driver for (you may need to click “+” to expand the selection).
4. Click **Driver** (tab) and click the **Update Driver** or **Uninstall** button and follow the on screen prompts.

### User Account Control (Win Vista)

If a **User Account Control** prompt appears as part of the driver installation procedure, click **Continue/Allow**, and follow the installation procedure as directed.

### Windows Security Message

If you receive a *Windows* security message as part of the driver installation process. Just click “**Install this driver software anyway**” or **Install** to continue the installation procedure.

You will receive this message in cases where the driver has been released after the version of *Windows* you are currently using. All the drivers provided will have already received certification for *Windows*.

### New Hardware Found

If you see the message “**New Hardware Found**” (**Found New Hardware Wizard**) during the installation procedure (**other than when outlined in the driver install procedure**), click **Cancel** to close the window, and follow the installation procedure.

## Driver Installation Procedure

Insert the *Device Drivers & Utilities + User's Manual* disc and click **Install Drivers** (button), or **Option Drivers** (button) to access the optional driver menu.



### Driver Installation General Guidelines

The driver installation procedures outlined in this Chapter (and in **Chapter 7 Options & Modules**), are accurate at the time of going to press.

Drivers are always subject to upgrade and revision so the exact procedure for certain drivers may differ slightly. As a general guide follow the default on screen instructions for each driver (e.g. **Next > Next > Finish**) unless you are an advanced user. In many cases a restart is required to install the driver.

## Chipset

1. Click **1.Install Chipset Driver > Yes**.
2. Click **Next > Yes > Next > Next**.
3. Click **Finish** to restart the computer.

## Video

1. Click **2.Install Video Driver > Yes**.
2. Click **Next > Yes > Next > Next**.
3. Click **Finish** to restart the computer.

## LAN

1. Click **3.Install LAN Driver > Yes**.
2. Click **Next > Install**.
3. Click **Finish**.
4. The network settings can now be configured.

## Card Reader

1. Click **4.Install Cardreader Driver > Yes**.
2. Click **Install > Finish**.

## Touchpad

1. Click **5.Install Touchpad Driver > Yes**.
2. Click **Next**.
3. Click **Finish > Restart Now** to restart the computer.

### Trusted Platform Module (TPM)

Before installing the Trusted Platform Module driver you should enable the TPM State in the BIOS (see *“Security Menu” on page 5 - 11* and see *“Trusted Platform Module” on page 7 - 7* for full details.

1. Click **6.Install TPM Driver > Yes**.
2. Click **Install > Next**.
3. Click the button to accept the license and click **Next**.
4. Click **Next > Next > Install**.
5. Click **Finish > Yes** to restart the computer.

### Fingerprint Reader

1. Click **7.FingerPrint > Yes**.
2. Click **Software Installation**.
3. Click **Next > Next > Next**.
4. Click **Finish > Yes** to restart the computer.
5. See *“Fingerprint Reader Module” on page 7 - 13* for details.

### Hot Key Utility

1. Click **8.Install Hotkey Utility > Yes**.
2. Click **Next > Install**.
3. Click **Finish > Finish** to restart the computer.

### PC Camera (Optional)

Before installing the **PC Camera** driver, make sure that the optional PC Camera is on. Use the **Fn + F10 key combination** to power the camera on.

1. Click **9.Webcam > Yes**.
2. Choose the language you prefer and click **Next > Next**.
3. Click **Finish** to restart the computer.
4. See *“PC Camera Module” on page 7 - 19* for details.

## Audio

1. Click **10.Install Audio Driver > Yes**.
2. Click **Next**.
3. Click **Finish** to restart the computer.

Note that after installing the audio driver the system will not return to the **Drivers Installer** screen. To install any of the optional drivers listed overleaf, eject the *Device Drivers & Utilities + User's Manual* disc and then reinsert it (or double-click the disc icon in My Computer), and click **Option Drivers** (button) to access the optional driver menu.



### Windows Update

After installing all the drivers make sure you enable **Windows Update** in order to get all the latest security updates etc. (all updates will include the latest **hotfixes** from Microsoft).

To enable **Windows Update** make sure you are **connected to the internet**:

1. Click **Start**, and click **Control Panel** (or point to **Settings** and click **Control Panel**).
2. Click **Check for updates (Security)**, or double-click **Security Center** and click **Windows Update**.
3. Double-click **Check for updates (button)**.
4. The computer will now check for updates (you need to be connected to the internet).
5. Click **Install now** (button) to install the updates.

### Optional Drivers

See the pages indicated for the driver installation procedures for any optional modules included in your purchase option.



Figure 4 - 3 - Drivers Installer Screen 3

### Bluetooth Module

**Note:** The operating system is the default setting for **Bluetooth** control in *Windows Vista*, and does not require a driver. See *“Bluetooth Module” on page 7 - 2* for configuration instructions.

### Wireless LAN Module

See the introduction in *“Wireless LAN Module” on page 7 - 26*, and check the installation procedure.

### 3.75G/HSPA Module

See the introduction in *“3.75G/HSPA Module” on page 7 - 44*, and check the installation procedure.

# Chapter 5: BIOS Utilities

## Overview

This chapter gives a brief introduction to the computer's built-in software:

**Diagnostics:** The **POST** (Power-On Self Test)

**Configuration:** The *Phoenix SecureCore(tm) Setup Utility*

If your computer has never been set up, or you are making important changes to the system (e.g. hard disk setup), then you should review this chapter first and note the original settings found in *Setup*. Even if you are a beginner, keep a record of the settings you find and any changes you make. This information could be useful if your system ever needs servicing.

There is one general rule: *Don't make any changes unless you are sure of what you are doing*. Many of the settings are required by the system, and changing them could cause it to become unstable or worse. If you have any doubts, consult your service representative.



### BIOS Settings Warning

Incorrect settings can cause your system to malfunction. To correct mistakes, return to *Setup* and restore the *Setup Defaults* with <F9>.



### POST Screen

1. BIOS information
2. CPU type
3. Memory status
4. Enter **Setup** prompt appears only during POST

**Note:** The **POST** screen as pictured right is for guideline purposes only. The **POST** screen on your computer may appear slightly different. If you disable the **Boot-time Diagnostic Screen**, the POST screen will not appear.

Figure 5 - 1  
POST Screen

## The Power-On Self Test (POST)

Each time you turn on the computer, the system takes a few seconds to conduct a **POST**, including a quick test of the on-board RAM (memory). The screen below will appear if you have enabled the **Boot-time Diagnostic Screen** (see *“Boot-time Diagnostic Screen (Advanced Menu)” on page 5 - 9*).

As the **POST** proceeds, the computer will tell you if there is anything wrong. If there is a problem that prevents the system from booting, it will display a system summary and prompt you to run **Setup**. If there are no problems, the **Setup** prompt will disappear and the system will load the operating system. Once that starts, you can't get into **Setup** without rebooting.

```

Phoenix SecureCore(tm) NB
Copyright 1985-2007 Phoenix Technologies Ltd.
All Rights Reserved
Bios Revision: ***** ①
KBC/EC Firmware Revision: *****
CPU = 1 Processors Detected, Cores per Processor = 2
Intel(R) Core(TM)2 Duo CPU          U9300 @ 1.20GHz ②
990M System RAM Passed ③
3072 KB L2 Cache
System BIOS shadowed
Video BIOS shadowed
Fixed Disk 0: FUJITSU MHY2120BH
ATAPI CD-ROM: TSSTcorp CDDVDW TS-L633A
Mouse initialized

Press <F2> to enter SETUP ④
  
```

## Failing the POST

Errors can be detected during the **POST**. There are two categories, “fatal” and “non-fatal”.

### Fatal Errors

These stop the boot process and usually indicate there is something seriously wrong with your system. Take the computer to your service representative or authorized service center as soon as possible.

### Non-Fatal Errors

This kind of error still allows you to boot. You will get a message identifying the problem (make a note of this message!) followed by the prompt:

- Press <F1> to resume
- <F2> to enter Setup

Press **F1** to see if the boot process can continue. It may work, without the correct configuration.

Press **F2** to run the **Setup** program and try to correct the problem. If you still get an error message after you change the setting, or if the “cure” seems even worse, call for help.

# The Setup Program

The **Phoenix SecureCore(tm) Setup Utility** tells the system how to configure itself and manage basic features and subsystems (e.g. port configuration).

## Entering Setup

To enter *Setup*, turn on the computer and press **F2** during the **POST**. The prompt (*Press F2 to Enter Setup*) seen on page 5 - 2 is usually present for a few seconds after you turn on the system. If you get a “Keyboard Error”, (usually because you pressed **F2** too quickly) just press **F2** again.

If the computer is already on, reboot using the **Ctrl + Alt + Delete** combination and then hold down **F2** when prompted. The *Setup* main menu will appear.

## Setup Screens

The following pages contain additional advice on **portions** of the *Setup*.

Along the top of the screen is a menu bar with menu headings. When you select a heading, a new screen appears. Scroll through the features listed on each screen to make changes to *Setup*.

Instructions on how to navigate each screen are in the box along the bottom of the screen. If these tools are confusing, press **F1** to call up a **General Help** screen, and then use the arrow keys to scroll up or down the page.

The **Item Specific Help** on the right side of each screen explains the highlighted item and has useful messages about its options.

If you see an arrow ► next to an item, press **Enter** to go to a sub-menu on that subject. The sub-menu screen that appears has a similar layout, but the **Enter** key may execute a command.




### Setup Menus

The **Setup** menus shown in this section are for **reference** only. Your computer's menus will indicate the configuration appropriate for your model and options.

# Main Menu

Figure 5 - 2  
Main Menu



## System Time & Date (Main Menu)

The hour setting uses the 24-hour system (i.e., 00 = midnight; 13 = 1 pm). If you can change the date and time settings in your operating system, you will also change these settings. Some applications may also alter data files to reflect these changes.

### *SATA Port1/2 (Main Menu)*

Pressing **Enter** opens the sub-menu to show the configuration of a HDD/optical Device on the computer's SATA Port 1 or SATA Port 2. Use the **Auto** (Type:) setting to have the items configured automatically for you.

### *System/Extended Memory: (Main Menu)*

This item contains information on the system memory, and is not user configurable. The system will auto detect the amount of memory installed.

# Advanced Menu




Figure 5 - 3  
Advanced Menu

### SIO ITE8305E Configuration (Advanced Menu)

The sub-menu here allow you to enable/disable the external serial port. You can disable detection to save system power.

### *Installed O/S (Advanced Menu)*

This setting tells the computer what kind of operating system you're using. Make sure you choose the correct setting for your O/S in order to prevent system problems. Note: If you select the **Vista** O/S then the **SATA Mode Selection** menu will become available. If you are installing the **Windows XP** O/S make sure you have set the appropriate operating system here in order to prevent system problems.

### *Legacy USB Support: (Advanced Menu)*

Choose "**Enabled**" if you intend to use **USB** devices in systems which do not normally support USB functionality (e.g. DOS). The default setting is "**Enabled**" and does not need to be changed if you intend to use your USB devices in **Windows**.

### *Boot-time Diagnostic Screen (Advanced Menu)*

Use this menu item to enable/disable the Boot-time Diagnostic Screen or POST screen (see "**The Power-On Self Test (POST)**" on page 5 - 2).

### *Legacy OS Boot (Advanced Menu)*

If "**Enabled**" the system will attempt to load the Legacy OS (e.g. **Vista/Windows XP**) first. If set to "**Disabled**" the system will attempt to **EFI** (Extensible Firmware Interface) boot before the Legacy OS.

### *Reset Configuration Data (Advanced Menu)*

This item is set to **No** as default. You can change the setting to **Yes** if you have installed a new add-on which has reconfigured the system, resulting in such a serious system conflict that the operating system is unable to boot.

### *Power On Boot Beep (Advanced Menu)*

Use this menu item to enable/disable the beep as the computer starts up.

### *Battery Low Alarm Beep (Advanced Menu)*

Use this menu item to enable/disable the audible warning when the battery has reached low power status.


### *Fan Control (Advanced Menu)*

This menu item allows you to set the fan cooling behavior under light system activity (if you choose **Automatic** the system will adjust the fan cooling as appropriate for the system activity).

### *Power Conserve Mode (Advanced Menu)*

This menu allows you to configure power conservation from the *Setup Utility* to work in battery only, in AC and battery or to be disabled altogether.

# Security Menu





### Security Menu

The changes you make here affect the access to the **Setup** utility itself, and also access to your machine as it boots up after you turn it on. These settings do not affect your machine or network passwords which will be set in your software OS.

5

Figure 5 - 4  
Security Menu

## Set Supervisor Password (Security Menu)

You can set a password for access to the **Phoenix SecureCore (tm) Setup Utility**. This will not affect access to the computer OS (only the **Phoenix SecureCore (tm) Setup Utility**).



### Password Warning

If you set a boot password (Password on boot is “Enabled”), **NEVER** forget your password.

The consequences of this could be serious. If you cannot remember your boot password you must contact your vendor and you may lose all of the information on your hard disk.

5

### *Set User Password (Security Menu)*

You can set a password for user mode access to the **Phoenix SecureCore (tm) Setup Utility**. This will not affect access to the computer OS, (only the *Setup* utility) unless you choose to set a **Password on Boot** (see below). Many menu items in the **Phoenix SecureCore (tm) Setup Utility** cannot be modified in user mode. You can only set the user password after you have set the supervisor password.

### *Fixed disk boot sector (Security Menu)*

If you choose “**Write-Protect**” this will protect against viruses being written to the hard disk boot sector (this is not a substitute for installing an anti-virus program - see “*Viruses*” on page 8 - 4).

### *Password on boot (Security Menu)*

Specify whether or not a password should be entered to boot the computer (**you may only set a password on boot if a supervisor password is enabled**). If “*Enabled*” is selected, only users who enter a correct password can boot the system (see the warning in the sidebar). The default setting is “*Disabled*”.

**Note:** To clear existing passwords press **Enter** and type the existing password, then press **Enter** for the new password (without typing any password entry) and **Enter** again to confirm the password clearance.

### *TPM Support (Security Menu)*

Enable **TPM Support** from this menu, and the **TPM State** menu will then appear (see “*TPM State*” on page 5 - 14). **Note:** If you disable TPM Support then your TPM information may be erased altogether. You should only disable TPM support when you need to clear the TPM information. The default setting is “*Enabled*”.



#### TPM Password

Note that you should set a supervisor password in the BIOS to protect the **TPM information** from being tampered with by unauthorized users.

## TPM State




### TPM State Menu

To access this menu you must first enable TPM support from the security menu (see page 5 - 13).

### Password Protection

Note that you should set a supervisor password in the BIOS to protect the TPM information from being tampered with by unauthorized users.




### Change TPM State (TPM State)

This menu allows you to set the level of TPM functionality. You can enable/disable the TPM function altogether, or clear all existing TPM information.

**Note:** If you clear all TPM information it will be erased altogether and the information will need to be reconfigured.

Figure 5 - 5  
TPM State


If you have made any changes to the TPM State you will be asked to execute or reject the changes made after you have saved and exited the BIOS. Highlight the required option (it will be white), and then press Enter to save it.



Phy  
5

## Boot Menu

Figure 5 - 7  
Boot Menu



When you turn the computer on it will look for an operating system (e.g. *Windows Vista*) from the devices listed in this menu, and **in this priority order**. If it cannot find the operating system on that device, it will try to load it from the next device in the order specified in the **Boot priority order**. Item specific help on the right is available to help you move devices up and down the order.

## Exit Menu




Figure 5 - 8  
Exit Menu

Choosing to *Discard Changes*, or *Exit Discarding Changes*, will wipe out any changes you have made to the *Setup*. You can also choose to restore the original *Setup* defaults that will return the *Setup* to its original state, and erase any previous changes you have made in a previous session.



# Chapter 6: Upgrading The Computer

## Overview

This chapter contains information on upgrading the computer. Follow the steps outlined to make the desired upgrades. If you have any trouble or problems you can contact your service representative for further help. Before you begin you will need:

- A small crosshead or Phillips screwdriver
- A small regular slotted (flathead) screwdriver
- An antistatic wrist strap

Before working with the internal components you will need to wear an antistatic wrist strap to ground yourself because static electricity may damage the components.

The chapter includes:

- Removing the Battery
- Upgrading the Hard Disk Drive
- Upgrading the Optical (CD/DVD) Device
- Upgrading the System Memory (RAM)
- What to do if you Spill Liquid on the Computer

**Please make sure that you review each procedure before you perform it.**



### Warranty Warning

Please check with your service representative before undertaking any upgrade procedures to find out if this will VOID your warranty.

The CPU is not a user serviceable part. Accessing the CPU in any way, may violate your warranty.

Unauthorized tampering with the HDD may also violate your warranty.



### Power Safety Warning

Before you undertake any upgrade procedures, make sure that you have turned off the power, and disconnected all peripherals and cables (including telephone lines). It is advisable to also remove your battery in order to prevent accidentally turning the machine on.

### When Not to Upgrade

These procedures involve opening the system's case, adding and sometimes replacing parts. You should **not** perform any of these upgrades if:

- Your system is still under warranty or a service contract
- You don't have all the necessary equipment
- You're not in the correct environment
- You doubt your abilities

Under any of these conditions, contact your service representative to purchase or replace the component(s).



### Removal Warning

When removing any cover(s) and screw(s) for the purposes of device upgrade, remember to replace the cover(s) and screw(s) before turning the computer on.


### Upgrading the Processor

If you want to upgrade your computer by replacing the existing processor with a faster/new one you will need to contact your customer service representative. We recommend that you do not do this yourself, since if it is done incorrectly you may damage the processor or mainboard.

## Removing the Battery

If you are confident in undertaking upgrade procedures yourself, for safety reasons it is best to remove the battery.

1. Turn the computer **off**, and turn it over.
2. Slide the latch **1** in the direction of the arrow.
3. Slide the latch **2** in the direction of the arrow, and hold it in place.
4. Slide the battery out in the direction of the arrow **3**.



  
**Warranty Warning**

Please check with your service representative before undertaking any upgrade procedures to find out if this will VOID your warranty.

*Figure 6 - 1*  
**Battery Removal**



### HDD System Warning

New HDD's are blank. Before you begin make sure: You have backed up any data you want to keep from your old HDD.


You have all the CD-ROMs and FDDs required to install your operating system and programs.

If you have access to the internet, download the latest application and hardware driver updates for the operating system you plan to install. Copy these to a removable medium.

## Upgrading the Hard Disk Drive


The hard disk drive can be taken out to accommodate other 2.5" serial (SATA) hard disk drives with a height of 9.5mm (h) (see *“Storage” on page C - 2*). Follow your operating system’s installation instructions, and install all necessary drivers and utilities (see *“Driver Installation” on page 4 - 2*), when setting up a new hard disk.

1. Turn **off** the computer, and turn it over and remove the battery.
2. Locate the hard disk bay cover and remove screws **1** & **2**.
3. Remove the hard disk bay cover **3**.



*Figure 6 - 2*  
Removing the Hard  
Disk Bay Cover

- Carefully lift the hard disk up at point 4.
- Grip the tab 5 and slide the hard disk in the direction of arrow 6.




*Figure 6 - 3*  
Removing the Hard  
Disk

## Upgrading The Computer

6. Remove the hard disk.
7. Carefully insert the new hard disk and replace all the covers and screws.

*Figure 6 - 4*  
Hard Disk Out



*Figure 6 - 5*  
Hard Disk Insertion



## Upgrading the Optical (CD/DVD) Device

1. Turn **off** the computer, and turn it over and remove the battery.
2. Locate the RAM & CPU bay cover and remove screws **1** - **4**.
3. Carefully (**a fan and cable are attached to the under side of the cover**) lift up the bay cover.
4. Carefully disconnect the fan cable **5**, and remove the cover **6**.



### Fan Cable

Make sure you reconnect the fan cable **5** before screwing down the bay cover.

*Figure 6 - 6*  
Removing the RAM  
& CPU Bay Cover

## Upgrading The Computer

5. Remove screws **7** - **9** and use a screwdriver to carefully slide out the optical device at point **10**.
6. Insert the new device and replace the optical device screws **7** - **9**.
7. **Reconnect the fan cable before replacing the bay cover** (**5** in [Figure 6 - 6 on page 6 - 7](#)).
8. Replace the bay cover and screws.



*Figure 6 - 7*  
Removing the  
Optical Device

## Upgrading the System Memory (RAM)

1. Turn **off** the computer, and turn it over and remove the battery.
2. Locate the RAM & CPU bay cover and remove screws ① - ④.
3. Carefully (**a fan and cable are attached to the under side of the cover**) lift up the bay cover.
4. Carefully disconnect the fan cable ⑤, and remove the cover ⑥.



### Fan Cable

Make sure you reconnect the fan cable ⑤ before screwing down the bay cover.



### System Memory

The computer has **one** memory socket for 200 pin Small Outline Dual In-line (SO-DIMM) **DDRII (DDR2)** type memory modules (see *“Memory” on page C - 2* for details of supported module types).

The total memory size is automatically detected by the POST routine once you turn on your computer.

*Figure 6 - 8*  
**Removing the RAM  
& CPU Bay Cover**

## Upgrading The Computer




### Contact Warning

Be careful not to touch the metal pins on the module's connecting edge. Even the cleanest hands have oils which can attract particles, and degrade the module's performance.

6

5. Gently pull the two release latches on the sides of the memory socket in the direction indicated by the arrows (7 & 8) in *Figure 6 - 9*.
6. The RAM module will 9 pop-up, and you can remove it.



*Figure 6 - 9*  
**RAM Module  
Release Latches**

7. Insert a new module holding it at about a 30° angle and fit the connectors firmly into the memory slot.
8. The module's pin alignment will allow it to only fit one way. Make sure the module is seated as far into the slot as it will go. **DO NOT FORCE** the module; it should fit without much pressure.
9. Press the module in and down towards the mainboard until the slot levers click into place to secure the module.
10. **Reconnect the fan cable before replacing the bay cover** (5) in *Figure 6 - 8 on page 6 - 9*.
11. Replace the bay cover and screws.
12. Restart the computer to allow the BIOS to register the new memory configuration as it starts up.

## What to do if you Spill Liquid on the Computer

The keyboard incorporates a drainage system that minimizes the chances of liquid spillages on the keyboard penetrating the inside components of the computer. Liquid spilled on the computer is drained through the drainage hole at the bottom of the computer. There is no guarantee that all water can be prevented from entering the computer, and damage resulting from spillages is not covered in the warranty. However if you follow the steps outlined here you should be able to prevent water from entering the sensitive parts of the computer and causing damage.

1. If you spill liquid on the computer immediately turn it off and disconnect the AC adapter.
2. Carefully lift the computer up (water will drain through the drainage hole at the bottom of the computer), to prevent water from entering the vents/fan intakes on the bottom of the computer, while keeping it level (**do not tilt the computer**).



  
**Warranty Warning**

Note that the keyboard drainage system is designed to help prevent and minimize damage from liquid spillages on the computer keyboard. However damage resulting from spillages is not covered in the warranty.

*Figure 6 - 10*  
**Lift the Computer Up**

## Upgrading The Computer

3. Move the computer to a dry place (while keeping it level) and wipe any liquid off the keyboard using a clean, soft, dry cloth.



*Figure 6 - 11*  
**Wipe the Computer  
Dry**

4. Wipe any remaining liquid off the bottom of the computer.
5. Remove the battery (see ***“Removing the Battery” on page 6 - 3***).
6. Remove the DVD Drive module (see ***“Upgrading the Optical (CD/DVD) Device” on page 6 - 7***) and wipe any wet parts with a clean, soft, dry cloth.
7. Contact your service center to have the computer examined for any problems.

# Chapter 7: Modules & Options

## Overview

This chapter contains information on the following modules, which may come with your computer, depending on the configuration purchased. If you are unsure please contact your service representative.

- Bluetooth Module
- Security Modules (TPM & Fingerprint)
- PC Camera Module
- Wireless LAN Module
- 3.75G/HSPA Module
- GPS Module



### Wireless Device Operation Aboard Aircraft

The use of any portable electronic transmission devices aboard aircraft is usually prohibited. Make sure the module(s) are **OFF** if you are using the computer aboard aircraft.



### Wireless Device Operation Aboard Aircraft

The use of any portable electronic transmission devices aboard aircraft is usually prohibited. Make sure the module(s) are OFF if you are using the computer aboard aircraft.

Use the **Fn + F12** key combination to toggle power to the Bluetooth module, and check the LED indicator to see if the module is powered on or not (see [Table 1 - 3, on page 1 - 11](#)/[Table 1 - 2, on page 1 - 9](#)).

## Bluetooth Module

The operating system's **Bluetooth Devices** control panel is used to configure the Bluetooth settings in *Windows Vista*, and therefore does not require a driver. Use the **Fn + F12** key combination (see "[Function Keys & Visual Indicators](#)" on [page 1 - 11](#)) to toggle power to the Bluetooth module.



### Bluetooth Data Transfer

Note that the transfer of data between the computer and a Bluetooth enabled device is supported **in one direction only (simultaneous data transfer is not supported)**. Therefore if you are copying a file from your computer to a Bluetooth enabled device, you will not be able to copy a file from the Bluetooth enabled device to your computer until the file transfer process from the computer has been completed.


## Bluetooth Configuration in Windows Vista

### Setup your Bluetooth Device so the Computer Can Find it

1. Turn your Bluetooth device (e.g. PDA, mobile phone etc.) on.
2. Make the device discoverable (to do this check your device documentation).

### To Turn the Bluetooth Module On

1. Press the **Fn + F12** key combination to power on the Bluetooth module.
2. A Bluetooth icon  will appear in the taskbar (see sidebar).
3. You can then do any of the following to access the **Bluetooth Devices** control panel.
  - **Double-click** the icon  to access the **Bluetooth Devices** control panel.
  - Click **Start**, and click **Control Panel** (or point to **Settings** and click **Control Panel**), and then click **Bluetooth Devices (Hardware and Sound)**.
  - **Click/Right-click** the icon  and choose an option from the menu.



### Bluetooth Taskbar Icon

If you cannot see the Bluetooth icon in the taskbar, access the **Bluetooth Devices** control panel. Click **Options** (tab), and make sure that **Show Bluetooth icon in the notification area** check box (**Connections**) has a tick inside it.


Note that you will need to check the LED indicator to see if the module is powered on or not.

*Figure 7 - 1*  
**Bluetooth Devices & Click Icon Menu**


### To Add a Bluetooth Device

1. Access the **Bluetooth Devices** control panel.
2. Click **Options** (tab), and make sure that **Allow Bluetooth devices to connect to this computer** check box (**Connections**) has a tick inside it.
3. Click **Devices** (tab), and then click **Add**.
4. The **Add Bluetooth Device Wizard** will appear.
5. Click to select “**My device is set up and ready to be found**”, and then click **Next**.

Figure 7 - 2  
Add Bluetooth  
Device Wizard



6. The **Wizard** will then search for any available Bluetooth devices within range.
7. Click to select the device you want to communicate with, and click **Next**.
8. Select an appropriate passkey option and click **Next**.



9. Click **Finish**.

### Passkey Options

You can allow the system to choose a passkey for you. You will then be prompted to enter the generated passkey on your Bluetooth device.


Figure 7 - 3  
Passkey Option

## To Change Settings for the Bluetooth Device

1. Access the **Bluetooth Devices** control panel.
2. Click on the device you want to change and click **Properties** to:
  - Change the **name** of the device (click **General**, type a new name and click **OK**).
  - Enable/Disable a **service** (click **Services**, clear/tick the check box next to the service and click **OK**).

## To Make your Computer Discoverable to Bluetooth Devices

1. Access the **Bluetooth Devices** control panel.
2. Click **Options**, and make sure that **Allow Bluetooth devices to find this computer** check box (**Discovery**) has a tick inside it.
3. Make sure that **Alert me when a new Bluetooth device wants to connect** check box (**Connections**) has a tick inside it, if you want to be notified when a Bluetooth device wants to connect.



### Bluetooth Help

To get help on Bluetooth configuration and settings, select **Help and Support** from the **Start** menu. Type Bluetooth in the **Search Help** box, and select an item from the returned search results to get more information.

*Figure 7 - 4*  
**Bluetooth Devices Options**



### Password Warning

If you set passwords for any of the security modules, **NEVER** forget your password.

The consequences of this could be serious. If you cannot remember your boot password you must contact your vendor and you may lose all of the information on your hard disk.

## Security Modules (TPM & Fingerprint)

The encrypted channel between the **Trusted Platform Module security chip** and the **optional fingerprint reader** with **Protector Suite Software** provides a high level of security for your computer. A further level of security and control is provided in the BIOS (see *“Security Menu” on page 5 - 11* and *“TPM State” on page 5 - 14*). Make sure you install the TPM (see *“Trusted Platform Module (TPM)” on page 4 - 6*) and fingerprint reader (see *“Fingerprint Reader” on page 4 - 6*) drivers.

The **fingerprint reader** and **Protector Suite Software** allow you to:

- Access or Lock your computer
- Protect sensitive files
- Display and file your favorite web pages
- Fill in frequently used dialogs
- Run your favorite applications

The **TPM security chip** allows you to create and manage digital certificates for user and platform authentication. This type of security is usually administered within large enterprises and organizations, and therefore requires implementation by a system administrator before users can access security features.

Individual users can use the TPM as an authentication with the fingerprint reader.

# Trusted Platform Module

Before setting up the TPM functions you must initialize the security platform.

## Enabling & Activating TPM

1. Restart the computer.
2. Enter the **PhoenixBIOS Setup Utility** by pressing **F2** during the **POST**.
3. Use the arrow keys to select the **Security** menu.
4. Select **TPM Support** and set the item to **Enabled**.
5. The **TPM State** menu will then appear.





Figure 7 - 5  
TPM Support

## Modules & Options

- Use the arrow keys to select the **TPM State** menu.
- Select **TPM State**, and set the item to **Enable & Activate**.

Figure 7 - 6  
TPM State



- Press **F10** to save the changed BIOS information, exit the BIOS and restart the computer.
- If you make any changes to the TPM State you will be asked to **Execute/Reject** the change after restart (*"Physical Presence Operations" on page 5 - 15*).
- You can now **install the TPM driver** (see *"Trusted Platform Module (TPM)" on page 4 - 6*).

## Initializing TPM

1. To initialize the TPM it may be necessary to first clear any existing TPM information if applicable.
2. Enter the **PhoenixBIOS Setup Utility** by pressing **F2** during the **POST**.
3. Use the arrow keys to select the **TPM State** menu.
4. Select **TPM State**, and set the item to **Clear**.




Figure 7 - 7  
TPM State - Clear

5. Press **F10** to save the changed BIOS information, exit the BIOS and restart the computer.
6. If you make any changes to the TPM State you will be asked to **Execute/Reject** the change after restart (*“Physical Presence Operations” on page 5 - 13*).


7. Run the application from the **Infineon Security Platform Solution > Manage Security Platform** item in the **Start > Programs/All Programs** menu.
8. Click **User Settings** (tab) and click **Yes**, or right-click the taskbar icon  and select **Security Platform Initialization** (or click the **Security Platform State** taskbar bubble).
9. The **Quick Initialization** method will automatically be selected for you (if you need to use advanced settings provided by your network administrator then select **Advanced Initialization**)
10. You will need to use a removable media (e.g. a USB Flash Drive) to store passwords and data (keep the media in a safe place until required).
11. Select the drive you want to use from the drop-down menu and click **Next**.

7

*Figure 7 - 8*  
**Security Platform  
Quick Initialization  
Wizard**



12. Click **Next**.
13. Choose the **Security Platform Features** you want to use by clicking the appropriate tickbox.
14. Enter a **Basic User Password** (and re-type to confirm it) and click **Next**.



15. Click **Next** to confirm the settings.
16. The computer will then initialize the settings.
17. Click **Finish**.
18. Click the tabs and control panels to adjust the settings.
19. Double-click the taskbar icon  to access the **Infineon Security Platform Settings Tool**, or right-click the taskbar icon  and select a menu item.



### Help

Right-click the taskbar icon  to bring up the menu to select **Help** or **How to use the Security Platform Features**.

*Figure 7 - 9*  
**Settings**




### Help

Right-click the taskbar icon  to bring up the menu to select **Help** or **How to use the Security Platform Features**.

## Infineon Security Platform Settings Tool

The Infineon Security Platform Settings Tool allows you to manage and check the TPM state, manage your password information, and to backup and restore the TPM data. As TPM is usually administered within large enterprises and organizations, your system administrator will need to assist you in managing the information here.



*Figure 7 - 10*  
**Infineon Security Platform Settings Tool**

## Fingerprint Reader Module

The fingerprint reader module provides a high level of security for your computer. Make sure you have administrator's rights to your computer, and have a *Windows* password enabled for full security protection.

Before beginning the enrollment process it is recommended that you go through the fingerprint tutorial. To run the tutorial click **Start > Programs/All Programs > Protector Suite QL > Fingerprint Tutorial** after installing the driver.

Make sure you install the fingerprint reader driver (see "*Fingerprint Reader*" on page 4 - 6).



### Help & Manual

Right-click the taskbar icon  to bring up the menu to select **Help**.

Insert the *Device Drivers & Utilities + User's Manual* disc and click **Option Drivers** (button). Click **Unlock** (button) and then click **7.FingerPrint >Yes**.

Click **Documentation** to open the folder containing the manual in .pdf format.

To install the Adobe Acrobat Reader software to read the file, insert the *Device Drivers & Utilities + User's Manual* disc and click **User's Manual** (button), and click **Install Acrobat Reader** (button).



### Fingerprint Enrollment


Note that it is strongly recommended that you **enroll more than one finger** in case of injury etc.

### User Enrollment


1. Click **Start > Programs/All Programs > Protector Suite > Control Center**, or double click the taskbar icon  (click **Initialize**).
2. On the first run of the program you will be asked to click the **Accept** button to accept the license.
3. If you have not set a **Windows** password you will be prompted to do so (**note**: If you have not set a password **Protector Suite** cannot secure access to your computer).
4. Click **Submit** when you have entered password.
5. You will then be prompted to enroll your fingerprints (you can click **Tutorial** to get help with fingerprint enrollment at any time).

7

Figure 7 - 11  
Fingerprint Enrollment



6. Click the button above any of the fingers to begin the enrollment process for that finger.
7. Swipe the finger until the progress bar reaches **100%** to enroll that finger.
8. Repeat the process for all the fingers you wish to enroll (see sidebar), and then click **Save and Continue**.
9. Enter a backup password and click **Apply**.
10. Close the fingerprint status window.



### Fingerprint Enrollment


Note that it is strongly recommended that you **enroll more than one finger** in case of injury etc.

*Figure 7 - 12*  
Fingerprint Status

## Modules & Options

11. Right-click the taskbar icon  and select **Start Control Center** (and then swipe a finger) to allow you to **Edit Fingerprints**, register **Applications**, edit **Settings** and access the **Help** menu etc. You can also run the **Control Center** etc. from the **Protector Suite** item in the **Programs/All Programs** menu
12. Click "**Help**" in **Control Center Home** to get more information on any topic.
13. You can also run the **Tutorial**, or **Product Tour** video to get more information.


*Figure 7 - 13*  
**Control Center &  
Biomenu**



14. See "**Help & Manual**" on page 7 - 13 for further details.
15. If you swipe your finger over the reader at any time you can access the **Biomenu** to **lock the computer**, register websites, access the **Personal Safe**, **E-Wallet** or **Strong Password Generator**, open the **Control Center** and access the **Help** menu.

## Protector 2009 TPM Initialization

1. Click **Start > Programs/All Programs > Protector Suite > Control Center**, or double click the taskbar icon .
2. Swipe a registered finger or enter the password.
3. Click **Advanced Settings (Control Center Home > Settings)**.
4. Click **Trusted Platform Module (TPM)**.
5. Click **Initialize**.
6. Click **Identity** and then click **Mulifactor** to configure fingerprint authentication along with TPM.
7. Select the method required and click **Apply**.



*Figure 7 - 14*  
**Protector Suite TPM  
 Initialization &  
 Multifactor**



### Help

For more information on these and other features simply access “**Help**” in the **Fingerprint Control Center** and select the item from the menu on the left.

## Fingerprint Control Center Features

### Application Launcher

The **Application Launcher** allows you to register applications to be launched when assigned to a particular finger. Simply copy the application icon on to one of the registered fingers and then click OK to close the application window. Once registered the application will launch when you swipe the appropriate finger across the sensor.

### Password Bank

The **Password Bank** stores registrations of user names, passwords and other settings for web sites etc.

### Strong Password Generator

**Strong Password Generator** helps you to create complicated passwords resistant to dictionary attacks from the Internet.

### E-Wallet

The **E-Wallet** provides biometric security for important personal information such as credit card details, account numbers etc.

### File Safe

**File Safe** is an encrypted area assigned on your hard drive that allows you to store files and folders to be protected by fingerprint protection.

## PC Camera Module

The PC Camera module uses the **BisonCap** application to capture video files and to take pictures. Before installing the driver, make sure that the optional PC Camera is on.

Before installing the **PC Camera** driver, make sure that the optional PC Camera is on. **Use the Fn + F10 key combination** (see *“Function Keys & Visual Indicators” on page 1 - 11*) to toggle power to the PC Camera module. Make sure you install the drivers in the order indicated in *Table 4 - 1, on page 4 - 3*.

Make sure you install the PC Camera driver (see *“PC Camera (Optional)” on page 4 - 6*).



### Latest PC Camera Driver Information

Check the *Device Drivers & Utilities + User's Manual disc*, and any accompanying insert pages, for the latest updated information on the PC Camera driver, which may override the information provided here.

### PC Camera Audio Setup

If you wish to capture video & **audio** with your camera, it is necessary to setup the audio recording options in *Windows*.

1. Click **Start**, and click **Control Panel** (or point to **Settings** and click **Control Panel**).
2. Click **Sound**  (**Hardware and Sound**).
3. Click **Recording** (tab).
4. Right-click **Microphone** (Realtek High Definition Audio) and make sure the item is not disabled.
5. Double-click **Microphone** (or select **Properties** from the right-click menu).
6. Click **Levels** (tab), and adjust the **Microphone** and **Microphone Boost** sliders to the level required.
7. Click **OK** and close the control panels.
8. Run the **BisonCap** application program from the **Start > Programs/All Programs > BisonCam** menu.
9. Go to the **Devices** menu heading and select **Microphone (Realtek....)** (it should have a tick alongside it).
10. Go to the **Capture** menu heading and select **Capture Audio** (it should have a tick alongside it).





Figure 7 - 15  
Audio Setup for PC  
Camera





### Pre-Allocating File Space

You may pre-allocate the file size (**File > Allocate File Space**) for the capture file in the **BisonCap** program.

Pre-allocating space on the hard disk can improve the capture quality (particularly of large capture files), by reducing the amount of work the hard disk has to do in finding space for the video data as it is being captured.

See also *“Reducing Video File Size” on page 7 - 23.*

### BisonCap

**BisonCap** is a video viewer for general purpose video viewing and testing, and for capturing video files to .avi format.

1. Run the **BisonCap** program from the **Start > Programs/All Programs > Bison-Cam** menu (it is recommended that you **set the capture file** before the capture process - **see Set Capture File below**).
2. Go to the **Capture** menu heading (if you wish to capture audio check *“PC Camera Audio Setup” on page 7 - 20*) and select **Start Capture**.
3. Click **OK** (the file location will be displayed in the pop-up box) to start capturing the video, and press **Esc** to stop the capture (you can view the file using the **Windows Media Player**).

### Set Capture File

Prior to capturing video files you may select the **Set Capture File...** option in the **File** menu, and set the file name and location before capture (this will help avoid accidentally overwriting files). Set the name and location then click **Open**, then set the **"Capture file size:"** and click **OK**. You can then start the capture process as above.

Note the important information in *“Reducing Video File Size” on page 7 - 23* in order to save file space, and help prevent system problems.

## Reducing Video File Size

Note that capturing high resolution video files requires a substantial amount of disk space for each file. After recording video, check the video file size (right-click the file and select **Properties**) and the remaining free space on your hard disk (go to **My Computer**, right-click the hard disk, and select **Properties**). If necessary you can remove the recorded video file to a removable medium e.g. CD, DVD or USB Flash drive.

Note that the *Windows Vista* system requires a minimum of **15GB** of free space on the **C: drive** system partition. In order to prevent system problems it is recommended that you save the captured video file to a location other than the **C: drive** (see “*Set Capture File*” on page 7 - 22), limit the file size of the captured video (see “*Pre-Allocating File Space*” on page 7 - 22) or reduce video resolution (see below).

### To Reduce Video Resolution Output Size:

1. Run the **BisonCap** program.
2. Go to **Options** and scroll down to select **Video Capture Pin...**
3. Click the **Output Size** drop box and select a lower resolution size in order to reduce the captured file size.



### PC Camera Screen Refresh


The PC Camera module supports a frame rate of 12 fps. If you find that the screen refresh rate is subject to lag or stuttering, then **reduce the window size**, or adjust the **Output Size** and/or **Color Space Compression**.

To reduce **Output Size** and/or **Color Space Compression** run the **BisonCap** application, click **Options** and select **Video Capture Pin**. Adjust the settings from the appropriate pull-down menu.

### Eliminating Screen Flicker

If you find that the video screen in the **BisonCap** program is flickering, you can try to adjust the setting in the **Video Capture Filter** options.

1. Run the **BisonCap** program.
2. Go to **Options** and scroll down to select **Video Capture Filter...**
3. Click either **50Hz** or **60Hz** under **Frequency** in **Property Page** (tab).



*Figure 7 - 16*  
Video Capture Filter

## Zoom

The **BisonCap** program allows you to zoom the camera in and out.

1. Run the **BisonCap** program.
2. Go to **Zoom** and select **Zoom Out/Zoom In**.




Figure 7 - 17  
Zoom/Setting

## Taking Still Pictures

The **BisonCap** program allows you to take still pictures.

1. Run the **BisonCap** program.
2. Go to **Options** and select **Take Picture**.
3. The picture (in JPEG format) will be placed in the **Snapshot** folder  on the desktop.



### Snapshot Folder

The Snapshot folder's default location is on the desktop. Do not move this folder or an error may appear when you try to take a still picture.

If you accidentally delete or move the folder, you can create a new Snapshot folder on the desktop in order to capture the files.



### Wireless Device Operation Aboard Aircraft

The use of any portable electronic transmission devices aboard aircraft is usually prohibited. Make sure the module(s) are OFF if you are using the computer aboard aircraft.

Use the **Fn + F11** key combination/ button to toggle power to the WLAN module, and check the indicator to see if the module is powered on or not (see [Table 1 - 3, on page 1 - 11](#)/ [Table 1 - 2, on page 1 - 9](#)).

## Wireless LAN Module

If you have included an **Intel® Wi-Fi Link 5100/5300 Series (802.11 a/g/n) WLAN module**, or **3rd Party 802.11b/g WLAN module** in your purchase option, make sure that the Wireless LAN module is on before installing the driver.

Use the **Fn + F11 key combination** (see *“Function Keys & Visual Indicators” on page 1 - 11*), to **toggle power to the Wireless LAN module**. Make sure you install the drivers in the order indicated in *Table 4 - 1, on page 4 - 3*.

The standard driver installation procedure for the **Intel® Wi-Fi Link 5100/5300 Series module** is outlined overleaf. If you want to include **Intel® My WiFi Technology** as part of the installation procedure, **DO NOT install the driver as per the instructions overleaf**, instead see *“Intel® My WiFi Installation & Configuration” on page 7 - 31*.

If you have installed the standard driver (as per the instructions overleaf) and wish to enable **Intel® My WiFi Technology** at a later point you will need to reinstall the driver (choose **Unlock** from the Drivers Installer menu). Follow the driver installation procedure and choose **Modify** from the menu when the option appears, and then follow the remaining installation instructions in *“Intel® My WiFi Installation & Configuration” on page 7 - 31*.

## 802.11 b/g WLAN Driver Installation

1. Make sure the module is powered on, and then insert the *Device Drivers & Utilities + User's Manual* disc into the CD/DVD drive.
2. Click **Option Drivers** (button).
3. Click **1.Wireless Lan > Yes**.
4. Choose the language you prefer and click **Next**.
5. Click **Next > Install**.
6. Click **Finish** to complete the installation.
7. The operating system is the default setting for Wireless LAN control in *Windows Vista* (see overleaf).

## Intel® Wi-Fi Link 5100/5300 Series (802.11 a/g/n) Driver Installation

1. Make sure the module is powered on, and then insert the *Device Drivers & Utilities + User's Manual* disc into the CD/DVD drive.
2. Click **Option Drivers** (button).
3. Click **1.Wireless Lan > Yes**.
4. Click **Next > Next**.
5. Click the button to accept the license and click **Next**.
6. Click **Next > Next > Finish**.
7. The operating system is the default setting for Wireless LAN control in *Windows Vista* (see overleaf).



### Intel(R) PROSet/ Wireless

Access the **Intel PROSet Wireless** tools (Statistics and Diagnostic tools) from the Start menu (Start > Programs/All Programs > **Intel PROSet**). These tools provide diagnostic and statistical information only (use the WLAN control in *Windows Vista* to connect to a WLAN access point).

### Connecting to a Wireless Network

Make sure the Wireless LAN module is turned on.

1. Click the taskbar wireless icon , and then click **Connect to a network** (or right-click the icon , and then click **Connect to a network**).

Figure 7 - 18  
Taskbar Menu



2. In the **Show** list, click to choose **Wireless** from the drop-down menu.
3. A list of currently available networks will appear.



Figure 7 - 19  
Connect to a  
Network

#### Network and Sharing Center

You can also use the **Network and Sharing Center** control panel in Windows (**Network and Internet**) to connect to any available wireless networks.

4. Click a network, and then click **Connect**.
5. If you do not see a network you want to connect to, click **Set up a connection or network** (a list of options will appear allowing manual searching, and creating a new network).




Figure 7 - 20  
Connecting

6. Move the cursor over the taskbar icon  to see the connection status (see below).



Figure 7 - 21  
Connection Status

## Modules & Options



### Security Enabled Networks

You should try to make sure that any network you are connecting to is a secure network.

Connecting to unsecure networks may allow unauthorized access to your computer, documents, websites and files etc.

7. To disconnect from the wireless network you can click the taskbar wireless icon , and then select **Connect or disconnect** to access the network menu, and click Disconnect (or **right-click** the icon , and then click **Disconnect from**).




Figure 7 - 22  
Disconnecting

## Intel® My WiFi Installation & Configuration

Intel® My WiFi Technology uses your WLAN module to allow you to connect up to eight other WiFi enabled devices (e.g. digital cameras, other computers, cell phones, handheld devices etc.) to your computer (similar to Bluetooth), while still connecting to the Internet through your WiFi wireless connection. Intel® My WiFi Technology offers greater range and speed than other personal area networks, and does not require an access point.



### Intel® My WiFi Help

To get help on **Intel® My WiFi** configuration and settings, access the **Intel® My WiFi Utility** from the **Start** menu (Start > Programs/All Programs > Intel PROSet Wireless > Intel My WiFi Technology), or by clicking the taskbar icon . Click the **Help** icon  and select a help topic from the **Contents** menu.



### Intel(R) PROSet/ Wireless


Access the **Intel PROSet Wireless** tools (Statistics and Diagnostic tools) from the Start menu (Start > Programs/All Programs > **Intel PROSet**). These tools provide diagnostic and statistical information only (use the WLAN control in **Windows Vista** to connect to a WLAN access point).

*Figure 7 - 23*  
**Intel(R) PRO Set  
Intel(R) My WiFi  
Technology  
Installation**

## Intel® Wi-Fi Link 5100/5300 Series My WiFi Driver Installation

If you see the message “**Found New Hardware**” click **Cancel** to close the window.

1. Make sure the module is powered on, then insert the *Device Drivers & Utilities + User’s Manual* disc into the CD/DVD drive.
2. Click **Option Drivers** (button).
3. Click **1.Wireless Lan > Yes**.
4. Click **Next > Next**.
5. Click the button to accept the license and click **Next > Next**.
6. Click **Custom** (button) and click **Next**.
7. Click **Intel(R) My WiFi Technology** (button) and select “**This feature will be installed on local hard drive.**”



8. Click **Next > Finish**.

## Intel® My WiFi Configuration

You can configure the My WiFi settings as follows.

1. Access the **Intel® My WiFi Utility** from the **Start** menu (**Start > Programs/All Programs > Intel PROSet Wireless > Intel My WiFi Technology**), or by clicking the taskbar icon .
2. Click **Enable**  (on the first run of the program there will be no connected devices listed).




Figure 7 - 24  
Intel® My WiFi  
Utility

## Modules & Options

3. Click **Start**, and click **Control Panel** (or point to **Settings** and click **Control Panel**).
4. Click **Network and Sharing Center** (Network and Internet).
5. Click **Manage Network Connections**.

*Figure 7 - 25*  
**Network and Sharing Center**


Click **Manage Network Connections**



6. Right-click **Intel My WiFi STA** (Station) in **Network Connections** and select **Properties**.

*Figure 7 - 26*  
**Intel My WiFi STA**  
**Properties**  
**(Network Connections)**


Right-click **Intel My WiFi STA** (Station) and select **Properties**.



7. Click **Sharing (tab)** and select “**Allow other network users to connect through this computer’s Internet connection**”.
8. Select **Intel My WiFi PAN** under **Home Networking Connection**.
9. Click **OK**.

Click “**Allow other network users to connect through this computer’s Internet connection**”.

Select **Intel My WiFi PAN**.



*Figure 7 - 27*  
**Intel WiFi STA Properties - Sharing**

## Modules & Options


Figure 7 - 28  
IP Address  
Warning



### IP Addresses

The Intel® My WiFi default gateway IP address is **192.168.0.1**. DO NOT use this address for any Wireless Access Point (or any other static IP address on your network).

10. A message will appear to inform you that the LAN adapter will be set to use the IP address **192.168.0.1**.
11. Click **Yes** to enable Internet Connection Sharing.



12. Access the **Intel® My WiFi Utility** from the **Start** menu (**Start > Programs/All Programs > Intel PROSet Wireless > Intel My WiFi Technology**), or by clicking the taskbar icon .
13. Click **Profiles** .

Figure 7 - 29  
Intel® My WiFi  
Utility



14. Click **Profiles**, click **Intel Wireless PAN** and click **Edit**.



Figure 7 - 30  
IP Address  
Warning

15. You can change the **Profile Name** and **Network Name** to your personal preferences in **General** (tab).



### Profile and Network Names

The **Profile Name** is the name as displayed on your computer in the **Network Connections** control panel (see [Figure 7 - 26 on page 7 - 34](#)).

The **Network Name (SSID)** is the name the devices see when they try to connect to your computer.





Figure 7 - 31  
Intel® My WiFi  
Profile Settings -  
General

- Click **Security** (tab).
- Change the **Security Type** to **WEP** and the **Encryption Type** to **64bit**.
- Enter a password (5 characters long) in the **Passphrase** box.
- Click **OK**.



**7**  
*Figure 7 - 32*  
**Intel® My WiFi**  
**Profile Settings -**  
**Security**

20. Click **Sharing** (tab).
21. Make sure **Filter Network Traffic** and **DHCP and DNS Server** are **Disabled**.
22. Click **OK**.

Set Filter Network Traffic & DHCP and DNS Servers to **Disabled**.





Figure 7 - 33  
Intel® My WiFi  
Profile Settings -  
Sharing


## Modules & Options

23. Click **Advanced** (tab).
24. Make sure the **Default Channel** is set to **Channel 1, 6 or 11**.
25. Click **OK**.



**7**  
*Figure 7 - 34*  
**Intel® My WiFi**  
**Profile Settings -**  
**Advanced**


26. Double-click **Intel My WiFi PAN** (Personal Area Network) in **Network Connections**.
27. Click **Details** to display the **Network Connection Details**.



*Figure 7 - 35*  
**Intel My WiFi PAN**  
**Network**  
**Connection Details**  
**(Network**  
**Connections)**

## Modules & Options

28. Access the **Intel® My WiFi Utility** from the **Start** menu (**Start > Programs/All Programs > Intel PROSet Wireless > Intel My WiFi Technology**), or by clicking the taskbar icon .
29. To add a new device follow the instructions in the devices' user guide for connecting to a WiFi network.
30. Click **Add New Device** in **Intel® My WiFi Utility** to confirm the security settings detail.



*Figure 7 - 36*  
**Intel® My WiFi  
Utility  
(Add New Device)**

## Windows Mobility Center

The **Windows Mobility Center** control panel provides an easy point of access for information on battery status, power plans used and wireless device status etc.

To access the Windows Mobility Center:

1. Click **Start**, and click **Control Panel** (or point to **Settings** and click **Control Panel**).
2. Double-click **Windows Mobility Center (Mobile PC)**.
3. Click the button to **Turn wireless off/on**, or click the icon  to access the network menu.



Figure 7 - 37  
Windows Mobility  
Center



### 3.75G/HSPA Module Options

There are **three optional** 3.75G/HSPA modules available for this series of computer models. Each module is supplied with the appropriate application software.

The module type supplied may depend upon the computer model purchased. Check with your service center for details.

Install the driver from the Drivers Installer menu and check the instructions for the appropriate application on the following pages.

## 3.75G/HSPA Module

If you have included an **optional 3.75G/HSPA** (High Speed Packet Access) module (see *“Communication” on page A - 3* for specification details) in your purchase option, you will have the appropriate software provided for your module. Follow the instructions *on page 7 - 46* to install the USIM card (supplied by your service provider), and then install the appropriate application. Make sure you install the drivers in the order indicated in *Table 4 - 1, on page 4 - 3*.



### Important Notice

If your purchase option includes both **Wireless LAN** and **3.75G/HSPA** modules, then the appropriate antennas will be installed. Note that In order to comply with FCC RF exposure compliance requirements, the antenna must not be co-located or operate in conjunction with any other antenna or transmitter.

**Before installing the application, make sure that the 3.75G/HSPA module is ON** (installing the driver with the module off will not allow the software to detect the module hardware correctly). Use the **Fn +  key combination** (see [Table 1 - 5, on page 1 - 15](#)) to **toggle power to the 3.75G/HSPA module**. When the 3.75G/HSPA module is powered on, the indicator  will briefly be displayed. **Note that exiting the application does NOT turn off the 3.75G/HSPA module.**

- **3G Watcher** - See [“3G Watcher Application” on page 7 - 48](#) for driver installation information and [“Setting Up a Carrier Profile” on page 7 - 49](#) for instructions on using the **3G Watcher** application.
- **HSPA Modem Interface** - See [“HSPA Modem Interface Installation” on page 7 - 55](#) for driver installation information and [“HSPA Modem Interface” on page 7 - 56](#) for instructions on using the **HSPA Modem Interface**.
- **Mobile Partner** - See [“Mobile Partner Application Installation” on page 7 - 64](#) for driver installation information and [“Mobile Partner Application” on page 7 - 65](#) for instructions on using the **Mobile Partner** application.



### 3.75G/HSPA Modules & System Wake Up

Note that the 3.75G/HSPA modules **DO NOT** support system wake up on 3.75G/HSPA modem activity.



### Important Notice 3.75G/HSPA & Bluetooth/Wireless LAN Modules

In order to comply with FCC regulations you should NOT operate the 3.75G/HSPA module and the Bluetooth/Wireless LAN modules at the same time as this may disrupt radio frequency, and cause interference. When the 3.75G/HSPA module is powered on, make sure that the Bluetooth/Wireless LAN modules are powered off.





### Power Safety Warning

Before you undertake any installation procedures, make sure that you have turned off the power, and disconnected all peripherals and cables (including telephone lines). It is advisable to also remove your battery in order to prevent accidentally turning the machine on.

## USIM Card Installation

1. Turn the computer **off**, and turn it over.
2. Slide the latch **1** in the direction of the arrow.
3. Slide the latch **2** in the direction of the arrow, and hold it in place.
4. Slide the battery out in the direction of the arrow **3**.



*Figure 7 - 38*  
**Battery Removal**

5. Insert the USIM card as illustrated below until it clicks fully into position, and replace the battery.



*Figure 7 - 39*  
**USIM Card  
Insertion**



### Wireless Device Operation Aboard Aircraft

The use of any portable electronic transmission devices aboard aircraft is usually prohibited. Make sure the module(s) are OFF if you are using the computer aboard aircraft.

Use the **Fn + ** key combination to toggle power to the 3.75G/HSPA module, and check the indicator to see if the module is powered on or not (see [Table 1 - 3, on page 1 - 11](#) / [Table 1 - 2, on page 1 - 9](#)).

## 3G Watcher Application

With the **3.75G/HSPA module** and USIM card (provided by your service provider) installed you may then install the 3G Watcher application. The **3G Watcher** application allows you to directly access your 3.75G internet service from the computer.

### 3G Watcher Application Installation

1. Enable power to the module by pressing the **Fn + ** key combination (the on screen icon  will indicate the module's power status).
2. If a *Found New Hardware* window appears, click **Cancel**.
3. Click **Option Drivers** (button).
4. Click **2.3.5G Generation Module > Yes**, and then click **Next**.
5. Click the button to accept the license agreement, and then click **Install**.
6. When the next screen appears **wait (for about 2 minutes) until you see the message "Your devices are ready to use" in the taskbar before clicking Finish** (this allows the hardware to detect the 3.75G module).
7. Access the **3G Watcher** application from the **Start** menu (**Start > Programs/All Programs > Sierra Wireless > 3G Watcher**), or by double-clicking the desktop icon .

## Setting Up a Carrier Profile

Although the connection information is stored on the USIM card supplied by the service provider, you may need to set up the appropriate carrier profile in 3G Watcher.

1. Power on the 3.75G/HSPA module using the **Fn +**  key combination.
2. Access the **3G Watcher** application from the **Start** menu (**Start > Programs/All Programs > Sierra Wireless > 3G Watcher**), or by double-clicking the desktop icon .
3. Click **Tools** and select **Options**.
4. Click **Profiles** and then click the **Add new profile** button , and select **WWAN profile**.




Figure 7 - 40  
Add WWAN Profile

## Modules & Options

Figure 7 - 41  
User Options



### Profile Details

If you have chosen the profile from the drop-down list then most of the information in the **General** and **Advanced** tabs should be automatically filled in for you (however check with your service provider for the latest information as you may at least need to add in your **Username** and **Password**).


Figure 7 - 42  
Choose Profile



### Profile Information

Click **General** and/or **Advanced** (and the **sub-menus** under **Advanced**) in the left menu, and then click in any of the fields to add the appropriate information supplied by your service provider.

5. You can then enter a new profile name or choose a profile from the drop-down list provided by the software (see the **sidebars** for information on the profile details).



6. Click **Apply** > **OK** to save the information.
7. You can choose the profile from the pull-down menu.



### Connecting to the Service Provider

1. Power on the 3.75G/HSPA module using the **Fn +**  key combination.
2. You can access the **3G Watcher** application from the **Start** menu (**Start > Programs/All Programs > Sierra Wireless > 3G Watcher**), or by double-clicking the desktop icon .
3. The software will run and display the service provider name (see **“Setting Up a Carrier Profile” on page 7 - 49**).



Figure 7 - 43  
Connect Button

4. Click **Connect**  to begin the connection process.
5. The **3G Watcher** application will then display the connection information in the window.



Figure 7 - 44  
Connecting

## Modules & Options

- When the connection is successful a taskbar notification will appear (as below).

Figure 7 - 45  
Connected  
Taskbar  
Notification



- You can then access the internet, download e-mail etc. as per any internet connection.
- While you are connected the taskbar icon will be green  (it will be red  when the program is running but not connected).
- To disconnect click the **Disconnect**  icon.

Figure 7 - 46  
3GWatcher  
Connected



- The program will disconnect from the service provider.
- The module will still be on, and you will need to press the **Fn +**  key combination to turn it off.

12. If you click the **3G Watcher** close icon  a message will be displayed asking you to click **OK** to confirm the program exit.



*Figure 7 - 47*  
**Exit Warning**

13. Exiting the program DOES NOT turn off the 3.75G/HSPA module, and you will need to press the **Fn + ** key combination to turn off the module (pay careful attention to this aboard aircraft - see [“Wireless Device Operation Aboard Aircraft” on page 7 - 48](#)).
14. If the module is on and the computer enters a power-saving state, then the power status of the module on resuming from the power-saving state will be as below:
- If the 3.75G/HSPA module is on and the computer is **Shut Down or Restarted**; the module will be **off** when the computer starts up.
  - If the 3.75G/HSPA module is on and the computer enters **Sleep or Hibernate**; the module will be **off** when the computer resumes from sleep.

### Short Messaging Service

In addition to standard internet services you may also send and receive SMS text messages using the **3G Watcher** program, if your service supports SMS.

#### Reading SMS Messages

1. The SMS message indicator  in the main window will notify you of any new messages received.
2. Double-click the icon  or select **Tools > SMS Express**.
3. Select the inbox folder and select any message to read it.
4. You cannot receive any new messages if the USIM card becomes full, so you will need to delete some of the messages in order to free up space on the USIM card.

#### Creating and Sending SMS Messages

1. Double-click the icon  or select **Tools > SMS Express**.
2. Select **File > New Message** or click the **New** button.
3. Enter the recipient's number in the **To..** field or click the **To..** button to select an entry from the phone book, and click the **Message** button.
4. Type in the message details in the message body area.
5. Click the **Send** button (or save the message to send later).

For more details on SMS see **3GWatcher Online Help** from the **Help > Help Topics** menu.

## HSPA Modem

With the **3.75G/HSPA** modem module and USIM card (supplied by your service provider) installed you may then install the **HSPA** modem interface. The **HSPA** modem interface application allows you to directly access your HSPA internet service from the computer.

### HSPA Modem Interface Installation

1. Enable power to the module by pressing the **Fn** +  key combination (the on screen icon  will indicate the module's power status).
2. If a **Found New Hardware** window appears, click **Cancel**.
3. Insert the **Device Drivers & Utilities + User's Manual** disc into the CD/DVD drive.
4. Click **Option Drivers** (button).
5. Click **2.3.5G Generation Module > Yes**, and then click **Next**.
6. Click **Next > Install**.
7. Click **Finish** to restart the computer.
8. Access the **HSPA modem** interface from the **Start** menu (**Start > Programs/All Programs > HSPA modem**), or by double-clicking the **HSPA modem** icon on the desktop.



### Wireless Device Operation Aboard Aircraft

The use of any portable electronic transmission devices aboard aircraft is usually prohibited. Make sure the module(s) are OFF if you are using the computer aboard aircraft.

Use the **Fn** +  key combination to toggle power to the 3.75G/HSPA module, and check the indicator to see if the module is powered on or not (see [Table 1 - 3](#), on page 1 - 11/ [Table 1 - 2](#), on page 1 - 9).



### HSPA Modem Help

To get help on HSPA modem configuration and settings, click the help icon  and select **Help**.

## HSPA Modem Interface

The connection information is stored on the USIM card supplied by the service provider.

1. Power on the 3.75G/HSPA modem module using the **Fn + ** key combination.
2. Access the **HSPA Modem** interface from the **Start** menu (**Start > Programs/All Programs > HSPA Modem > HSPA Modem**), or by double-clicking the desktop icon .
3. If a USIM card is not installed then a message will appear to notify you of this (click **OK** to close the message and install the USIM card).
4. If you are required to enter a pin # then a message will appear to prompt you to enter a pin #. (**Note:** to change pin # go to **Settings ** and click **OK** in **PIN code**.)
5. Click the **Network connection ** button and the **HSPA Modem** interface window will display **Connection Manager**.



### Connection Manager

The connection information is commonly stored on the USIM card supplied by the service provider. However if your service provider requires details such as **IP Address, Username** and **Password** etc. to be entered before connection you can enter them in the **Connection Manager** tab, or save the details in **Profiles**.



Figure 7 - 48  
HSPA Modem  
Interface Window

- Click **Connect**  to connect to your service provider.



*Figure 7 - 49*  
**Connecting to Network**

- The message **“Network is connected”** will be displayed when the network connection is successful.



*Figure 7 - 50*  
**Network is Connected**

- You can then access the internet, download e-mail etc. as per any internet connection.

*Figure 7 - 51*  
**Uploading/  
Downloading Rates  
and Speed**

9. While you are connected the upper right corner of the **HSPA Modem** interface will display the upload and download rates, and the taskbar icon will display the connection speed.



10. To disconnect click the **Disconnect**  icon (**Connection Manager**).
11. The program will disconnect from the service provider.
12. The module will still be on, and you will need to press the **Fn +**  key combination to turn it off.

### Adding a Profile

1. Access the **HSPA Modem** interface from the **Start** menu (**Start > Programs/All Programs > HSPA Modem > HSPA Modem**), or by clicking the desktop icon.
2. Click the **Network connection** , and click **Profiles** (tab).

*Figure 7 - 52*  
**Profiles**



3. Click **Add** (button) and input any **Network Settings** required by your service provider.
4. Click **OK** to save the profile.



*Figure 7 - 53*  
**Network Settings & Profiles**

5. You can **Edit** or **Delete** profiles from the **Profiles** tab.
6. To use a profile click to select it, and then click **Apply** (button) and the settings will be transferred to **Connection Manager**.

### Contacts

1. Access the **HSPA Modem** interface from the **Start** menu (**Start > Programs/All Programs > HSPA Modem > HSPA Modem**), or by clicking the desktop icon.
2. Click **Contacts**  (button).


*Figure 7 - 54*  
**Network Settings & Profiles**



3. Click **Refresh** (button) to download the contacts from the USIM card to the computer.
4. The **Contacts** will then be displayed.
5. Double-click any contact to edit the information (or right-click and select **Edit**).
6. You can also **Export/Import** contacts by clicking the appropriate button.

## Messages

1. Access the **HSPA Modem** interface from the **Start** menu (**Start > Programs/All Programs > HSPA Modem > HSPA Modem**), or by clicking the desktop icon.
2. Click **Messages**  (button).



3. Click **Refresh** (button) to download the messages from the USIM card to the computer.
4. Click **New** (button) to create a new message.
5. You can either type the telephone number in the recipient field, or press **To** (button) to select the contact from the list.



### SMS Service

In addition to standard internet services you may also send and receive SMS text messages using the **HSPA Modem** interface, if your service supports SMS.

Figure 7 - 55  
Network Settings &  
Profiles

## Modules & Options

6. Click to select a contact from the list and then click **Add** (button) and the phone number will automatically be added to the recipient field.
7. Type the message information into the message body and click **Send** (button) to send it, or **Save to draft** (button) to save the message.
8. Select any message to **forward** or **delete** it, or to **reply** to it.


### Settings

1. Access the **HSPA Modem** interface from the **Start** menu (**Start > Programs/All Programs > HSPA Modem > HSPA Modem**), or by clicking the desktop icon.
2. Click **Settings**  (button).



7  
*Figure 7 - 56*  
**Settings**

3. Click **OK** alongside any of the options to configure the settings.
4. The **Network** can be configured for an **Automatic** (usually from the USIM card) or **Manual** connection.
5. The **Network Mode** can be configured for any appropriate mode required.



*Figure 7 - 57*  
Settings - Network/  
Network Mode

6. You can also change your settings for the Pin #, and input your phone number.
7. Exiting the program DOES NOT turn off the 3.75G/HSPA modem module, and you will need to press the **Fn + [ ]** key combination to turn off the module (pay careful attention to this aboard aircraft - see [“Wireless Device Operation Aboard Aircraft” on page 7 - 55](#)).
8. If the module is on and the computer enters a power-saving state, then the power status of the module on resuming from the power-saving state will be as below:
  - If the 3.75G/HSPA modem module is on and the computer is **Shut Down or Restarted**; the module will be **off** when the computer starts up.
  - If the 3.75G/HSPA modem module is on and the computer enters **Sleep or Hibernate**; the module will be **off** when the computer resumes from sleep.



### Wireless Device Operation Aboard Aircraft

The use of any portable electronic transmission devices aboard aircraft is usually prohibited. Make sure the module(s) are OFF if you are using the computer aboard aircraft.

Use the **Fn + ** key combination to toggle power to the 3.75G/HSPA module, and check the indicator to see if the module is powered on or not (see [Table 1 - 3, on page 1 - 11/ Table 1 - 2, on page 1 - 9](#)).

## Mobile Partner

With the **3.75G/HSPA** module and USIM card (supplied by your service provider) installed you may then install the **Mobile Partner** application. The **Mobile Partner** application allows you to directly access your HSPA internet service from the computer.


## Mobile Partner Application Installation

1. Enable power to the module by pressing the **Fn + ** key combination (the on screen icon  will indicate the module's power status).
2. If a *Found New Hardware* window appears, click **Cancel**.
3. Click **Option Drivers** (button).
4. Click **2.3.5G Generation Module > Yes**.
5. Choose the language you prefer and click **OK**.
6. Click **I Agree** (button) to accept the license agreement.
7. Click **Next > Install**.
8. Click **Finish** to restart the computer.
9. Access the **Mobile Partner** application from the **Start** menu (**Start > Programs/All Programs > Mobile Partner**), or by double-clicking the **Mobile Partner** icon on the desktop.

## Mobile Partner Application

You will need to contact your service provider to obtain the exact details of how exactly to configure the settings on this page.

### Profile Management

1. Power on the **3.75G/HSPA** module using the **Fn +**  key combination.
2. Access the **Mobile Partner** application from the **Start** menu (**Start > Programs/ All Programs > Mobile Partner**), or by double-clicking the **Mobile Partner** icon on the desktop .
3. If you have not created a profile, click **Tools** and select **Options**, and then click **Profile Management**.
4. Click **New**  and input the appropriate information for **Profile Name**, **APN** and **Authentication** etc. as supplied by your service provider.
5. Click **Save**  to save the profile.



### Mobile Partner Help

To get help on **Mobile Partner** configuration and settings, click the **Help** menu and select **Online Help** or press **F1**.





Figure 7 - 58  
Profile Management

### Connecting to the Service Provider


1. Power on the **3.75G/HSPA** module using the **Fn +**  key combination.
2. Access the **Mobile Partner** application from the **Start** menu (**Start > Programs/ All Programs > Mobile Partner**), or by double-clicking the **Mobile Partner** icon on the desktop .
3. The software will run and you can select the **Profile Name** from the menu.
4. Click **Connect**  to begin the connection process.

*Figure 7 - 59*  
**Connect**



5. The Mobile Partner application will then display the connection information.

*Figure 7 - 60*  
**Network  
Connection Prompt**



- When the connection is successful you can move the cursor over the network icon in the taskbar to display the connection information.




*Figure 7 - 61*  
**Connected Taskbar Notification**

- You can then access the internet, download e-mail etc. as per any internet connection.
- While you are connected the indicators in the Mobile Partner window will display uploading and downloading icons and a network icon in the taskbar .



- To disconnect click the **Disconnect**  icon, or right click the taskbar icon and select **Disconnect**.



*Figure 7 - 62*  
**Disconnect**

- The program will disconnect from the service provider.

## Modules & Options

11. The module will still be on, and you will need to press the **Fn +**  key combination to turn it off.
12. If you click the **Mobile Partner** close icon  a message will be displayed asking you to click **OK** to confirm the program exit and to **terminate the connection**.

Figure 7 - 63  
Exit Prompt



13. Exiting the program terminates the connection, but DOES NOT turn off the 3.75G/HSPA module, and you will need to press the **Fn +**  key combination to turn off the module (pay careful attention to this aboard aircraft - see *“Wireless Device Operation Aboard Aircraft” on page 7 - 64*).
14. If the module is on and the computer enters a power-saving state, then the power status of the module on resuming from the power-saving state will be as below:
  - If the 3.75G/HSPA module is on and the computer is **Shut Down or Restarted**; the module will be **off** when the computer starts up.
  - If the 3.75G/HSPA module is on and the computer enters **Sleep or Hibernate**; the module will be **off** when the computer resumes from sleep.

## GPS Module

If you have included an Global Positioning System (**GPS**) receiver module in your purchase option, you will need to obtain map software suitable for your global location. Map software programs are both commercially available and downloadable directly from the internet.

A Global Positioning System satellite continually transmits high-frequency radio signals containing the time and location of the satellite in relation to the earth. Your computer's GPS receiver obtains information from satellites and calculates your current position on the planet (to an accuracy of between 3 and 15 meters).

For the best quality signal use the **optional** antenna and screw the antenna into the GPS Active Aerial Socket on the right of the computer (see *“System Map: Right View” on page 1 - 14*).



# Chapter 8: Troubleshooting

## Overview

Should you have any problems with your computer, before consulting your service representative, you may want to try to solve the problem yourself. This chapter lists some common problems and their possible solutions. This can't anticipate every problem, but you should check here before you panic. If you don't find the answer in these pages, make sure you have followed the instructions carefully and observed the safety precautions in the preface. If all else fails, talk to your service representative. You should also make a record of what happened and what remedies you tried.

Of course, if something goes wrong, it will happen at the most inconvenient time possible, so you should preview this section just in case. If, after you've tried everything, and the system still won't cooperate, try turning it off for a few minutes and then rebooting. You will lose any unsaved data, but it may start working again. Then call your service representative.

# Basic Hints and Tips

Many of the following may seem obvious but they are often the solution to a problem when your computer appears not to be working.

- **Power** - Is the computer actually plugged into a working electrical outlet? If plugged into a **power strip**, make sure it is actually working. Check the **LED Power & Communication Indicators** (see “*LED Indicators*” on page 1 - 9) to see the computer’s power status.
- **Connections** - Check all the **cables** to make sure that there are no **loose connections** anywhere.
- **Power Savings** - Make sure that the system is not in **Hibernate** or **Sleep** mode by pressing the keys configured in your *Power Options* (see “*Power-Saving States*” on page 3 - 6), the **Fn + F4** key combination, or power button to wake-up the system.
- **Brightness** - Check the brightness of the screen by pressing the **Fn + F8 and F9** keys to adjust the brightness.
- **Display Choice** - Press **Fn + F7** to make sure the system is not set to “external only” display.
- **Boot Drive** - Make sure there are no **optical media and/or USB storage devices** in any connected drive (this is a common cause of the message “*Invalid system disk - Replace the disk, and then press any key*” / “*Remove disks or other media. Press any key to restart*”).

## Backup and General Maintenance

- Always **backup** your important data, and keep copies of your OS and programs safe, but close to hand. Don't forget to note the **serial numbers** if you are storing them out of their original cases, e.g. in a CD wallet.
- Run **maintenance programs** on your hard disk and OS as often as you can. You may schedule these programs to run at times when you are not using your computer. You can use those that are provided free with your OS, or buy the more powerful dedicated programs to do so.
- Write down your passwords and keep them safe (away from your computer). This is especially important if you choose to use a **Supervisor** password for the BIOS (see *“The Power-On Self Test (POST)” on page 5 - 2*).
- Keep copies of vital **settings files** such as network, dialup settings, mail settings etc.(even if just brief notes).



### Warranty

The CPU is not a user serviceable part. Opening this compartment, or accessing the CPU in any way, may violate your warranty.

# Viruses

- Install an **Anti-Virus** program and keep the **definitions file** (the file which tells your program which viruses to look for) up to date. New computer viruses are discovered daily, and some of them may seriously harm your computer and cause you to lose data. **Anti-Virus** programs are commercially available and the **definitions file updates** are usually downloadable directly from the internet.
- Be careful when opening e-mail from sources you don't know. **Viruses** are often triggered from within **e-mail attachments** so take care when opening any attached file. You can configure most **Anti-Virus** programs to check all **e-mail attachments**. **Note:** You should also beware of files from people you know as the virus may have infected an **address book** and been automatically forwarded without the person's knowledge.
- Keep a "**Bootable CD-ROM/DVD-ROM/USB storage device**" (this CD/DVD/USB device provides basic information which allows you to startup your computer) handy. You may refer to your OS's documentation for instructions on how to make one, and many **Anti-Virus** programs will also provide such a disk (or at least instructions on how to make one).

## Upgrading and Adding New Hardware/Software

- Do not be tempted to make changes to your **Windows Registry** unless you are very sure of what you are doing, otherwise you will risk severely damaging your system.
- Don't open your computer or undertake any repair or upgrade work if you are not comfortable with what you are doing.
- Read the **documentation**. We can assume, since you are reading this that you are looking at the computer's manual, but what about any new peripheral devices you have just purchased? Many problems are caused by the installation of new hardware and/or software. Always refer to the documentation of any new hardware and/or software, and pay particular attention to files entitled "**READ ME**" or "**READ ME FIRST**".
- When installing a new device always make sure the device is powered on, and in many cases you will need to restart the computer. Always check that all the cables are correctly connected.
- Make sure you have installed the **drivers** for any new hardware you have installed (latest **driver files** are usually available to download from vendor's websites).

## Troubleshooting

- Thoroughly check any **recent changes** you made to your system as these changes may affect one or more system components, or software programs. If possible, go back and undo the change you just made and see if the problem still occurs.
- Don't over complicate things. The less you have to deal with then the easier the source of the problem may be found; **Example** - if your computer has many devices plugged into its ports, and a number of programs running, then it will be difficult to determine the cause of a problem. Try disconnecting all of the devices and restarting the computer with all the peripheral devices unplugged. A process of elimination (adding and removing devices and restarting where necessary) will often find the source of a problem, although this may be time consuming.

## Problems and Possible Solutions

Problem	Possible Cause - Solution
<p>You turned on the <b>power</b> but it doesn't work.</p>	<p><i>Battery missing / incorrectly installed.</i> Check the battery bay, make sure the battery is present and seated properly (the design of the battery only allows it to go in one way). Make sure there's nothing interfering with the battery contacts.</p>
<p>The battery <b>LED power</b> indicator , is blinking orange.</p>	<p><i>Low Battery.</i> Plug in the DC power source. If the computer doesn't start up immediately, turn it off then on again.</p>
<p>You are <b>losing battery power</b> too quickly.</p>	<p><i>The system is using too much power.</i> If your OS has a <i>Power Options</i> scheme (see "<a href="#">Power Plans</a>" on page 3 - 4/<a href="#">Power Schemes</a>" on page D - 19) check its settings. You may also be using an ExpressCard/USB device/external device that is drawing a lot of power.</p>
<p>Actual <b>battery operating time</b> is shorter than expected.</p>	<p><i>The battery has not been fully discharged before being recharged.</i> Make sure the battery is fully discharged and recharge it completely before reusing (see "<a href="#">Battery Information</a>" on page 3 - 10/<a href="#">Battery Information</a>" on page D - 24).</p> <p><i>Power Options have been disabled.</i> Go to the <b>Control Panel</b> in <i>Windows</i> and re-enable the options.</p> <p><i>A peripheral device/USB device/ExpressCard is consuming a lot of power.</i> Turn off/remove the unused device to save power.</p>

## Troubleshooting

Problem	Possible Cause - Solution
<p>The computer feels <b>too hot</b>.</p>	<p>Make sure the computer is properly ventilated and the Vent/Fan intakes are not blocked. If this doesn't cool it down, put the system into <b>Hibernate</b> mode or turn it off for an hour. Make sure the computer isn't sitting on a thermal surface (see <i>"Overheating" on page 1 - 15</i>). Make sure you're using the correct adapter.</p> <p>Make sure that your notebook is completely powered off before putting it into a travel bag (or any such container). Putting a notebook which is powered on in a travel bag may cause the Vent/Fan intakes to be blocked.</p>
<p><b>Nothing appears</b> on screen.</p>	<p><i>The system is in a power saving mode.</i> Toggle the sleep/resume key combination, <b>Fn + F4</b> (see <i>"Configuring the Power Buttons" on page 3 - 8</i>/<i>"Configuring the Power Button" on page D - 23</i>).</p> <p><i>The screen controls need to be adjusted.</i> Toggle the screen control key combinations <b>Fn + F8/F9</b>. If you're connected to an external monitor, make sure it's plugged in and turned on. You should also check the monitor's own brightness and contrast controls.</p> <p><i>The computer is set for a different display.</i> Toggle the screen display key combination, <b>Fn + F7</b>. If an external monitor is connected, turn it on.</p> <p><i>The <b>screen saver</b> is activated.</i> Press any key or touch the <b>Touchpad</b>.</p>
<p>No image appears on the <b>external monitor</b> I have plugged in and powered on.</p>	<p><i>You haven't installed the video driver and configured it appropriately from the <b>Control Panel</b>.</i> See <i>Appendix B/"Video Features" on page D - 7</i> for instructions on installing and configuring the video driver.</p>

Problem	Possible Cause - Solution
You forget the <b>boot password</b> .	<i>If you forget the password, you may have to discharge the battery of the CMOS. Contact your service representative for help.</i>
 <p><b>Password Warning</b></p> <p>If you choose to set a boot password, <b>NEVER</b> forget your password. The consequences of this could be serious. If you cannot remember your boot password you must contact your vendor and you may lose all of the information on your hard disk.</p>	
The sound cannot be heard or the <b>volume is very low</b> .	<i>The volume might be set too low. Check the volume control in the <b>Volume Control Panel</b> in the Windows taskbar, or use the key combination <b>Fn + F5</b> and <b>F6</b> (see <b>“Audio Features” on page 2 - 9</b>“<b>Audio Features” on page D - 6</b>) to adjust.</i>
The CD/DVD <b>cannot be read</b> .	<i>The CD/DVD is dirty. Clean it with a CD/DVD cleaner kit.</i>
The CD/DVD <b>tray will not open</b> when there is a disc in the tray.	<i>The CD/DVD is not correctly placed in the tray. Gently try to remove the disc using the eject hole (see <b>“Loading Discs” on page 2 - 3</b>).</i>
The <b>DVD regional codes</b> can no longer be changed.	<i>The code has been changed the maximum <b>5</b> times. See <b>“DVD Regional Codes” on page 2 - 5/ “DVD Regional Codes” on page D - 2</b>.</i>

## Troubleshooting

Problem	Possible Cause - Solution
<b>Unwelcome numbers</b> appear when typing.	If the LED  is lit, then Num Lock is turned <b>ON</b> (see <a href="#">“LED Indicators” on page 1 - 9</a> ).
 <h3>Other Keyboards</h3> <p>If your keyboard is damaged or you just want to make a change, you can use any standard USB keyboard. The system will detect and enable it automatically. However special functions/hot keys unique to the system's regular keyboard may not work.</p>	
The <b>system freezes</b> or the screen goes dark.	<i>The system's power saving features have timed-out.</i> Use the AC/DC adapter, press the sleep ( <b>Fn + F4</b> ) key combination, or press the power button if no LEDs are lit.
The system never goes into a <b>power saving mode</b> .	Power Options features are not enabled. Go to the <b>Windows</b> Power Options menu and enable the features you prefer (see <a href="#">“Power-Saving States” on page 3 - 6</a> / <a href="#">“System Power Options” on page D - 21</a> ). Make sure you have enabled <b>Hibernate</b> mode from the control panel.
The <b>Wireless LAN/Bluetooth/3.75G</b> modules cannot be detected.	<i>The modules are off.</i> Check the LED indicator (  ) and/or function key indicator  to see if the WLAN/Bluetooth/3.75G module is on or off (see <a href="#">“LED Indicators” on page 1 - 9</a> ). If the LED indicator is off, then press the <b>Fn + F11 (WLAN)</b> , <b>Fn + F12 (Bluetooth)</b> or <b>Fn + </b> ( <b>3.75G</b> ) key combination(s) in order to enable the modules (see <a href="#">“Function Keys &amp; Visual Indicators” on page 1 - 11</a> ).

Problem	Possible Cause - Solution
The <b>PC Camera</b> module cannot be detected.	<i>The module is off. Press the <b>Fn + F10</b> key combination in order to enable the module (see “<b>Function Keys &amp; Visual Indicators</b>” on page 1 - 11). Run the camera program to view the camera picture.</i>
The <b>Wireless LAN/ PC Camera/3.75G</b> modules cannot be configured.	<i>The driver(s) for the module(s) have not been installed. Make sure you have installed the driver for the appropriate module (see the instructions for the appropriate module in “<b>Modules &amp; Options</b>” on page 7 - 1/“<b>Module Drivers</b>” on page D - 33).</i>
A file cannot be copied to/from a connected <b>Bluetooth</b> device.	<i>The transfer of data between the computer and a Bluetooth enabled device is supported <b>in one direction only (simultaneous data transfer is not supported)</b>. If you are copying a file from your computer to a Bluetooth enabled device, you will not be able to copy a file from the Bluetooth enabled device to your computer until the file transfer process from the computer has been completed.</i>
The <b>Card Reader/ Network (LAN) Device</b> does not appear in the <b>Device Manager</b> in <b>Windows</b> .	<i>This is a power saving feature. When not in use the Card Reader/Network (LAN) Device will not appear in the <b>Windows Device Manager</b> as they are not consuming any power. However as soon as the Card Reader is reading from/writing to an inserted card, or the LAN card is experiencing network activity, the device will reappear in the <b>Windows Device Manager</b>.</i>



## Troubleshooting

Problem	Possible Cause - Solution
The <b>Hibernate</b> function has disappeared.	<p>You have a computer with <b>4GB</b> of RAM and have installed <b>Windows Vista Service Pack 1</b>. This is a known issue if your computer has <b>4GB</b> of RAM and is running <b>Windows Vista Service Pack 1</b>. To re-enable <b>Hibernate</b> mode go to the <b>Command Prompt</b> and type the command "<b>powercfg -h on</b>" (make sure you are logged on as an Administrator):</p> <ol style="list-style-type: none"><li>1. Click <b>Start</b>  (menu button).</li><li>2. Type "<b>cmd</b>" in the <b>Start Search</b> box .</li><li>3. Double click the <b>Command Prompt</b>  <b>cmd</b> when it appears in the menu.</li><li>4. Type "<b>powercfg -h on</b>" in the Command Prompt window.</li><li>5. Close the Command Prompt window.</li><li>6. The <b>Hibernate</b> function will now be enabled.</li></ol>

## Screen Resolution Error

If you are experiencing either screen resolution reduction, or screen flickering **after resuming from Sleep in Windows Vista only** then follow the instructions below to fix this problem. This error arises in compliance with **Windows Vista** policy, which triggers **TMM** (Transient Multi-Monitor Manager) when the notebook lid (**S3**) is closed. **TMM** disconnects the LCD display from the OS and then adds the LCD display back when the lid is opened. This may trigger **TMM** to restore an old display setting which may result in screen flickering or a screen resolution change. To fix this problem you will need to disable **TMM** in the OS:

1. Go to the **Control Panel** in the **Windows OS** and double-click the **Administrative Tools** icon (**System and Maintenance**).
2. Double-click **Task Scheduler (Schedule Tasks)**.




Figure 8 - 1 - Control Panel System and Maintenance

## Troubleshooting

3. Double-click **Task Scheduler Library > Microsoft > Windows**.
4. Click **MobilePC** to open the control panel.
5. Right-click **TMM** and select **Disable**.




Figure 8 - 2 - TMM Disable

6. Close all the control panels.

# Appendix A: Interface (Ports & Jacks)

## Overview

The following chapter will give a quick description of the interface (ports & jacks) which allow your computer to communicate with external devices, connect to the internet etc.

# Notebook Ports and Jacks

Item	Description
Card Reader Port  MMC / SD / MS	The card reader allows you to use some of the latest digital storage cards. Push the card into the slot and it will appear as a removable device.
DC-In Jack 	Plug the supplied AC/DC adapter into this jack to power your computer.
External Monitor (VGA) Port 	This port allows you to connect an external monitor, or Flat Panel Display, to get dual video or simultaneous display on the LCD and external monitor/FPD.
Headphone-Out Jack 	Headphones or speakers may be connected through this jack. <b>Note:</b> Set your system's volume to a reduced level before connecting to this jack.
Microphone-In Jack 	Plug an external microphone in to this jack to record on your computer.
RJ-45 LAN Jack 	This port supports LAN (Network) functions. <b>Note:</b> Broadband (e.g. ADSL) modems usually connect to the LAN port.

## Interface (Ports & Jacks)

Item	Description
Security Lock Slot 	To prevent possible theft, a Kensington-type lock can be attached to this slot. Locks can be purchased at any computer store.
Serial (COM1) Port 	The serial communication port allows you to connect various RS232 supported devices to the computer. Serial ports are still used in legacy applications e.g. industrial automation systems.
S/PDIF-Out Jack 	This S/PDIF (Sony/Philips Digital Interface Format) Out Jack allows you to connect your DVD-capable PC to a Dolby AC-3 compatible receiver for "5.1" or 'dts' surround sound.
USB 2.0/1.1 Ports 	These USB 2.0 compatible ports (USB 2.0 is fully USB 1.1 compliant) are for low-speed peripherals such as keyboards, mice or scanners, and for high-speed peripherals such as external HDDs, digital video cameras or high-speed scanners etc. Devices can be plugged into the computer, and unplugged from the computer, without the need to turn the system off (if the power rating of your USB device is 500mA or above, make sure you use the power supply which comes with the device).

## Interface (Ports & Jacks)

A

# Appendix B: Intel Video Driver Controls

The basic settings for configuring the LCD are outlined in “*Video Features*” on [page 1 - 17](#).

## Intel Video Driver Installation

Make sure you install all the drivers in the order indicated in [Table 4 - 1, on page 4 - 3](#).

### Video

1. Insert the *Device Drivers & Utilities + User’s Manual* disc into the CD/DVD drive.
2. Click **Install Drivers**.
3. Click **2.Install Video Driver > Yes**.
4. Click **Next > Yes > Next > Next**.
5. Click **Finish** to restart the computer.

### Dynamic Video Memory Technology

Intel® DVMT automatically and dynamically allocates as much (up to **256MB**) system memory (RAM) as needed to the video system (**the video driver must be installed**). DVMT returns whatever memory is no longer needed to the operating system.



#### DVMT Notes

DVMT is not local video memory.

DVMT is not user-configurable.

DVMT will not function in MS-DOS. DOS uses the legacy memory indicated.



### Taskbar Icon


The **Intel GMA** control panel can also be accessed by clicking the icon  in the taskbar and selecting **Graphics Properties** from the menu.

If you cannot see the tray icon click the “**Show Tray Icon**” tickbox in the **Intel(R) Graphics Media Accelerator for Mobile** tab.

## Intel Graphics Properties

More advanced video configuration options are provided by the **Intel(R) Graphics Media Accelerator Driver for Mobile**.

1. Open the **Display Settings** control panel (see “**Video Features**” on page 1 - 17) and click **Advanced Settings** (button).
2. Click the **Intel(R)...** tab and click **Graphics Properties** (button).



*Figure B - 1*  
**Intel Graphics Properties**

B

You may make changes to the devices, color, schemes, **Hot Keys** etc. by clicking the appropriate menu item or button.






## Help Menus

Right-click on many of the items in the tabs to bring up the “What’s This?” button.

Click the “What’s This?” button to bring up the help menu.

## Operating Mode

At least one other display must be attached in order to view **Display Selection** options.



*Figure B - 2*  
**Intel Graphics Media Accelerator Driver for mobile (Control Panel Tabs)**

**B**



### Application.exe


You will need to locate the actual **application executable (.exe) file**, not just the shortcut. To find the application right-click its **shortcut** on the desktop click **Properties**. Click the **Shortcut** (tab) and see where the executable file is located by clicking the **Find Target** (button). Note the location and you will then be able to browse to this file.

## Scheme Options

Use Scheme Options to configure quick settings for applications which require specific resolution and color settings in order to run properly e.g. games, multimedia programs. To set the scheme options:

1. Open the **Display Settings** control panel and click **Advanced Settings** (button).
2. Click the **Intel(R)...** tab and click **Graphics Properties** (button).
3. Configure your display configuration, resolution etc. as per your requirements from **Display Settings**.
4. Click on **Scheme Options** (button).
5. Type a name for the scheme then click **Save**.
6. Click the tickbox "**Automatically launch an application when the scheme is applied**" If you want to run a scheme when opening an application.
7. Click **Browse** to find the executable file for the application you want to set the scheme for (see sidebar), and click **Open** to select it.
8. Click **Save (Save > OK)** to save the settings (you can click in the "**Restore the display settings after exiting this application**" box to return to your original settings when you exit the program).
9. Click **OK** to exit the window.
10. Click the taskbar icon  and **Select Scheme** to run it.

*Figure B - 3*  
**Select Scheme**




## Attaching Other Displays

Besides the built-in LCD, you can also use an external monitor/flat panel display, connected to the external monitor port at the rear of the computer, as your display device. The following are the display options:

1. The built-in LCD **OR** an external monitor/flat panel display connected to the external monitor port (**Single Display**).
2. The built-in LCD **AND** an external monitor/flat panel display connected to the external monitor port (**Multiple Display**).

### Configuring from Windows Vista

1. Attach your external display to the external monitor port, and turn it on.
2. If a **New Display Detected** window does not appear in **Windows Vista**, go to the **Windows Mobility Center** control panel (**Mobile PC > Adjust commonly used mobility settings**) and click **Connect display**.
3. Click on any of the buttons to configure the displays to your preference, or click **Display Settings** to access the control panel.



### Function Key Combination

You can use the **Fn + F7** key combination to toggle through the display options:

- Notebook Only
- External Display Only
- Notebook + External Display

Make sure you give the displays enough time to refresh.

Figure B - 4  
Windows Mobility  
Center

## Intel Video Driver Controls




### Operating Mode

At least one other display must be attached in order to view **Display Selection** options.

### Configuring from Intel® GMA Driver for Mobile

1. Go to the **Intel Graphics Properties** control panel (see *“Intel Graphics Properties” on page B - 2*) and click **Display Devices**.
2. Click to choose the display option from the **Operating Mode** menu.
3. Click **Apply** (and **OK** to confirm the settings change) and **OK** (button).



*Figure B - 5*  
**Display Devices**

## Display Modes

### Single Display

Only one of your attached displays is used.

### Intel(R) Dual Display Clone (mirrored)

This mode will drive multiple displays with the same content. Each device may be configured independently for different resolutions, refresh rates, color quality etc. Use this feature to display the screen through a projector for a presentation.

### Extended Desktop (extended)

This mode allows a desktop to span multiple displays and acts as a large workspace. This creates a lot more screen area for display. Use the **Display Properties** control panel to drag the monitors to match the physical arrangement you wish to use, or you may also use the **Extended Desktop Settings** control panel tab in **Graphics Properties** to configure the relative size and position.



#### Video Settings


Click **Video Settings** (button) in the **Intel(R) GMA Driver for mobile** control panel to access settings for **Video Quality**, **Color Control** and **Video Scaling**.

## Intel Video Driver Controls

### To Enable Intel(R) Dual Display Clone


1. Attach your external monitor to the external monitor port, and turn it on.
2. Go to the **Intel Graphics Properties** control panel (see *“Intel Graphics Properties” on page B - 2*) and click **Display Devices**.
3. Click to choose **Intel(R) Dual Display Clone (Operating Mode)**.
4. Click **Apply**, and **OK** to confirm the settings change.
5. Click **Display Settings** to adjust the settings for the attached devices.

*Figure B - 6*  
**Display Devices &  
Settings**



## To Enable Extended Desktop

1. Attach your external monitor to the external monitor port, and turn it on.
2. Go to the **Intel Graphics Properties** control panel (see *"Intel Graphics Properties" on page B - 2*) and click **Display Devices**.
3. Click to choose **Extended Desktop (Operating Mode)**.
4. Click **Apply**, and **OK** to confirm the settings change.
5. Click **Display Settings** to adjust the settings for the attached devices.



Click the appropriate monitor icon and drag it to match the physical arrangement you wish to use (e.g. the secondary display may be extended left/right/above/below the primary display).

Click **Display Settings** to make any adjustments required.



### Display Settings Extended Desktop

You can have different Colors, Screen Area and Monitor Refresh Rates for each display device **provided your monitor can support them**.

You can drag the monitor icons to match the physical layout of your displays. Icons and programs may also be dragged between the displays.

*Figure B - 7*  
**Extended Desktop  
Mode**

## Intel Video Driver Controls



### Display Settings Extended Desktop

Use the control panel to drag the monitors to match the physical arrangement you wish to use.

You can drag any icons or windows across to either display desktop, which makes it possible to have one program visible in one of the displays, and a different program visible in the other display.

### Using Windows Vista to Enable Extended Mode

1. Attach your external display to the external monitor port, and turn it on.
2. If a **New Display Detected** window does not appear in *Windows Vista*, go to the **Windows Mobility Center** control panel (**Mobile PC > Adjust commonly used mobility settings**) and click **Connect display**.
3. Click to select **Show different parts of my desktop on each display (extended)**.
4. Click **Right** or **Left** under **Extend your desktop**.
5. Click **Apply > OK**.





Figure B - 8

### Display Properties (Extended Desktop)

B

## Using Display Settings to Enable Extended Mode

1. Attach your external display to the external monitor port, and turn it on.
2. Open the **Display Settings** control panel (see *“Video Features” on page 1 - 17*).
3. Click the monitor icon (e.g. **2**), and make sure you have checked **“Extend my Windows desktop onto this monitor.”** and click **Apply**.



Click the appropriate monitor icon (e.g. **2**) to be able to select the option to extend the desktop on to it.

In this example the Primary Display **1** is on the left, the Secondary Display **2** is on the right.

*Figure B - 9*  
**Display Properties**  
**(Extended Desktop)**



### TV Wizard

Use the TV Wizard to configure the external display settings either manually or automatically.

The wizard will take you through any necessary steps in order to configure the optimal video settings e.g **HDTV Format, Display Size and Position** etc.

## Intel Clear Video Technology

Intel Clear Video Technology is designed to help users get high-quality video playback, sharp image quality, precise color control and advanced support for the latest High Definition displays without the need for expensive video cards etc.

1. Attach your external display to the external monitor port.
2. Go to the **Intel(R) GMA Driver for mobile** control panel (see **“Intel Graphics Properties” on page B - 2**) and configure your external display as the **Single** display from the **Operating Mode** menu.
3. Click **Intel(R) TV Wizard Intel(R) GMA Driver for mobile** control panel.
4. The wizard will now take you through the steps to set up high quality video support for your external display (configure in either **Automatic** or **Manual** modes).




Figure B - 10  
Intel® TV Wizard

# Appendix C: Specifications



## Latest Specification Information

The specifications listed in this Appendix are correct at the time of going to press. Certain items (particularly processor types/speeds and CD/DVD device types) may be changed, updated or delayed due to the manufacturer's release schedule. Check with your service center for details.

## Specifications

<b>Processor</b>	<b>Memory</b>	<b>Storage</b>
<p><b>Intel® Core™2 Duo Processor ULV: SU9300 (1.20GHz)</b> 45nm (45 Nanometer) Process Technology, 3MB L2 Cache &amp; 800MHz FSB - TDP 10W, BGA Socket P Pin-Out, 22 * 22mm CPU On Board</p> <p><b>Intel® Celeron® Processor ULV: 723 (1.20GHz)</b> 45nm (45 Nanometer) Process Technology, 1MB L2 Cache &amp; 800MHz FSB - TDP 10W, BGA Socket P Pin-Out, 22 * 22mm CPU On Board</p>	<p>64-bit Wide <b>DDRII (DDR2)</b> Data Channel Supporting Dual Channel <b>DDRII (DDR2)</b> SDRAM One 200 Pin SO-DIMM Socket Supporting <b>DDRII (DDR2)</b> 800MHz Memory Expandable up to <b>2GB</b></p>	<p>One Changeable 12.7mm(h) Super Multi Optical Device Drive - SATA interface</p> <p>One Changeable 2.5" 9.5 mm (h) HDD OR 2.5" SSD with <b>SATA</b> (Serial) Interface</p>
<b>Core Logic</b>	<b>Video</b>	<b>Audio</b>
<p>Intel® GS45 + ICH9M-SFF Chipset</p>	<p>Intel® GS45 Integrated Video High Preference 3D/2D Graphic Accelerator Shared Memory Architecture of up to 256M Supports Microsoft DirectX 10</p>	<p>High Definition Audio Compliant with Microsoft UAA (Universal Audio Architecture) Direct Sound 3D™ Compatible Built-In Microphone 2 * Built-In Speakers</p>
<b>Display</b>	<b>BIOS</b>	<b>Keyboard &amp; Pointing Device</b>
<p>13.3" WXGA (1280 * 800) LED Backlight Panel</p>	<p>One 32Mb SPI Flash ROM Phoenix™ BIOS</p>	<p>Full Size WinKey Keyboard Built-in TouchPad (integrated scrolling key functionality)</p>

Interface	Communication	Power Management			
<p>Three USB 2.0 Ports            One Serial (COM1) Port            One External Monitor Port            One Headphone-Out Jack            One Microphone-In Jack            One S/PDIF-Out Jack            One RJ-45 LAN Jack for 10/100/1000Mb Fast Ethernet            One DC-In Jack</p>	<p>Built-In 10M/100M/100M Base-TX Ethernet LAN            Bluetooth 2.1 + EDR (Enhanced Data Rate) Module (<b>Factory Option</b>)            Intel® WiFi Link 5300 Series (3*3 - 802.11a/g/n) Wireless LAN PCIe interface Half Mini-Card Module (<b>Option</b>)            Intel® WiFi Link 5100 Series (1*2 - 802.11a/g/n) Wireless LAN PCIe interface Half Mini-Card Module (<b>Option</b>)            3rd Party 802.11b/g Wireless LAN PCIe interface Half Mini-Card Module (<b>Option</b>)            2.0M or 3.0M Pixel PC Camera Module with USB interface (<b>Factory Option</b>)            3.75G Module:            UMTS/HSPDA-based 3.75G Module with Mini-Card Interface (<b>Factory Option</b>)            Quad-band GSM/GPRS (850 MHz, 900 MHz, 1800 MHz, 1900 MHz)            UMTS WCDMA FDD (2100 MHz)  <b>Note that UMTS modes CAN NOT be used in North America</b>            GPS Module without Internal Antenna (<b>Factory Option</b>)</p>	<p>Supports Wake on LAN            Supports Wake on Modem Ring</p> <tr> <th data-bbox="1034 281 1482 330">Power</th> </tr> <p>Full Range AC/DC Adapter            AC input 100 - 240V, 50 - 60Hz,            DC Output 19V, 3.42A or 18.5V, 3.5A (<b>65 Watts</b>)            4 Cell Smart Lithium-Ion Battery Pack, 2600mAH            8 Cell Smart Lithium-Ion Battery Pack, 5200mAH (<b>Option</b>)</p> <tr> <th data-bbox="1034 589 1482 638">Security</th> </tr> <p>Security (Kensington® Type) Lock Slot            Fingerprint ID Reader Module            BIOS Password            Trusted Platform Module V1.2</p> <tr> <th data-bbox="1034 781 1482 831">Operating System</th> </tr> <p>Windows® Vista (with Service Pack 1)            Windows® XP (with Service Pack 3)</p>	Power	Security	Operating System
Power					
Security					
Operating System					
Card Reader					
<p>Embedded 7-in-1 Card Reader (MS/ MS Pro/ SD/ Mini SD/ MMC/ RS MMC/ MS Duo) <b>Note:</b> MS Duo/ Mini SD/ RS MMC Cards require a PC adapter</p>					
Slots					
<p>One ExpressCard/34/54 Slot  <b><u>Two Mini-Card Slots with USB &amp; PCIe interface:</u></b>            Slot 1 for Half Mini-Card WLAN Module            Slot 2 for 3.75G Module (<b>Factory Option</b>)</p>					



## Specifications

Environmental Spec	Optional
Temperature Operating: 5°C - 35°C Non-Operating: -20°C - 60°C Relative Humidity Operating: 20% - 80% Non-Operating: 10% - 90%	Super Multi Optical Device Drive Intel® WiFi Link 5300 Series (3*3 - 802.11a/g/n) Wireless LAN PCIe interface Half Mini-Card Module Intel® WiFi Link 5100 Series (1*2 - 802.11a/g/n) Wireless LAN PCIe interface Half Mini-Card Module 3rd Party 802.11b/g Wireless LAN PCIe interface Half Mini-Card Module 8 Cell Smart Lithium-Ion Battery Pack, 5200mAH Bluetooth 2.1 + EDR (Enhanced Data Rate) Module ( <b>Factory Option</b> ) 2.0M or 3.0M Pixel PC Camera Module with USB interface ( <b>Factory Option</b> ) UMTS/HSPDA-based 3.75G Module with Mini-Card Interface ( <b>Factory Option</b> ) GPS Module without Internal Antenna ( <b>Factory Option</b> )
Dimensions & Weight	
317mm (w) * 229mm (d) * 35mm (h) 2.0 kg (full system with 1G RAM, 2.5" HDD, ODD and 4 Cell Battery)	

# Appendix D: Windows XP Information

This Appendix contains information (including control panel information, driver installation etc.) for users of the *Windows XP OS*.

# DVD Regional Codes



### Changing DVD Regional Codes

Go to the **Control Panel** and double-click **System > Hardware** (tab), click **Device Manager**, then click the **+** next to **DVD/CD-ROM drives**. Double-click on the DVD-ROM device to bring up the **Properties** dialogue box, and select the **DVD Region** (tab) to bring up the control panel to allow you to adjust the regional code.

DVD region detection is device dependent, not OS-dependent. You can select your module's region code **5** times. The fifth selection is permanent. This cannot be altered even if you change your operating system or you use the module in another computer.

Region	Geographical Location
1	USA, Canada
2	Western Europe, Japan, South Africa, Middle East & Egypt
3	South-East Asia, Taiwan, South Korea, The Philippines, Indonesia, Hong Kong
4	South & Central America, Mexico, Australia, New Zealand
5	N Korea, Russia, Eastern Europe, India & Most of Africa
6	China

Table D - 1 - DVD Region Codes




Figure D - 1 - DVD Regions

## Windows XP Start Menu & Control Panel

Most of the control panels, utilities and programs within *Windows XP* (and most other *Windows* versions) are accessed from the **Start** menu. When you install programs and utilities they will be installed on your hard disk drive, and a shortcut will usually be placed in the **Start** menu and/or the desktop. You can customize the look of the **Start** menu by right-clicking the **Start** menu and selecting **Properties** from the menu.



Figure D - 2 - Start Menu & Control Panel

In many instances throughout this manual you will see an instruction to open the **Control Panel**. The **Control Panel** is accessed from the **Start** menu, and it allows you to configure the settings for most of the key features in *Windows* (e.g. power, video, network, audio etc.). *Windows XP* provides basic controls for many of the features, however many new controls are added (or existing ones are enhanced) when you install the drivers. To see all controls it may be necessary to toggle off Category View.

# Touchpad and Buttons/Mouse

The Touchpad is an alternative to the mouse; however, you can also add a mouse to your computer through one of the USB ports. The Touchpad buttons function in much the same way as a two-button mouse.

Once you have installed the Touchpad driver (see *“Touchpad” on page D - 31*) you can configure the functions by double-clicking the Touchpad driver icon  on the **taskbar**. You may then configure the Touchpad tapping, buttons, scrolling, pointer motion and sensitivity options to your preferences. You will find further information at [www.synaptics.com](http://www.synaptics.com).



### Mouse Driver

If you are using an external mouse your operating system may be able to auto-configure your mouse during its installation or only enable its basic functions. Be sure to check the device's user documentation for details.




Figure D - 3 - Mouse Properties

## Function Keys & Visual Indicators

The **function keys** (F1 - F12 etc.) will act as **hot keys** when pressed while the **Fn** key is held down. In addition to the basic function key combinations; visual indicators (see the table below) are available when the hot key driver is installed (see *“Module Drivers” on page D - 33*).

Keys	Function/Visual Indicators	Keys	Function/Visual Indicators
Fn + ~	Play/Pause (in Audio/Video Programs)	Fn + F7	Display Toggle
Fn + 	3.75G Module Power Toggle  	Fn + F8/F9	Brightness Decrease/Increase  
Fn + F1	Touchpad Toggle	Fn + F10	PC Camera Power Toggle  
Fn + F2	Turn LCD Backlight Off (Press a key to or use Touchpad to turn on)	Fn + F11	WLAN Module Power Toggle  
Fn + F3	Mute Toggle  	Fn + F12	Bluetooth Module Power Toggle  
Fn + F4	Sleep Toggle	Fn + NumLk	Number Lock Toggle
Fn + F5/F6	Volume Decrease/Increase  	Fn + ScrLk	Scroll Lock Toggle

Table D - 2 - Function Keys & Visual Indicators

# Audio Features

You can configure the audio options on your computer from the **Sounds and Audio Devices**  *Windows* control panel, or from the **Realtek HD Audio Manager**  icon in the taskbar/control panel (this will bring up the Realtek Audio Configuration menus). The volume may also be adjusted by means of the **Fn + F5/F6** key combination.



### Sound Volume Adjustment

How high the sound volume can be set depends on the setting of the volume control within *Windows* (and the volume control function keys on the computer). Click the Volume icon on the taskbar to check the setting.



The image shows a Windows XP volume control slider. It has a vertical track with a green slider bar in the middle. Below the track is a 'Mute' checkbox, which is currently unchecked. The word 'Volume' is written at the top of the slider.



Figure D - 4 - Realtek Audio Configuration Menus

## Video Features

You can switch display devices, and configure display options, from the **Display Properties** control panel in *Windows* as long as the appropriate **Intel video driver** is installed.

To access Display Properties in *Windows*:

1. Click **Start**, point to **Settings** and click **Control Panel** (or just click **Control Panel**).
2. Double-click **Display** (icon) - In the **Appearances and Themes** category.
3. Click **Settings** (tab) in the **Display Properties** dialog box.
4. Move the slider to the preferred setting in **Screen resolution** ① (*Figure D - 5 on page D - 8*).
5. Click the arrow, and scroll to the preferred setting in **Color quality** ② (*Figure D - 5 on page D - 8*).
6. Open the **Display Properties** control panel, and click **Advanced** (button) ③ (*Figure D - 5 on page D - 8*) to bring up the Advanced properties tabs.
7. The **Intel GMA** control panel can be accessed by clicking the icon  in the taskbar and selecting **Graphics Properties** from the menu (or from the **Intel GMA Driver for Mobile Control Panel** in the *Windows* control panel).

### Dynamic Video Memory Technology



Intel® DVMT automatically and dynamically allocates as much (up to **256MB**) system memory (RAM) as needed to the video system (**the video driver must be installed**). DVMT returns whatever memory is no longer needed to the operating system.

## Display Properties

### Taskbar Icon

The **Intel GMA** control panel can also be accessed by clicking the icon  in the taskbar and selecting **Graphics Properties** from the menu.

If you cannot see the tray icon click the **“Show Tray Icon”** tickbox in the **Intel(R) Graphics Media Accelerator for Mobile** tab.



Right-click taskbar icon




Figure D - 5 - Display Properties & Intel GMA Driver for Mobile Control Panel

# Intel GMA Driver Controls

Access the **Intel GMA** control panel as indicated *on page D - 7*. You may make changes to the Display Devices, Display Settings, Color Correction, Hot Keys etc. by clicking the appropriate menu item.




Figure D - 6 - Intel GMA Driver for Mobile



## Help Menu

Right-click on many of the items in the tabs to bring up the “What’s This?” button.

Click the “What’s This?” button to bring up the help menu.

## Operating Mode

At least one other display must be attached in order to view **Display Selection** options.



### Application.exe

You will need to locate the actual **application executable (.exe) file**, not just the shortcut. To find the application right-click its **shortcut** on the desktop click **Properties**. Click the **Shortcut** (tab) and see where the executable file is located by clicking the **Find Target** (button). Note the location and you will then be able to browse to this file.

## Scheme Options

Use Scheme Options to configure quick settings for applications which require specific resolution and color settings in order to run properly e.g. games, multimedia programs. To set the scheme options:

1. Open the **Display Settings** control panel and click **Advanced Settings** (button).
2. Click the **Intel(R)...** tab and click **Graphics Properties** (button).
3. Configure your display configuration, resolution etc. as per your requirements from **Display Settings**.
4. Click on **Scheme Options** (button).
5. Type a name for the scheme then click **Save**.
6. Click the tickbox "**Automatically launch an application when the scheme is applied**" if you want to run a scheme when opening an application.
7. Click **Browse** to find the executable file for the application you want to set the scheme for (see sidebar), and click **Open** to select it.
8. Click **Save (Save > OK)** to save the settings (you can click in the "**Restore the display settings after exiting this application**" box to return to your original settings when you exit the program).
9. Click **OK** to exit the window.
10. Click the taskbar icon  and **Select Scheme** to run it.

*Figure D - 7*  
**Select Scheme**



## Display Devices & Options

Besides the built-in LCD you can also use an external monitor/flat panel display connected to the external monitor port as your display device. The following are the display options:

Intel Display Mode	Description
Single Display	One of the connected displays is used as the display device
Multiple Display - Intel(R) Dual Display Clone	Both connected displays output the same view and may be configured independently
Multiple Display - Extended Desktop	Both connected displays are treated as separate devices, and act as a virtual desktop

*Figure D - 8 - Display Options*



### Function Key Combination

You can use the **Fn + F7** key combination to toggle through the display options:

- Notebook Only
- External Display Only
- Notebook + External Display

Make sure you give the displays enough time to refresh.

### Attaching Other Displays (Intel GMA)

1. Attach your external display to the external monitor port and turn it on.
2. Go to the **Intel GMA** control panel and click **Display Devices**.
3. Click to choose the display option from the **Operating Mode** menu.
4. Click to choose the display selection from the **Display Selection** menu.
5. Click **Apply**, and **OK** to confirm the settings change.



#### Function Key Combination

You can use the **Fn + F7** key combination to toggle through the display options:

- Notebook Only
- External Display Only
- Notebook + External Display

Make sure you give the displays enough time to refresh.




Figure D - 9 - Display Devices

## To Enable Intel(R) Dual Display Clone (Intel GMA)

1. Attach your external display to the external monitor port and turn it on.
2. Go to the **Intel GMA** control panel and click **Display Devices**.
3. Click to choose **Intel(R) Dual Display Clone** from the **Operating Mode** menu.
4. Choose which device is to be the **Primary Device** from the **Display Selection** menu.
5. Click **Apply**, and **OK** to confirm the settings change.
6. Click **Display Settings** to adjust the settings for the attached devices.




Figure D - 10 - Display Devices - Intel(R) Dual Display Clone

## Windows XP Information


### To Enable Extended Desktop (Intel GMA)

1. Attach your external display to the external monitor port and turn it on.
2. Go to the **Intel GMA** control panel and click **Display Devices**.
3. Click to choose **Extended Desktop** from the **Operating Mode** menu.
4. Choose which device is to be the **Primary Device** from the **Display Selection** menu.
5. Click **Apply**, and **OK** to confirm the settings change.
6. Click **Display Settings** to adjust the settings for the attached devices.

#### Display Settings Extended Desktop

You can have different Color Quality, Screen Resolution and Refresh Rates for each display device **provided your monitor can support them**.

You can drag the monitor icons to match the physical layout of your displays. Icons and programs may also be dragged between the displays.




Click the appropriate monitor icon and drag it to match the physical arrangement you wish to use (e.g. the secondary display may be extended left/right/above/below the primary display).

Click Display Settings to make any adjustments required.

Figure D - 11 - Display Devices - Extended Desktop

## To Enable Extended Desktop (Windows Display Properties)

1. Attach your external display to the external monitor port and turn it on.
2. Click **Start**, point to **Settings** (or click **Control Panel**) and click **Control Panel** (if you are in **Category View** choose **Appearance and Themes**).
3. Double-click **Display** (icon).
4. In the **Display Properties** dialog box, click **Settings** (tab).
5. Click the monitor icon (e.g. **2**), and make sure you have checked “**Extend my Windows desktop onto this monitor.**” and click **Apply**.



Click the appropriate monitor icon (e.g. **2**) to be able to select the option to extend the desktop on to it.

In this example the Primary monitor **1** is on the left, the secondary display **2** is on the right.

### Display Settings Extended Desktop

Use the control panel to drag the monitors to match the physical arrangement you wish to use.

You can drag any icons or windows across to either display desktop, which makes it possible to have one program visible in one of the displays, and a different program visible in the other display.

Figure D - 12 - Display Properties (Extended Desktop)



### OS Note

Power management functions will vary slightly depending on your operating system. For more information it is best to refer to the user's manual of your operating system.

(**Note:** All pictures used on the following pages are from the *Windows XP OS*.)

## Power Management Features

To conserve power, especially when using the battery, your computer uses the ACPI power management system. Power management conserves power by controlling individual components of the computer (the monitor and hard disk drive) or the whole system.

The **Power Options** control panel icon in *Windows* (see page *D - 3*) allows you to configure power management features for your computer. You may conserve power through individual components such as the monitor or hard disk, or you may use either **Stand by** or **Hibernate** mode to conserve power throughout the system.

## Advanced Configuration and Power Interface

The **ACPI** interface provides the computer with enhanced power saving techniques and gives the operating system (OS) direct control over the power and thermal states of devices and processors. For example, it enables the OS to set devices into low-power states based on user settings and information from applications. ACPI is fully supported in *Windows XP*.

## The Power Sources

The computer can be powered by either an AC/DC adapter or a battery pack.

### AC/DC Adapter

Use only the AC/DC adapter that comes with your computer. The wrong type of AC/DC adapter will damage the computer and its components.

1. Attach the AC/DC adapter to the DC-in jack on the left of the computer.
2. Plug the AC power cord into an outlet, and then connect the AC power cord to the AC/DC adapter.
3. Raise the lid/LCD to a comfortable viewing angle.
4. Press the power button to turn “On”.

### Battery

The battery allows you to use your computer while you are on the road or when an electrical outlet is unavailable. Battery life varies depending on the applications and the configuration you're using. **To increase battery life, let the battery discharge completely before recharging** (see *“How do I completely discharge the battery?” on page D - 27*).

We recommend that you do not remove the battery. For more information on the battery, please refer to *“Battery Information” on page D - 24*.



### Shutdown

Note that you should always shut your computer down by choosing the **Turn Off Computer** command from the **Start** menu in *Windows*. This will help prevent hard disk or system problems.

## Turning on the Computer

Now you are ready to begin using your computer. To turn it on simply press the power button on the front panel.

When the computer is on, you can use the power button as a Stand by/Hibernate/Shutdown hot-key button when it is pressed for less than **4 seconds** (pressing and holding the power button for longer than this will shut the computer down). Use **Power Options** in the *Windows* control panel to configure this feature.



### Forced Off

If the system “hangs”, and the **Ctrl + Alt + Del** key combination doesn’t work, press the power button for **4 seconds**, or longer, to force the system to turn itself off.

### Power Button as Stand by or Hibernate Button

If you are using a fully ACPI-compliant OS, (such as Windows XP) you can use the OS’s “Power Options” control panel to set the power button to send the system into Stand by or Hibernate mode (see your OS’s documentation, or [“Configuring the Power Button” on page D - 23](#) for details).

## Power Schemes

You can set your computer to conserve power through individual components by means of **Power Schemes**. You can also adjust the settings for each scheme to set the monitor to turn off after a specified time, and the computer's hard disk motor to turn off if the hard disk drive has not been accessed for a specified period of time (if the system reads or writes data, the hard disk motor will be turned back on). The schemes may also be set to set a specified time for the system to enter **Stand by** or **Hibernate** modes (see *“System Power Options” on page D - 21*).



### Resuming Operation

Press a key on the keyboard, or move the mouse/TouchPad to resume from Monitor or Hard Disk Stand by.




Figure D - 13  
Power Schemes

## Windows XP Information

Each **Windows Power Scheme** will also adjust the processor performance of your machine in order to save power. This is worth bearing in mind if you are experiencing any reduced performance (especially under DC/battery power).

Choose the **Home/Office Desk** scheme for maximum performance when the computer is powered from an AC power source. Choose the **Max Battery** scheme (bear in mind that this scheme may slow down the overall performance of the computer in order to save power) for maximum power saving when the computer is battery (DC power) powered. **Windows** will use **Portable/Laptop** as the default scheme.

## System Power Options

You can use the system power options to stop the computer's operation and restart where you left off. This system features **Stand by** and **Hibernate** sleep mode levels (**Hibernate** mode will need to be enabled by clicking the option in the **Hibernate** tab in the **Power Options** control panel - see "*Hibernate*" on page D - 22).

### Hibernate Mode vs. Shutdown

Hibernate mode and Shutdown are the same in that the system is off and you need to press the power button to turn it on. Their main difference is:

When you come back from hibernation, you can return to where you last left off (what was on your desktop) without reopening the application(s) and file(s) you last used.

You can use either method depending on your needs.

### Stand by Mode vs. Hibernate Mode

If you want to stay away from your work for just a while, you can put the system on Stand by instead of in hibernation. It takes a longer time to wake up the system from **Hibernate** mode than from **Stand by** mode.



#### Stand by/Hibernate or Shutdown Error

The computer may stop responding when you put it into (or resume from) Stand By or Hibernate, or when you shut down.

This error is caused by power management within **Windows XP**, when applied to a **PC Camera** attached to the internal USB hub.

Microsoft has posted a Hotfix for this error on its website (search for Hotfix KB909667).

Download and install the Hotfix to correct this error.



### System Resume

The system can resume from Stand by mode by:

- Pressing the power button
- Pressing the **Sleep/Resume** key combination
- Network card (Wake On LAN) activity (if enabled)

### Stand by

Stand by saves the least amount of power, but takes the shortest time to return to full operation. During Stand by the hard disk is turned off, and the CPU is made to idle at its slowest speed. All open applications are retained in memory. When you are not using your computer for a certain length of time, which you specify in the operating system, it will enter Stand by mode to save power.

### Hibernate

Hibernate uses no power and saves all of your information on a part of the HDD before it turns the system off. Although it saves the most power it takes the longest time to return to full operation. You can set your computer to automatically enter Hibernate mode when the battery power is almost depleted. You will need to enable Hibernate mode from the **Hibernate** tab in the Power Options control panel. **The system will resume from Hibernate mode by pressing the power button.**



*Figure D - 14*  
**Enable Hibernation**

## Configuring the Power Button

The power button may be set to send the computer in to either **Stand by** or **Hibernate** mode. In **Stand by** mode, the LED  will blink green. In **Hibernate** mode the LED will be off (battery) or orange (AC/DC adapter). If you are in a power saving mode set to save power through individual components (e.g. hard disk, monitor), the LED will remain green.



### Sleep Button

You may also configure the **Sleep/Resume** key combination (**Fn + F4**) from the menu illustrated. In **Windows** this is referred to as the **Sleep** button.



Power Button

Lid

Sleep/Resume  
(Sleep) Button

*Figure D - 15*  
**Power Options  
(Advanced - Power  
Buttons)**



### Low Battery Warning

When the battery is critically low, immediately connect the AC/DC adapter to the computer or save your work, otherwise, the unsaved data will be lost when the power is depleted.

## Battery Information

Please follow these simple guidelines to get the best use out of your battery.


### New Battery

Always completely discharge, then fully charge, a new battery (see *“Battery FAQ” on page D - 27* for instructions on how to do this).

### Battery Life

Your computer’s battery life is dependent upon many factors, including the programs you are running, and peripheral devices attached. **Power Options** (you may set low battery **Alarms** and actions, and check the **Power Meter** from the **Power Options** control panel), and settings in the OS will help prolong the battery life if configured appropriately.

*Figure D - 16*  
**Power Options**  
**(Alarm & Power**  
**Meter)**



Battery life may be shortened through improper maintenance. **To optimize the life and improve its performance, fully discharge and recharge the battery at least once every 30 days.**

We recommend that you do not remove the battery yourself. If you need to remove the battery for any reason, see *“Removing the Battery” on page 6 - 3.*

## Recharging the Battery with the AC/DC Adapter

The battery pack automatically recharges when the AC/DC adapter is attached and plugged into an electrical outlet. If the computer is powered on, and in use, it will take several hours to fully recharge the battery. When the computer is turned off but plugged into an electrical outlet, battery charge time is less. (Refer to *“LED Indicators” on page 1 - 9* for information on the battery charge status, and to *“Battery Information” on page D - 24* for more information on how to maintain and properly recharge the battery pack.)



### Conserving Battery Power

To conserve battery power:

Lower the brightness level of the LCD display. The system will decrease LCD brightness slightly to save power when it is not powered by the AC/DC adapter.

Close modem or communication applications when they are not being used.

Remove any unused PC Cards from the computer (PC Cards quickly use up battery power even if the system enters sleep mode).

Disconnect any unnecessary external devices.

### Proper handling of the Battery Pack

- DO NOT disassemble the battery pack under any circumstances
- DO NOT expose the battery to fire or high temperatures, it may explode
- DO NOT connect the metal terminals (+, -) to each other



#### Damaged Battery Warning

Should you notice any physical defects (e.g. the battery is bent out of shape after being dropped), or any unusual smells emanating from the notebook battery, shut your computer down immediately and contact your service center. If the battery has been dropped we do not recommend using it any further, as even if the computer continues to work with a damaged battery in place, it may cause circuit damage, which may possibly result in fire. It is recommended that you replace your computer battery every two years.

## Battery FAQ

### How do I completely discharge the battery?

Use the computer with battery power until it shuts down due to a low battery. Don't turn off the computer by yourself even when you see a message that indicates the battery is critically low, just let the computer use up all of the battery power and shut down on its own. Disable the **Power Options** functions in the **Control Panel**, especially any **Alarms** (**unlick** the tickboxes - see page [D - 24](#)) and **Schemes** (change all the settings to **Never** - see page [D - 19](#)). As the battery nears the end of its life save and close any critical files.

### How do I fully charge the battery?

When charging the battery, don't stop until the LED charging indicator light changes from orange to green.

### How do I maintain the battery?

Completely discharge and charge the battery at least once every 30 days or after about 20 partial discharges.



#### Caution

Danger of explosion if battery is incorrectly replaced.

Replace only with the same or equivalent type recommended by the manufacturer. Discard used battery according to the manufacturer's instructions.

# Driver Installation

Insert the *Device Drivers & Utilities + User's Manual* disc, click *Install Drivers/Option Drivers* (button) and then click the appropriate driver name from the *Drivers Installer* menu. Follow the instructions to install the driver.



Figure D - 17 - Drivers Installer Screen 1

1. Check the driver installation order from *Table D - 3* (the **drivers must be installed in this order**) which is the same as that listed in the *Drivers Installer* menu below.
2. Click to select the driver you wish to install, after installing each driver it will become greyed out (if you need to reinstall any driver, click the **Unlock** button).
3. Follow the instructions for each individual driver installation procedure as listed on the following pages.



Figure D - 18 - Drivers Installer Screen 2

WinXP SP3 Driver	Page #
<i>Chipset</i>	<i>Page D - 30</i>
<i>Video</i>	<i>Page D - 30</i>
<i>LAN</i>	<i>Page D - 30</i>
<i>CardReader</i>	<i>Page D - 30</i>
<i>Touchpad</i>	<i>Page D - 31</i>
<i>Trusted Platform Module (TPM)</i>	<i>Page D - 31</i>
<i>Hot Key Utility</i>	<i>Page D - 31</i>
<i>PC Camera (Optional)</i>	<i>Page D - 31</i>
<i>Wireless LAN Module (Optional)</i>	<i>Page D - 32</i>
<i>Audio</i>	<i>Page D - 33</i>
<i>Fingerprint Reader Module</i>	<i>Page D - 47</i>
<i>3.75G/HSPA Module</i>	<i>Page D - 64</i> <i>Page D - 65</i> <i>Page D - 66</i>

Table D - 3 - Driver Installation

## Updating/Reinstalling Individual Drivers

If you wish to update/reinstall individual drivers it may be necessary to uninstall the original driver. To do this go to the **Control Panel** in the *Windows OS* and double-click the **Add/Remove Programs** item. **If you see the individual driver listed** (if not see below), uninstall it, following the on screen prompts (it may be necessary to restart the computer). Go to the appropriate section of the manual to complete the update/reinstall procedure for the driver in question.

If the driver is not listed in the **Add/Remove Programs** item:

1. Click **Start** (menu), point to **Settings** and click **Control Panel** (or click **Start > Control Panel**).
2. Double-click **System** (icon); System (icon) is in **Performance and Maintenance** (category).
3. Click **Hardware** (tab) > **Device Manager** (button).
4. Double-click the **device** you wish to update/reinstall the driver for (you may need to click "+").
5. Look for the **Update Driver** button (check the **Driver** tab) and follow the on screen prompts.

### Driver Installation Procedure

Insert the *Device Drivers & Utilities + User's Manual* disc and click **Install Drivers** (button), or **Option Drivers** (button) to access the optional driver menu.



#### Windows XP Service Pack 3

Make sure you install **Windows XP Service Pack 3** (or a Windows XP version which includes Service Pack 3) **before installing any drivers.**



#### Driver Installation General Guidelines

The driver installation procedures outlined in this Chapter are accurate at the time of going to press.

Drivers are always subject to upgrade and revision so the exact procedure for certain drivers may differ slightly. As a general guide follow the default on screen instructions for each driver (e.g. **Next > Next > Finish**) unless you are an advanced user. In many cases a restart is required to install the driver.

### Chipset

1. Click **1.Install Chipset Driver > Yes.**
2. Click **Next > Yes > Next > Next.**
3. Click **Finish** to restart the computer.

### Video

1. Click **2.Install Video Driver > Yes.**
2. Click **Next > Yes > Next > Next.**
3. Click **Finish** to restart the computer.

### LAN

1. Click **3.Install LAN Driver > Yes.**
2. Click **Next > Install.**
3. Click **Finish.**
4. The network settings can now be configured.

### CardReader

1. Click **4.Install Card Reader Driver > Yes.**
2. Click **Install > Finish.**

## Touchpad

1. Click **5.Install Touchpad Driver** > **Yes**.
2. Click **Next** > **Next** > **Next**.
3. Click **Finish** to restart the computer.

## Trusted Platform Module (TPM)

Before installing the Trusted Platform Module driver you should enable the TPM State in the BIOS (see *“Security Menu” on page 5 - 11* and see *“Trusted Platform Module” on page D - 41* for full details.

1. Click **6.Install TPM Driver** > **Yes**.
2. Click **Install** > **Next**.
3. Click the button to accept the license and click **Next**.
4. Click **Next** > **Next** > **Install**.
5. Click **Finish** > **Yes** to restart the computer.

## Hot Key Utility

1. Click **7.Install Hotkey Utility** > **Yes**.
2. Click **Next** > **Install**.
3. Click **Finish** > **Finish** to restart the computer.

## PC Camera (Optional)

Before installing the **PC Camera** driver, make sure that the optional PC Camera is on. Use the **Fn + F10** key combination to power the camera on.

1. Click **8.Webcam** > **Yes**.
2. Choose the language you prefer and click **Next** > **Next**.
3. Click **Finish** to restart the computer.
4. See *“PC Camera Module” on page D - 53* for details.

### Wireless LAN Module (Optional)

If you have included an **Intel® Wi-Fi Link 5100/5300 Series (802.11 a/g/n) or 802.11b/g WLAN** module in your purchase option, use the **Fn + F11** key combination to toggle power to the module. Your installation procedure will be dependent upon which WLAN module is included in your purchase option. See *“WLAN Module” on page D - 59* for details.

### Intel Wireless LAN Module

1. Click **9.Wireless Lan > Yes (if SP3 is installed go straight to step 9)**.
2. Click **Next > Next** to link to the required prerequisites on the Internet.
3. Click **Download** (button) to download the **Windows Installer** executable (.exe) file to the computer's hard disk.
4. Double-click (or click the **Run** button) to install the **Windows Installer** file and follow the on-screen instructions for file installation.
5. You will be required to restart the computer to complete the file installation.

6. Repeat steps **1** to **4** to get to the appropriate download location.
7. Click **Download** (button) to download the **Microsoft MSXML** file to the computer's hard disk (if you are unsure of which file to download for you processor you can click **Run** instead of acknowledging the file, and you will be informed if the file is appropriate or not).
8. Follow the on-screen instructions for file installation.
9. After the files have been installed click **Next > Next**.
10. Click the button to accept the license and click **Next > Next > Next**.
11. Click **Finish** to complete the installation.

### 802.11b/g WLAN Driver Installation

1. Click **9.Wireless Lan > Yes**.
2. Choose the language you prefer and click **Next**.
3. Click **Next > Install**.
4. Click **Finish** to complete the installation.

## Audio

1. Click **10.Install Audio Driver > Yes**.
2. Click **Next**.
3. Click **Finish** to restart the computer.

Note that after installing the audio driver the system will not return to the **Drivers Installer** screen. To install any of the optional drivers listed overleaf, eject the *Device Drivers & Utilities + User's Manual* disc and then reinsert it (or double-click the disc icon in My Computer), and click **Option Drivers** (button) to access the optional driver menu.

## Module Drivers

See the following pages for the driver installation procedures for any of the optional modules included in your purchase configuration.



Figure D - 19 - Drivers Installer Screen 2

## Windows XP Information

### Bluetooth Module

**Note:** The operating system is the default setting for **Bluetooth** control in *Windows XP*, and does not require a driver. See *“Bluetooth Module” on page D - 35* for configuration instructions.

### Fingerprint Reader Module

See *“Fingerprint Reader Driver Installation” on page D - 47*.

### 3.75G Module

See *“3.75G/HSPA Module” on page D - 62*.

## Wireless LAN, Bluetooth & 3.75G Modules



### Wireless Device Operation Aboard Aircraft

The use of any portable electronic transmission devices aboard aircraft is usually prohibited. Make sure the module(s) are **OFF** if you are using the computer aboard aircraft.



### Wireless LAN, Bluetooth & 3.75G Modules Power Toggle

Enable power to the modules as follows:

Fn + F11 = Wireless LAN Module Power Toggle

Fn + F12 = Bluetooth Module Power Toggle

Fn +  = 3.75G Module Power Toggle

The LED indicator  will be **green** if the WLAN module is on, and **orange** if the Bluetooth module is on.

## Bluetooth Module

The operating system's **Bluetooth Devices** control panel is used to configure the Bluetooth settings in *Windows XP*, and therefore does not require a driver. Use the **Fn + F12** key combination (see "*Function Keys & Visual Indicators*" on page D - 5).



### Bluetooth Data Transfer

Note that transferring data between the computer and a Bluetooth enabled device is supported **in one direction only (simultaneous data transfer is not supported)**.

Therefore if you are copying a file from your computer to a Bluetooth enabled device, you will not be able to copy a file from the Bluetooth enabled device to your computer until the file transfer process from the computer has been completed.



### Wireless Device Operation Aboard Aircraft

The use of any portable electronic transmission devices aboard aircraft is usually prohibited. Make sure the module(s) are OFF if you are using the computer aboard aircraft.


Use the **Fn + F12** key combination to toggle power to the Bluetooth module, and check the LED indicator to see if the module is powered on or not (see [Table D - 2](#), on page D - 5/ [Table](#), on page 1 - 9).

*Figure D - 20*  
**Local Area  
Connection**

### Bluetooth Local Area Connection Icon

If you want to display the Local Area Connection icon for the Bluetooth connection in the taskbar, set it up as follows:

1. Access the **Network Connections** control panel in **Windows (Start > Settings > Network Connections OR Start > Connect To > Show all Connections)** or by clicking the taskbar icon .
2. Right-click the Bluetooth connection icon, and select **Properties**.
3. Click to put a tick (if none is present) in the **“Show icon in the notification area when connected”** box and click **OK**.
4. Close the control panels and the icon  for the Bluetooth local area connection will be displayed in the taskbar **when connected** (see sidebar and overleaf).




## Bluetooth Configuration in Windows XP

### Setup your Bluetooth Device so the Computer Can Find it

1. Turn your Bluetooth device (e.g. PDA, mobile phone etc.) on.
2. Make the device discoverable (to do this check your device documentation).

### To Turn the Bluetooth Module On

1. Press the **Fn + F12** key combination to power on the Bluetooth module.
2. A Bluetooth icon  will appear in the taskbar (see sidebar).
3. You can then do any of the following to access the **Bluetooth Devices** control panel.
  - **Double-click** the icon  to access the **Bluetooth Devices** control panel.
  - Click **Start**, and click **Control Panel** (or point to **Settings** and click **Control Panel**), and then click **Bluetooth Devices (Network and Internet Connections)**.
  - **Click/Right-click** the icon  and choose an option from the menu.



### Bluetooth Taskbar Icon

If you cannot see the Bluetooth icon in the taskbar, access the **Bluetooth Devices** control panel. Click **Options** (tab), and make sure that **Show Bluetooth icon in the notification area** check box has a tick inside it.

Note that you will need to check the LED indicator to see if the module is powered on or not.

*Figure D - 21*  
Bluetooth Devices &  
Click Icon Menu

### To Add a Bluetooth Device

1. Access the Bluetooth Devices control panel.
2. Click **Options** (tab), and make sure that **Allow Bluetooth devices to connect to this computer** check box (**Connections**) has a tick inside it.
3. Click **Devices** (tab), and then click **Add**.
4. The **Add Bluetooth Device Wizard** will appear.
5. Click to select “**My device is set up and ready to be found**”, and then click **Next**.

Figure D - 22  
Add Bluetooth  
Device Wizard



#### Passkey Options

You can allow the system to choose a passkey for you. You will then be prompted to enter the generated passkey on your Bluetooth device.



6. The **Wizard** will then search for any available Bluetooth devices within range.
7. Click to select the device you want to communicate with, and click **Next**.
8. Select an appropriate passkey option and click **Next**.



9. Click **Finish**.

Figure D - 23  
Passkey Option

## To Change Settings for the Bluetooth Device

1. Access the **Bluetooth Devices** control panel.
2. Click on the device you want to change and click **Properties** to:
  - Change the **name** of the device (click **General**, type a new name and click **OK**).
  - Enable/Disable a **service** (click **Services**, clear/tick the check box next to the service and click **OK**).

## To Make your Computer Discoverable to Bluetooth Devices

1. Access the **Bluetooth Devices** control panel.
2. Click **Options**, and make sure that **Turn discovery on** check box (**Discovery**) has a tick inside it.
3. Make sure that **Alert me when a new Bluetooth device wants to connect** check box (**Connections**) has a tick inside it, if you want to be notified when a Bluetooth device wants to connect.



*Figure D - 24*  
**Bluetooth Devices  
Options**



### Password Warning

If you set passwords for any of the security modules, **NEVER** forget your password.

The consequences of this could be serious. If you cannot remember your boot password you must contact your vendor and you may lose all of the information on your hard disk.

## Security Modules (TPM & Fingerprint)

The encrypted channel between the **Trusted Platform Module security chip** and the **optional fingerprint reader** with **Protector Suite Software** provides a high level of security for your computer. A further level of security and control is provided in the BIOS (see *“Security Menu” on page 5 - 11* and *“TPM State” on page 5 - 14*). Make sure you install the TPM (see *“Trusted Platform Module (TPM)” on page D - 31*) and fingerprint reader (see *“Fingerprint Reader Module” on page D - 34*) drivers.

The **fingerprint reader** and **Protector Suite Software** allow you to:

- Access or Lock your computer
- Protect sensitive files
- Display and file your favorite web pages
- Fill in frequently used dialogs
- Run your favorite applications

The **TPM security chip** allows you to create and manage digital certificates for user and platform authentication. This type of security is usually administered within large enterprises and organizations, and therefore requires implementation by a system administrator before users can access security features.

Individual users can use the TPM as an authentication with the fingerprint reader.

# Trusted Platform Module

Before setting up the TPM functions you must initialize the security platform.

## Enabling & Activating TPM

1. Restart the computer.
2. Enter the **PhoenixBIOS Setup Utility** by pressing **F2** during the **POST**.
3. Use the arrow keys to select the **Security** menu.
4. Select **TPM Support** and set the item to **Enabled**.
5. The **TPM State** menu will then appear.





Figure D - 25  
TPM Support

## Windows XP Information

6. Use the arrow keys to select the **TPM State** menu.
7. Select **TPM State**, and set the item to **Enable & Activate**.

Figure D - 26  
TPM State



8. Press **F10** to save the changed BIOS information, exit the BIOS and restart the computer.
9. If you make any changes to the TPM State you will be asked to **Execute/Reject** the change after restart (*"Physical Presence Operations" on page 5 - 15*).
10. You can now **install the TPM driver** (see *"Trusted Platform Module (TPM)" on page D - 31*).

## Initializing TPM

1. To initialize the TPM it may be necessary to first clear any existing TPM information if applicable.
2. Enter the **PhoenixBIOS Setup Utility** by pressing **F2** during the **POST**.
3. Use the arrow keys to select the **TPM State** menu.
4. Select **TPM State**, and set the item to **Clear**.




Figure D - 27  
TPM State - Clear


5. Press **F10** to save the changed BIOS information, exit the BIOS and restart the computer.
6. If you make any changes to the TPM State you will be asked to **Execute/Reject** the change after restart (*"Physical Presence Operations" on page 5 - 13*).

7. Run the application from the **Infineon Security Platform Solution > Manage Security Platform** item in the **Start > Programs/All Programs** menu.
8. Click **User Settings** (tab) and click **Yes** (or click the **Security Platform State** taskbar bubble).
9. The **Quick Initialization** method will automatically be selected for you (if you need to use advanced settings provided by your network administrator then select **Advanced Initialization**)
10. You will need to use a removable media (e.g. a USB Flash Drive) to store passwords and data (keep the media in a safe place until required).
11. Select the drive you want to use from the drop-down menu and click **Next**.

*Figure D - 28*  
**Security Platform  
Quick Initialization  
Wizard**



12. Click **Next**.
13. Choose the **Security Platform Features** you want to use by clicking the appropriate tickbox.
14. Enter a **Basic User Password** (and re-type to confirm it) and click **Next**.



15. Click **Next** to confirm the settings.
16. The computer will then initialize the settings.
17. Click **Finish**.
18. Click the tabs and control panels to adjust the settings.
19. Double-click the taskbar icon  to access the **Infineon Security Platform Settings Tool**, or right-click the taskbar icon  and select a menu item.



### Help

Right-click the taskbar icon  to bring up the menu to select **Help** or **How to use the Security Platform Features**.

*Figure D - 29*  
**Settings**




### Help

Right-click the taskbar icon  to bring up the menu to select **Help** or **How to use the Security Platform Features**.

*Figure D - 30*  
**Infinion Security Platform Settings Tool**

## Infinion Security Platform Settings Tool

The Infinion Security Platform Settings Tool allows you to manage and check the TPM state, manage your password information, and to backup and restore the TPM data. As TPM is usually administered within large enterprises and organizations, your system administrator will need to assist you in managing the information here.



## Fingerprint Reader Module

If you have included the fingerprint reader in your purchase option you will need to install the driver as per the instructions below.

Make sure you have administrator's rights to your computer, and have a *Windows* password enabled for full security protection.

Before beginning the enrollment process it is recommended that you go through the fingerprint tutorial. To run the tutorial click **Start > Programs/All Programs > Protector Suite QL > Fingerprint Tutorial** after installing the driver.

### Fingerprint Reader Driver Installation

1. Insert the *Device Drivers & Utilities + User's Manual* disc into the CD/DVD drive.
2. Click **Option Drivers** (button).
3. Click **1.FingerPrint > Yes**.
4. Click **Software Installation**.
5. Click **Next > Next > Next**.
6. Click **Finish > Yes** to restart the computer.



#### Help & Manual

Right-click the taskbar icon  to bring up the menu to select **Help**.

Insert the *Device Drivers & Utilities + User's Manual* disc and click **Option Drivers** (button). Click **Unlock** (button) and then click **4.Install Fingerprint Driver > Yes**.

Click **Documentation** to open the folder containing the manual in .pdf format.

To install the Adobe Acrobat Reader software to read the file, insert the *Device Drivers & Utilities + User's Manual* disc and click **User's Manual** (button), and click **Install Acrobat Reader** (button).

## Windows XP Information

### User Enrollment

1. Click **Start > Programs/All Programs > Protector Suite QL > User Enrollment**, or double click the taskbar icon  (click **Start fingerprint enrollment**).
2. On the first run of the program you will be asked to click the button to accept the license, and then click **OK**.
3. Click **Next** (the enrollment method will automatically be configured), and then click **Finish**.
4. You will then be prompted to enter your **Windows** password (or you will need to set a Windows password if you have not configured one) and click **Next**.
5. Select either to use the fingerprint reader alone for authentication, or choose both the fingerprint reader and the **Windows** password, and then click **Next**.
6. Click **Next > Next** (if you have the "**Run interactive tutorial**" tickbox selected you will run through the Fingerprint Tutorial).
7. Click **Next** for each window of the tutorial (you can click the button to "**skip tutorial**" at any time).
8. Click the button above any of the fingers to begin the enrollment process for that finger.





Figure D - 31 - Fingerprint Enrollment

9. Swipe the finger **five** times to enroll that finger.

10. Repeat the process for all the fingers you wish to enroll (see sidebar), and then click **Next > Finish**.
11. Click **“Help”** in the **Fingerprint Control Center** to get more information on any topic.
12. You can also run the **Tutorial**, or **Introduction** (to run the product tour video) to get more information.
13. Right-click the taskbar icon  to bring up the **Control Center** that allows you to **Edit Fingerprints, register applications, manage Password Bank, File Safe** and access the **Help** menu etc. You can also run the **Control Center** etc. from the **Protector Suite QL** item in the **Programs/All Programs** menu.




*Figure D - 32 - Control Center & Biomenu*

14. See **“Help & Manual” on page D - 47** for further details.
15. If you swipe your finger over the reader at any time you can access the **Biomenu** to **lock the computer, register websites, access the Personal Safe** open the **Control Center** and access the **Help** menu.

### Protector Suite TPM Initialization

1. Click **Start > Programs/All Programs > Protector Suite > Control Center**, or double click the taskbar icon .
2. Click **System Settings** and click **TPM (Tab)**.

*Figure D - 33*  
**Protector Suite TPM  
Initialization &  
Multifactor**



3. Click **Initialize TPM**.
4. Click **Next > Finish**.
5. Click **OK** to close the **System Settings** control panel.

6. Click **Enroll or Edit Fingerprints** and then click **Next**.
7. Enter the password or swipe a finger and click **Next**.
8. Select the **Authentication Factors** in **Multifactor** to configure fingerprint authentication along with TPM.
9. Enter a password and retype it to confirm it and then click **Next**.
10. Click **Next > Next > Finish**.



*Figure D - 34*  
**Protector Suite TPM  
Initialization &  
Multifactor**

### Fingerprint Control Center Features

#### Application Launcher

The **Application Launcher** allows you to register applications to be launched when assigned to a particular finger. Simply copy the application icon on to one of the registered fingers and then click OK to close the application window. Once registered the application will launch when you swipe the appropriate finger across the sensor.

#### Password Bank

The **Password Bank** stores registrations of user names, passwords and other settings for web sites etc.

#### File Safe

**File Safe** is an encrypted area assigned on your hard drive that allows you to store files and folders to be protected by fingerprint protection.

For more information on these and other features simply access “**Help**” in the **Fingerprint Control Center** and select the item from the menu on the left.

## PC Camera Module

Before installing the optional **PC Camera** module driver use the **Fn + F10** key combination (see *“Function Keys & Visual Indicators” on page D - 5*) to toggle power to the PC Camera module. The PC Camera module uses the **BisonCap** application to capture video files.

Make sure you install the PC Camera driver (see *“PC Camera (Optional)” on page D - 31*). Run the **BisonCap** application program from the **BisonCam** shortcut on the desktop, or from the **BisonCam** item in the **Start > Programs/All Programs** menu (if the hardware is turned off use the **Fn + F10** key combination to turn it on again).



### Taking Still Pictures

Double-click the **My Computer** icon on the desktop, or go the **Start** menu and point to **My Computer**, then click it.

Double-click the camera icon. Click **Take a new picture** in the **Camera Tasks** box.



## Windows XP Information

### PC Camera Audio Setup

If you wish to capture video & **audio** with your camera, it is necessary to setup the audio recording options in *Windows*.

1. Go to the **Start** menu and point to **Settings** (or just click **Control Panel**) and click **Control Panel**, then double-click the **Sounds & Audio Devices** icon (**Sounds, Speech, and Audio Devices** in Category View).
2. Click **Advanced** in the **Volume > Device volume** tab.
3. Click **Options** and scroll down and click **Properties**.
4. Select **Realtek HD Audio Input** from the **Mixer device** menu.
5. Make sure the **Mic Volume** (check box) is checked, then click **OK**.
6. Boost the volume in the (**Mic Volume**) section (in the Recording Control menu) as high as it will go.
7. Close the **Recording Control** window, and then click **OK**.
8. Run the **BisonCap** application program from the **Start > Programs/All Programs > BisonCam** menu.
9. Go to the **Devices** menu heading and select **Realtek HD Audio Input** (it should have a tick alongside it).
10. Go to the **Capture** menu heading and select **Capture Audio** (it should have a tick alongside it).

## BisonCap

**BisonCap** is a video viewer for general purpose video viewing and testing, and for capturing video files to .avi format.

1. Run the **BisonCap** application from the **Start > Programs/All Programs > Bison-Cam** menu (it is recommended that you **set the capture file** before the capture process - **see Set Capture File below**).
2. Go to the **Capture** menu heading (if you wish to capture audio check **“PC Camera Audio Setup” on page D - 53**) and select **Start Capture**.
3. Click **OK** (the file location will be displayed in the pop-up box) to start capturing the video, and press **Esc** to stop the capture (you can view the file using the **Windows Media Player**).

## Set Capture File

Prior to capturing video files you may select the **Set Capture File...** option in the **File** menu, and set the file name and location before capture (this will help avoid accidentally overwriting files). Set the name and location then click **Open**, then set the **“Capture file size:”** and click **OK**. You can then start the capture process as above.

**Note the important information in “Reducing Video File Size” on page D - 56 in order to save file space, and help prevent system problems.**



### Pre-Allocating File Space

You may pre-allocate the file size (**File > Allocate File Space**) for the capture file in the **BisonCap** program.

Pre-allocating space on the hard disk can improve the capture quality (particularly of large capture files), by reducing the amount of work the hard disk has to do in finding space for the video data as it is being captured.

See also **“Reducing Video File Size” on page D - 56**.

## Windows XP Information

### Reducing Video File Size

Note that capturing high resolution video files requires a substantial amount of disk space for each file. After recording video, check the video file size (right-click the file and select **Properties**) and the remaining free space on your hard disk (go to **My Computer**, right-click the hard disk, and select **Properties**) If necessary you can remove the recorded video file to a removable medium e.g. CD, DVD or USB Flash drive.

Note that the *Windows XP* system requires a minimum of **1.5GB** of free space on the **C: drive** system partition. In order to prevent system problems it is recommended that you save the captured video file to a location other than the **C: drive** (see *“Set Capture File” on page D - 55*), limit the file size of the captured video (see *“Pre-Allocating File Space” on page D - 55*) or reduce video resolution (see below).


### To Reduce Video Resolution Output Size:

1. Run the **BisonCap** program.
2. Go to **Options** and scroll down to select **Video Capture Pin...**
3. Click the **Output Size** drop box and select a lower resolution size in order to reduce the captured file size.

## Eliminating Screen Flicker

If you find that the video screen in the **BisonCap** program is flickering, you can try to adjust the setting in the **Video Capture Filter** options.

1. Run the **BisonCap** program.
2. Go to **Options** and scroll down to select **Video Capture Filter....**
3. Click either **50Hz** or **60Hz** under **Frequency** in **Property Page** (tab).




*Figure D - 35*  
Video Capture Filter

### Zoom

The **BisonCap** program allows you to zoom the camera in and out.

1. Run the **BisonCap** program.
2. Go to **Zoom** and select **Zoom Out/Zoom In**.



*Figure D - 36*  
**Zoom/Setting**



### Snapshot Folder

The Snapshot folder's default location is on the desktop. Do not move this folder or an error may appear when you try to take a still picture.

If you accidentally delete or move the folder, you can create a new Snapshot folder on the desktop in order to capture the files.

### Taking Still Pictures

The **BisonCap** program allows you to take still pictures.

1. Run the **BisonCap** program.
2. Go to **Options/Capture** and select **Take Picture/Snapshot**.
3. The picture (in JPEG format) will be placed in the **Snapshot** folder  on the desktop.

## WLAN Module

If you have included an **Intel® Wi-Fi Link 5100/5300 Series (802.11 a/g/n) or 802.11b/g WLAN** module in your purchase option, use the **Fn + F11** key combination to toggle power to the module. Your installation procedure will be dependent upon which WLAN module is included in your purchase option.



### Download Prerequisite Files (Intel WLAN modules if Service Pack 3 is not installed)

Make sure you install **Windows XP Service Pack 3** (or a Windows XP version which includes Service Pack 3) **before installing the Intel WLAN driver**. If you DO NOT have Service Pack 3 installed then **make sure you have a working internet connection** before beginning the driver installation process for *Windows XP*.

You will be pointed to download the required **Windows Installer 3.1** and **Microsoft MSXML 6.0** files, as part of the installation procedure overleaf. This information applies to Intel WLAN modules only.

Make sure you install the appropriate Wireless LAN driver (see *“Intel Wireless LAN Module” on page D - 32* or *“802.11b/g WLAN Driver Installation” on page D - 32*).

## Windows XP Information

### Intel WLAN Configuration

1. Configure the settings by going to the **Intel PROSet Wireless WiFi Connection Utility (Start > Programs/All Programs > Intel PROSet Wireless WiFi Connection Utility)**, or by double-clicking the taskbar icon .
2. Click to select any available network, and click **Connect** to establish a connection.
3. If you do not see your Wireless Access Point click **Refresh** (button).
4. Click **Help** (link) to bring up the **Help** Menu.
5. Make sure that the **WiFi On** button is selected.





Figure D - 37 - Intel PROSet Wireless WiFi Connection Utility

## 802.11b/g WLAN Configuration

1. The operating system is the default setting for Wireless LAN control in **Windows XP**.
2. Access any available wireless networks from **Network Connections > Wireless Network Connection** menu in **Windows**, or click the icon   in the taskbar, and click **View Wireless Connections**.



### Network Connection

Use the **Windows Network Connections** control panel to access available wireless networks (**Start > Settings > Network Connections** or **Start > Connect To > Show all Connections**).

*Figure D - 38*  
**Wireless Network Control Panels**



### 3.75G/HSPA Module Options

There are **three optional** 3.75G/HSPA modules available for this series of computer models. Each module is supplied with the appropriate application software.

The module type supplied may depend upon the computer model purchased. Check with your service center for details.

Install the driver from the Drivers Installer menu and check the instructions for the appropriate application on the following pages.

## 3.75G/HSPA Module

If you have included an optional **3.75G/HSPA module** in your purchase option follow the instructions [on page 7 - 46](#) to install the USIM card (which will be provided by your service provider), and then install the application.

Before installing the application, make sure that the 3.75G/HSPA module is on. Use the **Fn +  key combination** (see [“Function Keys & Visual Indicators” on page D - 5](#)) to **toggle power to the 3.75G/HSPA module**.



### Important Notice - 3.75G/HSPA & Bluetooth/Wireless LAN Modules

In order to comply with FCC regulations you should NOT operate the 3.75G/HSPA module and the Bluetooth/Wireless LAN modules at the same time as this may disrupt radio frequency, and cause interference. When the 3.75G/HSPA module is powered on, make sure that the Bluetooth/Wireless LAN modules are powered off.

### Wireless Device Operation Aboard Aircraft

The use of any portable electronic transmission devices aboard aircraft is usually prohibited. Make sure the module(s) are OFF if you are using the computer aboard aircraft.

Use the **Fn +  key combination** to toggle power to the HSPA modem module, and check the indicator to see if the module is powered on or not (see [Table D - 2, on page D - 5 / Table , on page 1 - 9](#)).

**Before installing the application, make sure that the 3.75G/HSPA module is ON** (installing the driver with the module off will not allow the software to detect the module hardware correctly). Use the **Fn + ** key combination (see *“Function Keys & Visual Indicators” on page D - 5*) to toggle power to the 3.75G/HSPA module. When the 3.75G/HSPA module is powered on, the indicator  will briefly be displayed. Make sure you install the drivers in the order indicated in *Table D - 3, on page D - 29*. **Note that exiting the application does NOT turn off the 3.75G/HSPA module.**

- **3G Watcher** - See *“3G Watcher Application Installation” on page D - 64* for driver installation information and *“Setting Up a Carrier Profile” on page 7 - 49* for instructions on using the **3G Watcher** application.
- **HSPA Modem Interface** - See *“HSPA Modem Interface Installation” on page D - 65* for driver installation information and *“HSPA Modem Interface” on page 7 - 56* for instructions on using the **HSPA Modem Interface**.
- **Mobile Partner** - See *“Mobile Partner Application Installation” on page D - 66* for driver installation information and *“Mobile Partner Application” on page 7 - 65* for instructions on using the **Mobile Partner** application.



### 3.75G/HSPA Modules & System Wake Up

Note that the 3.75G modules **DO NOT** support system wake up on 3.75G/HSPA modem activity.

### 3G Watcher Application Installation

1. Enable power to the module by pressing the **Fn** +  key combination (the on screen icon  will indicate the module's power status).
2. If a *Found New Hardware* window appears, click **Cancel**.
3. Insert the *Device Drivers & Utilities + User's Manual* disc into the CD/DVD drive.
4. Click **Option Drivers** (button).
5. Click **2.3.5G Generation Module > Yes**, and then click **Next**.
6. Click the button to accept the license agreement, and then click **Install**.
7. When the next screen appears **wait (for about 2 minutes) until you see** the message bubble "**Found New Hardware**" in the taskbar **disappear** before clicking **Finish** (this allows the hardware to detect the 3.75G module).
8. Access the **3G Watcher** application from the **Start** menu (**Start > Programs/All Programs > Sierra Wireless > 3G Watcher**), or by double-clicking the desktop icon .

## HSPA Modem Interface Installation

1. Enable power to the module by pressing the **Fn** +  key combination (the on screen icon  will indicate the module's power status).
2. If a *Found New Hardware* window appears, click **Cancel**.
3. Insert the *Device Drivers & Utilities + User's Manual* disc into the CD/DVD drive.
4. Click **Option Drivers** (button).
5. Click **2.3.5G Generation Module** > **Yes**, and then click **Next**.
6. Click **Next** > **Install** > **Finish**.
7. Access the **HSPA modem** interface from the **Start** menu (**Start** > **Programs/All Programs** > **HSPA modem**), or by double-clicking the **HSPA modem** icon on the desktop.

### Mobile Partner Application Installation

1. Enable power to the module by pressing the **Fn** +  key combination (the on screen icon  will indicate the module's power status).
2. If a *Found New Hardware* window appears, click **Cancel**.
3. Insert the *Device Drivers & Utilities + User's Manual* disc into the CD/DVD drive.
4. Click **Option Drivers** (button).
5. Click **2.3.5G Generation Module > Yes**.
6. Choose the language you prefer and click **OK**.
7. Click **I Agree** (button) to accept the license agreement.
8. Click **Next > Install**.
9. Click **Finish** to restart the computer.
10. Access the **Mobile Partner** application from the **Start** menu (**Start > Programs/All Programs > Mobile Partner**), or by double-clicking the **Mobile Partner** icon on the desktop.
11. See *“Mobile Partner Application” on page 7 - 35* for instructions on using the **Mobile Partner** application.